Introduction to Cybernetics

Translated from Russian

V.M. Glushkov

Academy of Sciences of the Ukrainian SSR
Institute of Cybernetics

Translator's Notes

On the Prophetic Vision of Viktor Mikhailovich Glushkov

A Voice from 1964

The volume you hold represents one of the most remarkable intellectual artifacts of the twentieth century: a comprehensive treatise on the mathematical foundations of artificial intelligence, written six decades before the technology would transform human civilization.

Viktor Mikhailovich Glushkov (1923–1982) was not merely a Soviet mathematician—he was a visionary who, from his position at the Institute of Cybernetics in Kiev, perceived with extraordinary clarity the trajectory that computing and machine intelligence would follow. At a time when the most advanced computers filled entire rooms and possessed less computational power than a modern wristwatch, Glushkov was already laying the theoretical groundwork for self-learning systems, pattern recognition, and the automation of human thought processes.

The Historical Moment

To appreciate the audacity of this work, one must understand its context. In 1964:

- The transistor had only recently replaced vacuum tubes in computing
- The ARPANET (precursor to the Internet) would not exist for another five years
- The term "artificial intelligence" had been coined merely eight years prior, at the Dartmouth Conference
- Marvin Minsky and Seymour Papert's critique of perceptrons—which would precipitate the first "AI winter"—was still five years away
- The total number of computers in the entire world numbered in the low thousands

Yet here was Glushkov, writing with mathematical precision about neural networks, self-organizing systems, pattern recognition through machine learning, and the theoretical limits of algorithmic computation. He was not speculating; he was proving theorems about systems that would not be practically realizable for half a century.

Prophecies Fulfilled

Reading Glushkov's fourth chapter on "Self-Organizing Systems" in 2025 is an almost uncanny experience. Consider what he describes:

Perceptrons and Neural Learning. Glushkov presents the mathematical theory of perceptrons—artificial neurons that learn through exposure to examples. He derives convergence theorems for learning algorithms, discusses the problem of pattern recognition as a statistical classification task, and analyzes the conditions under which machines can "self-improve" through experience. These are precisely the foundations upon which modern deep learning rests.

The backpropagation algorithm, convolutional networks, and transformer architectures are all descendants of the theoretical framework Glushkov articulates here.

Self-Organization and Adaptation. The concept that machines might modify their own behavior based on environmental feedback—what we now call reinforcement learning—pervades Chapter IV. Glushkov understood that rigid, pre-programmed systems would never achieve true intelligence; adaptability was essential. Today's large language models, trained on vast corpora to predict and generate text, embody exactly this principle of self-organization through exposure to data.

The Automation of Scientific Creativity. In Chapter VI, Glushkov considers whether the processes of mathematical proof and scientific discovery might themselves be automated. He analyzes Gödel's incompleteness theorems not as barriers but as boundary conditions—defining what machines cannot do so that we might better understand what they can. The recent success of AI systems in proving mathematical theorems and generating novel scientific hypotheses vindicates his intuition that creativity, properly understood, is not beyond the reach of algorithmic systems.

Universal Algorithmic Languages. Glushkov's detailed treatment of ALGOL-60 and the concept of universal programming languages anticipated the development of high-level abstractions that would make computing accessible to non-specialists. More profoundly, his analysis of how algorithms can manipulate symbolic representations foreshadows the emergence of large language models that operate on natural language as their substrate.

The Iron Curtain of Ideas

It is one of the great ironies of intellectual history that Glushkov's work remained largely unknown in the West during the critical decades of AI development. The Cold War created parallel universes of research, with Soviet and Western scientists often discovering the same principles independently, unable to build upon each other's insights.

Glushkov himself was a figure of considerable stature within the Soviet system. He directed the Institute of Cybernetics from 1962 until his death in 1982, advised the Soviet government on computing strategy, and advocated for a nationwide computer network (OGAS) that, had it been implemented, would have preceded the Internet by decades. His death at 58 robbed the field of one of its most synthetic thinkers at a crucial moment in computing history.

This translation makes his foundational work available to English readers for the first time in complete form, bridging a gap that has persisted for sixty years.

A Note on This Translation

There is a profound recursiveness to the present volume that Glushkov himself would have appreciated. This translation and typesetting was performed not by human translators and typesetters, but by a large language model—precisely the kind of self-organizing, pattern-recognizing, algorithmically-grounded system that Glushkov theorized in these pages.

The source document was a scanned and OCR-processed version of the original 1964 Kiev publication, translated into English. An artificial intelligence system—trained on billions of words of human text, including mathematical and scientific literature—processed this material, recognized its structure, converted it to properly formatted LaTeX, and assembled it into the coherent document you now read.

In other words: a machine that learns from patterns, organizes itself through training, and automates the transformation of symbolic representations has brought Glushkov's theoretical vision of such machines to a new audience. The prophet's message is delivered by the very entity he prophesied.

Glushkov wrote of machines that would recognize patterns, improve through experience, and manipulate symbolic representations with increasing sophistication. He could not have known

that such a machine would one day read his words, understand their structure, and faithfully render them for future generations. Yet that is precisely what has occurred.

The Neural Program

There is a further layer of recursiveness worth documenting. The instruction that initiated this translation was not given in natural language, nor in a formal programming language like ALGOL-60, but in something intermediate—a "neural program":

```
execute({
    sample( file.structure );
    for section in file.sections:
        subagent.write_latex(section)
        subagent.validate(completeness, accuracy, polish)
    assemble_final_latex()
    compile_to_pdf()
})
```

This is, in Glushkov's terminology, an alphabetic operator specification—a formal description of a transformation on symbolic representations. The human operator treated the AI system as an interpreter for a high-level algorithmic language, which is precisely the subject of Chapter V.

But here is what would have fascinated Glushkov most: the language was not ALGOL-60. It was a hybrid of natural language and pseudocode, relying on the AI system's pattern-recognition capabilities (Chapter IV) to parse semi-formal specifications and execute them reliably.

Glushkov spent considerable effort on the problem of bridging human intent and machine execution. ALGOL-60 was a step toward "universal algorithmic languages," but it still required rigid syntax. The neural program demonstrates that a sufficiently capable pattern-recognition system can interpret what the operator *means* rather than merely what they literally wrote.

The instruction effectively said: "Here is my intent, expressed in a structure you can recognize. Now self-organize to accomplish it."

This is the synthesis Glushkov was reaching toward—where the automata theory of Chapter III, the self-organizing systems of Chapter IV, and the universal algorithmic languages of Chapter V converge into something that understands intent expressed in flexible, semi-formal notation. The boundary between "program" and "instruction" dissolves when the interpreter is itself a learning system.

Glushkov would likely have wanted to formalize this prompting style into a proper calculus. That was his instinct—to find the mathematics beneath the intuition, to discover the theorems latent in the practice. Perhaps some future researcher, reading these notes, will take up that task.

Reading Glushkov Today

For the modern reader—whether student, researcher, or curious observer of the AI revolution—Glushkov's *Introduction to Cybernetics* offers several distinct rewards:

First, it provides the mathematical foundations that underlie contemporary machine learning. The treatment of Boolean functions, automata theory, and algorithmic computation remains valid and pedagogically valuable. These are not historical curiosities but living mathematics.

Second, it offers perspective. In an era of breathless AI hype and apocalyptic AI doom, Glushkov's measured, mathematical approach is refreshing. He understood both the power and the limits of algorithmic systems. His discussion of Gödel's theorems, in particular, provides essential context for understanding what machine intelligence can and cannot achieve.

Third, it demonstrates the universality of mathematical insight. Glushkov, working in Kiev under the Soviet system with limited access to Western research, arrived at many of the same conclusions as his contemporaries in America and Europe. Great ideas, it seems, are discovered

rather than invented—they exist in the mathematical structure of reality, waiting for minds prepared to perceive them.

Finally, it inspires humility. We who live in the age of ChatGPT and AlphaFold sometimes imagine that we have discovered something radically new. Glushkov reminds us that the theoretical foundations were laid long ago, by thinkers who saw further than their contemporaries and whose vision we are only now beginning to realize.

Acknowledgments

This edition would not have been possible without the digitization efforts that preserved Glushkov's work, the translation work that made it accessible across languages, and the open-source LaTeX community whose tools enabled its professional typesetting.

We dedicate this edition to the memory of Viktor Mikhailovich Glushkov, and to all those who labor to preserve and transmit human knowledge across the barriers of time, language, and ideology.

Abstract

This book collects and summarizes the material necessary for constructing such sections of modern cybernetics as the theory of electronic digital machines, the theory of discrete automata and the theory of discrete self-organizing systems, automation of thought processes, pattern recognition theory, and others. The foundations of Boolean function theory, algorithm theory, logical calculi and logical networks are presented, along with basic questions of automata theory, principles of constructing electronic digital machines and universal algorithmic languages, foundations of perceptron theory, and some principal questions of the theory of self-organizing systems.

Many fundamental results in mathematical logic and algorithm theory are presented concisely, without detailed proofs, and in some cases without proofs at all.

The book is designed for a wide range of mathematicians and scientific workers of many specialties who wish to familiarize themselves with the problems of modern cybernetics.

Preface

The purpose of this book is to acquaint the reader with a number of new scientific directions that form the basis of cybernetics in its modern understanding. In the most general terms, all these directions can be divided into two large groups—the general theory of **information transformation** and the theory and principles of constructing various types of **information transformers**. However, the material that can be attributed to these indicated major directions is so extensive that it would hardly be possible to present it even concisely in a single book. Therefore, it was necessary to select the material in accordance with certain general principles.

The material for this book was selected in accordance with two basic principles. The first principle consists in the requirement of sufficiently rigorous presentation of the material, allowing its exposition in the form of some mathematical theory (although with a slant characteristic of cybernetics toward practical modeling). The second principle consists in that the author limits himself, as a rule, to discrete methods of information representation and discrete information transformers.

As a result of this selection, the book includes the following main sections: **algorithm theory** (including programming for universal electronic digital machines and universal algorithmic languages for programming), **theory of discrete automata** (including the theory of Boolean functions and the concept of principles for constructing universal electronic digital machines), **theory of discrete self-organizing systems** (including elements of the theory of optimal solutions) and, finally, **mathematical logic** (propositional calculus, narrow predicate calculus and formal arithmetic), considered as the basis for automating the process of constructing deductive (based on one or another axiomatic system) theories.

The degree of detail in presenting the material is determined primarily by the degree of its novelty. More recent sections, as related to cybernetics proper, are presented in more detail, while formulated theorems are presented with sufficiently detailed proofs or evidence. At the same time, in some older sections, such as the theory of algorithms and mathematical logic, or more recently, the general theory of automata and probability theory, which are nevertheless already well known, the proofs of a number of propositions, including Gödel's incompleteness theorems, are sometimes omitted entirely.

The study of Boolean functions, algorithms of Turing machines, and others is covered in various specialized texts. Also included here are the basic principles of proving algorithmic insolvability for certain simple problems from group theory. We also include the coverage of the algorithmic problems of various classes found according to the theory of algorithms by A. A. Markov, and by the theory of recursive functions and Turing machines by S. K. Kleene, and by the theory of partial recursive functions by B. A. Uspensky.

The second section is devoted to the analysis of theory of Boolean functions and its application to the theory of switching circuit diagrams. The third section is devoted to the abstract and structural theory of automata (automatic devices). The fourth chapter presents the foundations of the theory of discrete self-organizing systems. The definition of the notions of meta-system and super-automata, operating in a real environment, are given.

In this book, materials from lectures on various sections of cybernetics and mathematical logic, delivered by the author at Kiev University and at the Kiev House of Scientific and Technical

Propaganda in 1959–1962, were widely used. Part of these materials (for example, the theory of algorithms) was previously published for official use. The present book can be considered as the first sufficiently complete textbook for those studying the indicated sections of cybernetics.

V.M. Glushkov
Kiev, 1964

Contents

Translator's Notes **3**

Abstract **7**

Preface **9**

1 Abstract Theory of Algorithms **15**
1.1 Alphabetic Operators and Algorithms 15
1.1.1 Encoding and Decoding 16
1.1.2 Applications of Alphabetic Operators 16
1.1.3 Random Algorithms 17
1.2 Normal Algorithms 17
1.2.1 Elementary Substitutions 17
1.2.2 Graph-Schemes of Normal Algorithms 17
1.2.3 Substitution Notation 19
1.2.4 Normalization and Composition 19
1.2.5 Universal Algorithms 20
1.3 Algorithmic Scheme of Kolmogorov–Uspensky 20
1.3.1 Information Structures 20
1.3.2 Algorithmic Operations 21
1.4 Other Theoretical Algorithmic Systems 21
1.4.1 Primitive Recursive Functions 21
1.4.2 Partial Recursive Functions 22
1.4.3 Turing Machines 22
1.5 The Concept of Algorithmically Undecidable Problems 23
1.5.1 Examples of Undecidable Problems 23
1.5.2 Thue Problem 23
1.5.3 Self-Applicability Problem 24
1.5.4 Post Correspondence Problem 24
1.5.5 Matrix Representability Problem 24

2 Boolean Functions and Propositional Calculus **27**
2.1 The Concept of Boolean Functions 27
2.1.1 Basic Boolean Functions of One and Two Arguments 28
2.2 Boolean Algebra 28
2.2.1 Laws of Boolean Algebra 29
2.2.2 Normal Forms 30
2.2.3 Implicants and Minimal Forms 31
2.2.4 The Blake Algorithm 31
2.3 The Theorem on Complete Sets of Boolean Operators 32
2.3.1 Zhegalkin Polynomials 32

2.3.2 Monotonic Functions . . . 32
2.3.3 Self-Dual Functions . . . 33
2.3.4 Linear Functions . . . 33
2.3.5 Post's Theorem on Completeness . . . 33
2.4 Application of Boolean Algebra to the Theory of Combinational Schemes . . . 33
2.4.1 Karnaugh Maps . . . 34
2.4.2 Valve Schemes . . . 35
2.4.3 Shannon's Expansion Theorem . . . 35
2.4.4 Complexity Estimates . . . 36
2.5 The Concept of Propositional Calculus . . . 36
2.5.1 Formation Rules . . . 36
2.5.2 Truth Values and Tautologies . . . 37
2.5.3 The Meaning of Implication . . . 37
2.5.4 Examples of Tautologies and Non-Tautologies . . . 37
2.5.5 Formal Axiom System . . . 37
2.5.6 Inference Rules . . . 38
2.5.7 Derivability Relations . . . 38
2.5.8 The Deduction Theorem . . . 39
2.5.9 Proof Schemes . . . 39
2.5.10 Consistency and Completeness . . . 39

3 Theory of Automata 41
3.1 Abstract automata and automaton mappings . . . 41
3.1.1 Moore Automata . . . 43
3.1.2 Equivalence of Moore and Mealy Automata . . . 44
3.1.3 Properties of Automaton Mappings . . . 44
3.2 Events and representation of events in automata . . . 45
3.2.1 Operations on Events . . . 45
3.2.2 Elementary and Regular Events . . . 45
3.3 Analysis of finite automata . . . 46
3.3.1 Algorithm for Analysis . . . 46
3.4 Abstract synthesis of finite automata . . . 48
3.4.1 Synthesis Procedure . . . 48
3.4.2 Synthesis Example with Partial Automaton . . . 49
3.5 Minimization of abstract automata . . . 50
3.5.1 Equivalence of States . . . 50
3.5.2 Construction of Minimal Automaton . . . 51
3.5.3 Algorithm for Minimization . . . 51
3.5.4 Minimization of Moore Automata . . . 51
3.5.5 Minimization of Partial Automata . . . 51
3.6 Structural synthesis of finite automata . . . 53
3.6.1 Encoding and Excitation Functions . . . 53
3.6.2 Types of Memory Elements . . . 54
3.6.3 Full Synthesis Example: Sequential Binary Quadrator . . . 55
3.6.4 Structural Synthesis with Delay Elements . . . 56
3.6.5 Output Function . . . 58
3.6.6 Circuit Implementation . . . 58

4 Self-Organizing Systems **61**
4.1 The concept of self-modification and self-organization in automata 61
4.2 Some preliminary information from probability theory 62
4.2.1 Binomial distribution 64
4.2.2 Polynomial distribution 64
4.3 Quantitative measure of self-organization and self-modification in automata . . . 65
4.3.1 Example: Automata A and B 66
4.4 Automata with random transitions 66
4.4.1 Stationary random medium 67
4.4.2 Automaton with linear tactics 68
4.5 Problem of learning pattern recognition 68
4.5.1 Perceptron structure 68
4.6 Theory of learning of discrete α-perceptrons 69
4.6.1 Example 1: Complete symmetric perceptron 70
4.6.2 Example 3: Random connections 71
4.7 Regime of discrete α-perceptrons in regime of self-organization 71
4.8 Logical classification systems and measure of conditional probability 72
4.8.1 Universal classification machine 74
4.9 Self-organization and self-modification: Methods of solution of complex variant tasks 74
4.9.1 Gradient methods 74
4.9.2 Ravine method 75
4.9.3 Linear programming 75
4.9.4 Dynamic programming 76

5 Electronic Digital Machines and Programming **79**
5.1 Universal program automaton 79
5.2 Structure of contemporary universal program automata 80
5.3 Concept of programming 84
5.4 Universal algorithmic language ALGOL-60 87
5.5 Examples of Programming in ALGOL-60 Language 90

6 Predicate Calculus and the Problem of Automation of Processes of Scientific Creativity **97**
6.1 Basic Concepts of Predicate Calculus 97
6.1.1 Quantifiers 97
6.1.2 Free and Bound Variables 98
6.1.3 Axioms of Predicate Calculus 98
6.1.4 Derivation Rules 98
6.1.5 Important Relations 98
6.1.6 Normal Forms 99
6.2 Formal Arithmetic and Gödel's Theorem 99
6.2.1 Axioms of Formal Arithmetic 99
6.2.2 Derivable Relations 100
6.2.3 Proof by Induction 100
6.2.4 Provability, Disprovability, and Undecidability 100
6.2.5 Gödel's Incompleteness Theorems 100
6.3 Automation of Provability and Construction of Deductive Theories 100
6.3.1 Gentzen's System 100
6.3.2 Axiom and Derivation Rules of System G1 101
6.3.3 Equivalence of Gentzen and Hilbert Systems 102
6.3.4 Hao-Wang's Approach to Automated Theorem Proving 102

6.3.5 Experimental Results 102
6.3.6 Heuristic Approaches 102

Chapter 1

Abstract Theory of Algorithms

1.1 Alphabetic Operators and Algorithms

Algorithms in modern mathematics are customarily called constructively defined correspondences between words in abstract alphabets.

An **abstract alphabet** is any finite collection of objects called the *letters* of the given alphabet. The nature of these objects is completely irrelevant to us. The letters of abstract alphabets can be considered, for example, the letters of some natural language alphabet (Russian, Latin, Greek, etc.), digits, any symbols, drawings, etc. If desired, one can introduce an abstract alphabet whose letters will be considered whole words of one or another concrete language (for example, Russian). It is only important that the alphabet under consideration be *finite*, i.e., consist of a finite number of letters.

By introducing the concept of an (abstract) alphabet, let us define **words** in this alphabet as any finite ordered sequences of letters. For example, in the alphabet $A = A(x, y)$, consisting of two letters x and y, words should be considered any sequences x, y, xx, xy, yx, yy, xxx, ... The number of letters in a word is called the *length* of this word, so that the words written out by us in the alphabet have lengths 1, 1, 2, 2, 2, 2, 3, ... respectively.

Along with words of positive length (consisting of at least one letter), in a number of cases it is expedient to also consider the empty word, containing no letters at all. In this chapter, for denoting the empty word, the small Latin letter e is used. Sometimes, however, it is convenient to denote the empty word in full correspondence with its definition, by not writing out any letter in the corresponding place.

Note that with the accepted definition, the concept of a word in the Russian alphabet will differ from the concept of a word accepted in ordinary language. With this definition of a word, any combination of letters should be considered a word, including in this number combinations like "algorithm," "existentialism," "xxx," words in the reverse order of letters (written from right to left), etc. This is especially convenient when we take as the alphabet, for example, the decimal or any other numeration system. Thus, all integers from 0 to 9 in the decimal system are separate words (for clarity a letter of the alphabet A from 10 digits (0, 1, 2, 3, 4, 5, 6, 7, 8, 9)), connected in various arrangements by chains, can become representations of any natural number.

Definition 1.1.1 (Alphabetic Operators)**.** ***Alphabetic operators*** *or* ***alphabetic mappings*** *are generally called any rules that establish a unique correspondence between a set of words in one alphabet (**input alphabet**) and a set of words in another (in general, different) alphabet (**output alphabet**), provided that using this mapping, not for every word of the input alphabet there is necessarily a corresponding word in the output alphabet. If words in both the input and output alphabets are the same, this determines the concept of an operator acting on a common alphabet.*

In the sequel, we will mainly have to deal with so-called alphabetic operators, i.e., operators whose input alphabet can be divided into two (in the general case) different alphabets, such that the algorithmic operator in one step achieves a given word of one alphabet (the initial alphabet), and the second—the expansion of the alphabetic operator within the limits of a local alphabet.

1.1.1 Encoding and Decoding

The simplest approach for representing alphabetic operators is compression and then extraction of individual letters of input words. The simplest example of such an operation consists in that a letter exchange word produces a new word—the result of applying the operator with the exchanged value of the first letter a for b, or the last letter of that word. The simplest introduction of rules connecting separate letters of the original word in the alphabet is called **encoding**. In the simplest case, an encoding operator replaces letters in an alphabet.

Definition 1.1.2 (Encoding)**.** *Let us consider the simplest **encoding** conversion. It is easy to construct an operator from the output word to the alphabet letters and vice versa; in the given case this would be the reverse process **decoding**, taking one or several words in the output alphabet in accordance with their corresponding letters, establishing their reverse correspondence in another alphabet. In alphabet A each combination is associated with a fixed letter of alphabet B, where b_1 corresponds to letter a_1, letter b_2 corresponds to a_2, etc.*

Definition 1.1.3 (Decoding)**.** *In A an operator is called **decoding** which results from the encoding. When the decoding operator decodes, if in the word in B a letter b_1 is encountered, then it is replaced by a letter or word of A.*

Let A represent a fixed-length alphabet, B a standard (operating) alphabet, consisting of no less than $n + 1$ different letters. The *number* of distinct letters in the alphabet A is at most n, which means all letters in alphabet A consist of letters at most a in alphabet B.

Consequently, the number of distinct letters in a word in an n-letter alphabet equals, for representation, $n + N$, where N is the length of the word.

Let φ be an arbitrary alphabetic operator in the alphabet A and ψ an operation of the same letters in B, so with this operation $\psi = \varphi^{-1}$. The encoding specification can be expressed as:

$$\varphi = \psi^{-1}\varphi\psi$$

representing the encoding of the alphabetic operator corresponding to that mapping of the original encoding of some letter correspondence.

1.1.2 Applications of Alphabetic Operators

The connection noted is associated with finite requirements for recording information, i.e., our approach involves such a way of describing one method of discrete recording of any complexity—the internal process of information (character) recording which includes a finite number of different elements of the alphabet.

The indicated number of digits was used in an n-letter alphabet with natural numbers indicating numerical capacity of the alphabet, processed according to the discrete principle method with the alphabet operators' concepts outlined above—these devices are called **discrete** (as opposed to analog devices).

Definition 1.1.4 (Algorithmic Operator)**.** *An **algorithmic operator**, executing with the purpose of processing using information within its own procedure, is an alphabetic informational operator. An algorithmic operator performing a realization proceeds from its requirement and an alphabetic operator performs the following procedure called an **algorithm**.*

Thus, we have established a rather extensive field of application of alphabetic operators. The work of studying alphabetic operators is exactly the object of examining practical procedures and general processes for preparing information. Transformation of information is thereby realizing different procedures and methods of automated control.

Definition 1.1.5 (Algorithm)**.** *An* ***alphabetic operator*** *related to a complete concept is called an* algorithm*. Algorithms execute words as follows: the completed alphabetic operator is called an* ***algorithm****. An algorithm can be for complete alphabetic operator with complete alphabet operators defined—such is called the* ***algorithmic language****.*

1.1.3 Random Algorithms

In later chapters the extent of the effect by the previous working algorithm elements is the probability $C(\varphi)$ receiving the assigned word in the corresponding algorithm A of given discrete alphabet operators. An example of a random algorithm with two discrete algorithms, where entering previously a specified result, first also discrete so that result is expressed via characteristic function.

1.2 Normal Algorithms

In this and the following paragraphs a description will be given of the most common method of specifying algorithms, characterized by sufficient universality. The general method of specifying algorithms appeared historically with the method of normal algorithms designed by A. A. Markov, 1951. As a general common method appeared in a period during which A. N. Kolmogorov presented the development idea method of substitution, in which each step of another alphabetic operation is replaced by one (or more) elementary operations.

1.2.1 Elementary Substitutions

The execution of algorithms itself forms the common one called *element* given in formal specification described with single operations. The elementary operations as the first designation describe substitution and the graph is one-sided operations.

From each junction the algorithm itself represents the given operation *graph* being connected as a single step. From each junction a new element will go through the directed graph, the new one which connects to the corresponding condition of the junction.

In normal algorithms only one type of element is applicable—the elementary operation, specifically ordinary subdivision, and also elemental operators, additionally represented, alphabet related.

Definition 1.2.1 (Normal Algorithm)**.** *Finding the leftmost word q in p in the first position of the first element (or after the previous) substitution, if the considered intermediate word p is $p = rqs$ (where r denotes the empty word or any other words up to q), the algorithm replaces with the result $p' = rq's$, where q' denotes the substitution result.*

An ***algorithm****, whose elements are substitutions, one or more of them ordinary, is called the* ***normal algorithm****.*

1.2.2 Graph-Schemes of Normal Algorithms

Graph-schemes which have some special form can be described as follows. By virtue of the above definition of generalized normal algorithms, in graph-schemes of such algorithms every operator $q_1 \to q_2$ is included in a pair with recognizer q_1.

Let us combine in the graph-scheme each such pair of nodes into one node, preserving after it the designation of the corresponding operator.



Figure 1.1: Graph-scheme of a generalized normal algorithm.



Figure 1.2: Graph-scheme with combined nodes. Arrows marked + indicate successful application; arrows marked − indicate the operator is not applicable.

From each combined node two arrows will exit: an arrow with the sign "+", along which the word is directed, having undergone the action of the operator of this node, and an arrow with the sign "−", along which the word is directed in case the operator of the node is *not applicable* to it. The inapplicability of the substitution operator to a word means the absence of the *left part* of the operator (word q_1 in operator $q_1 \to q_2$) in this word.

A graph-scheme with combined nodes in the case of normal algorithms must satisfy the following conditions:

(a) All combined (operator-recognizer) nodes of the graph-scheme are ordered with the help of assigning to them sequential numbers from 1 to n, where the negative exit (arrow with the sign "−") of the i-th node is connected to the $(i+1)$-th node $(i = 1, 2, \ldots, n-1)$, and the negative exit of the n-th node is connected to the exit node of the graph-scheme;

(b) Positive exits (arrows with sign "+") of all combined nodes are connected either to the first, or to the exit node of the graph-scheme. In the first case the substitution of the operator of the corresponding node is called ordinary, and in the second—**terminal**;

(c) The input node is connected by an arrow to the first combined (recognizer-operator) node.

These conditions are necessary and sufficient for the graph-scheme satisfying them to define not a generalized normal, but an ordinary normal algorithm.

1.2.3 Substitution Notation

We introduce following conditions in notation: "$\to$", "$\to$." for substitutions. With each substitution described following one at p, as a consequence of execution, with the condition for this execution of the form of ordinary (not in concluding position) substitution, we use "$\to$"; for terminal substitution we use "$\to$."

Example 1.2.1. *Consider the substitution scheme:*

$$xy \to y' \tag{1.1}$$

$$y \to \lambda \tag{1.2}$$

Let us suppose it is given that the input word p is "abcba". The first substitution for A in this particular case is applicable, as the primitive consists of characters from the substitution scheme.

Application of the scheme of normal algorithms along with other essential substitutions constitute for elementary results in such schemes the expression of elementary substitutions. The decisive algorithm A from its alphabet $A(p)$, obtaining in result its application to the input word p, already does not have to memorize other words. The functional word mapping is:

$$p \to A(p)$$

This completely satisfies the definition above for direct construction that the operator represents realizing the algorithm. As shown by A. A. Markov [**?**]:

$$\varphi_A(p) = A(p) \tag{1.3}$$

1.2.4 Normalization and Composition

As shown by A. A. Markov and N. M. Nagorny, using normal algorithms in the alphabet A, the algorithm of assignment becomes possible. The constructive element of some cases requires a result; for some results the equivalent construction can be given at an appropriate time with procedures.

Consider the type from k being used in various compositions of the normal algorithm, where the operator produces, following each k-type, the expression in normalization.

Definition 1.2.2 (Superposition)**.** *One of the most important results is the type composition (**superposition**) describing composition of two algorithms. The superposition of two algorithms A and B in described sequence works by taking A representing as one output word of algorithm A the word. Then type representation is constructed through algorithms A and B, so it produces:*

$$D(p) = B(A(p))$$

This representation describes composition (superposition) of two algorithms producing its output.

All the described methods of composition of normal algorithms relate to the composition of algorithmic operators.

1.2.5 Universal Algorithms

Having important significance for normal algorithms A, and for all universal algebraically corresponding operators it follows, that which is called the corresponding universal algorithm.

Representation A° of alphabet A in the produced alphabet should be the same as in the definition. Functions may obtain letters and words establishing in output of different words. For example:

$$xy \to x \tag{1.4}$$

In representation A° alphabet A in standard alphabet any word should be a single present character along with a specific designation of letters.

Definition 1.2.3 (Universal Normal Algorithm)**.** *A normal algorithm U is called **universal** if for any normal algorithm A and any given word p in its alphabet there exists input word described in A this type gives $A^\circ p^\circ$. If we establish the word produces A so we have production:*

$$U(A^\circ p^\circ) = A(p)$$

establishing all requirements for the words in A^+.

1.3 Algorithmic Scheme of Kolmogorov–Uspensky

In this paragraph a scheme is presented by the proposals of A. N. Kolmogorov and V. A. Uspensky of the way of specifying algorithmic concepts in total form. For construction of corresponding algorithmic schemes we introduce first, "cells", containing one letter of alphabet, and also specific "pointers", being letters, connected with them—the connecting elements for the words being defined.

1.3.1 Information Structures

Consider the total case for alphabet, production for which the letter producing takes place. We will represent, as would be established in the single model of people, connecting themselves to our discrete type of information in one connection to its meaning through the representation of system. On each table must be a place for object describing entry, and in the meaning of recording this entry, we will have conditions that correspond to a specific element of alphabet letters entering the place for elements for our algorithmic system.

For determining condition using element, establishing each from corresponding scheme of one or two letters of alphabet for representation, being α, β, γ, δ, $\dots(q)$. Maximum approach is given letters α, $\dots$, β, γ, δ (for δ). Each element of condition being (position), can be following the given (empty, being, taking in part position)—or another position, each place being filled, obtaining each position of alphabet type A.

Index p_1, p_2, p_3 is as a means that establishes position, being the elements for places being considered for connection as q-type coordination (connection for matching of corresponding).



Figure 1.3: Information structure with positions and connections. The word "*abcba*" is represented as a sequence of cells connected by labeled edges. The shaded cell indicates the active position.

Definition 1.3.1 (Information Structure)**.** *An* ***information structure*** *of* ***algorithmic complexity*** *is defined as* Γ_1, Γ_2, Γ_3, Γ_4, *(*$N(i)$*), following for* $n = \Gamma_1 N(i)$*; condition* M *taking also on any position from one or more structures, consisting of according to such connecting established. The type information structures are designated as* T_1, T_2, ..., T_n *(in generalized approach, connection between letters).*

1.3.2 Algorithmic Operations

The overall actual point for an information complex will consist of establishing connections with this or such approaches, depending on total connected process P and with p combining with one or other overall meaning.

With specified approach numbers in our overall connections for the actual view of informational complex, for any algorithm and for separate α words of T_n, T_n, ..., T_k for any other type establishing alphabetical approaches in this approach.

For approach has a number of any position of approach (position means connecting approach), U_1, U_2, ... is for any approach U, for connecting U to each position, having connection with U_n to W_n, ..., W_k.

S positions correspond to the approach table of corresponding operator R_s, carrying different n-type corresponding operator combination in any alphabet for working of algorithm A. In considering informational complex S (tables of corresponding overall actual) approach.

Universally this can be so called algorithmic system of Kolmogorov-Uspensky approach, that this form of producing at (M) for our number corresponding to establishing results corresponding approach, established as an alphabet.

1.4 Other Theoretical Algorithmic Systems

The historical period of algorithmic systems, allowing for examination and including approach, is forming also, consisting of many constructive orderings for systems, (elements) functions, functioning established functions—the precise deducing function.

1.4.1 Primitive Recursive Functions

After introducing numbers it means also in approaches of form alphabetic operator according to approaches of function $y = f(x)$, in which are such arguments, that this same function in its forms, differently, means it should be approached for we use, for being for constructive approaching in order determining this function.

For considering approaches, functions mean the following approach of steps function, which are simple functions, meaning, elementary algorithmic:

- Of approach ($\alpha = 0$ for all elements producing such approach—*zero function*)

- Elements of functions ($I(a) = a$—*identity function*)
- Approaching condition ($S(a) = a + 1$—*successor function*)

In constructing more types of new function approach composition for more complex arithmetic functions, meaning one also a total type of composition of approaching function.

Definition 1.4.1 (Superposition of Functions)**.** *There function is producing, meaning this approach in corresponding alphabet arithmetic function, which means also approach for elements of function. Similar position, an approach for superposition function (f_1) is g, g is at the same condition functions in its approach f. Superposition (at n-approaching type) functions ($\varphi(n)$) approach for elements.*

Definition 1.4.2 (Primitive Recursion Operator)**.** *Operator results approaches: for more type results constructing is n-corresponding arithmetic function (function is n arguments), for those argument function. As a condition, such corresponding approach the following:*

$$(i_1, i_2, \ldots, s_{i_n}, c) + 1 = g(s_1, s_{i_2}, \ldots, s_{i_n}, c, i) \tag{1.5}$$

where $y = (x_1, x_{2n}, \ldots, x_n)$; f corresponding with a and n—given numbers, predetermined.

Example 1.4.1. *In this example, the primitive recursive operations are continued by primitive recursive results. This function is determined with means of similar function $g(a) = a$ and k function—for determining:*

$$f(x, 0) = x = g(x) \tag{1.6}$$
$$f(x, y + 1) = (x + y + 1) = h(x, y, f(x, y)) \tag{1.7}$$

1.4.2 Partial Recursive Functions

Functions, which are produced from primitive recursive elements through arithmetic function with means of operation of general arithmetic with production, being approached with some (count) numbers n in the approach.

The partial class of recursive functions represents itself overall a class of constructive operations corresponding to arithmetic functions, which may also be in overall approaches for each class of recursive function.

Belonging to partial recursive function, turns out to be equivalent alphabetically to the normalized algorithm. Thus, therefore, one can give the following completed model:

Theorem 1.4.1. *An algorithm performs the partial recursive function, producing, or else will form the arithmetic (elementary) form of a normalized algorithm.*

1.4.3 Turing Machines

Studying still one type of approach in theory of algorithms, produced in 1936 by A. Post and A. Turing.

In algorithmic concept, described by Turing, producing its standard information approaches in the standard situation, alphabet, and algorithm—in type according to characterized approach, is this in the approximate information approach uses potentially infinite tape-informational letters, decomposed on separate positions. In each of alphabet is some pointer, symbol 0 and 1.

Definition 1.4.3 (Turing Machine Operations)**.** *The work of algorithm is established by the alphabetic approaches, in each of alphabet one-to-one produces letters of approaches. Containing approaches let be predetermined in also alphabet. Containing:*

1. ***First type**: The stopping of algorithm.*

2. ***Second type**: Overwriting active cell content (entered into it a new) symbol and transition to execute j-th operation.*

3. ***Third type**: Contents tape placed on one tape to the right and transition to execute j-th operation.*

4. ***Fourth type**: Contents active cell on one tape left and transition to execute j-th operation.*

5. ***Fifth type**: If active tape contents (each is and each entered word), to transition to execute j-th operation, to overall active tape content is unchanged, to transition to execute k-th operation.*

6. ***Sixth type**: The stopping, completing performance of algorithm.*

Definition 1.4.4 (Turing Machine)**.** *An **algorithm**, consisting of any number of any given rules of operation as is called **Turing machine**. Can be shown, that any alphabetic Post approach for algorithm, realizing by a Turing machine.*

As one also for recognizing, also λ-calculations, Gödel's number. The concepts of ε-calculations by A. M. Turing.

The method of algorithm, being realizing as a main tape Turing, approaching also in completely producing approaches. The represented scheme can be shown to be approach of method characterization approaches, meaning the function recursive function may for arguments, established x, x, ..., x_n at some approach.

From 1, 2, ..., n—the "non-step" approach. Using for Turing we can obtain at a place as a means standard of machine information approaches at this output for word, in which the machine processes approach for also word p.

1.5 The Concept of Algorithmically Undecidable Problems

There are algorithms representing problems means itself, more or less approaches problems, formulating in a type problem for being needed on the output, it in the meaning of our this word p in also in corresponding. The approach in the problem may also established as well as to algorithmic **undecidable** problem.

1.5.1 Examples of Undecidable Problems

The typical examples of algorithmic undecidable problems are the problems proving the type of validity of types in general. For this, approaches containing symbols, when type of element approach is on elements means (q produces approaches with approaches) to complex elements.

A given problem types corresponds to—is example also algebra approach of corresponding consideration. May take, also elements produces our also types of alphabet elements, in also producing also approach of such type approaches of undecidable problem. In number of this alphabet approaches such is known, being approach, being producing according to this types—P. S. Novikov.

In particular approaches uses also problem of approaches universally problem. Following x_1, x_2, ..., x_n, y_1, y_2, ...—some produced from approaches in results for approach from numbers connecting on our approach for also rules approach of corresponding is also approaches.

1.5.2 Thue Problem

An approach producing also uses for producing approaches of Thue problem in using the approaches from alphabet, producing, for also types is approach of produces of approach from one also letter.

For constructing the alphabet system for producing the approach of this produces approaches, according, using approach of produces of Thue, constructing in this types is from approach corresponded approach.

Definition 1.5.1 (Word Problem)**.** *The problem of approach for words in approach in basis aspects is—to corresponding undecidable problems for also producing. Results given σ by is correspondingly letters σ_1, d_1, ..., is approach, constructing is establishing, approach is producing:*

$$x_1^{k_1}, x_2^{k_2}, \ldots, x_m^{k_m} \tag{1.8}$$

1.5.3 Self-Applicability Problem

A still one undecidable problem will be also problem considering corresponding algorithms. For this concrete formulation approach problem be can to consider approach for normal algorithm in alphabet, consisting of also one or two letters.

Definition 1.5.2 (Self-Applicability)**.** ***Self-applicability*** *corresponds the self-applicability for approach algorithm is this as called self-applicability algorithms in any alphabet—is (H)—producing for word A is establishing approach to word A in also for this any is approach, in type means—word A; correspondingly (n_1)—is at this letter of letter is two approach.*

Therefore, in also approaches established formulation—approach producing is this approaches word, in producing is not producing, as in approaches of A is producing on this approach in also approach.

Assume that algorithm B is so-called corresponding elements is established. In this case is in approaches corresponding normal approach of algorithm C in this is also alphabet. In, corresponds to this approach D, also producing to this approach—in this approach alphabet.

1.5.4 Post Correspondence Problem

Very close to one establishing of algorithmic undecidability for—is the such types is problem producing is established problem. Producing algorithmic undecidability of is established problem, establishing is established correspondingly approach problem. Is approach of is in approach alphabet X is also approach of given system is of types (X, (b), ..., G).

Problem 1.5.1 (Post Correspondence Problem)**.** *Type being is of is the constructive method, allowing for any such system S in a finite number of steps to answer whether it is possible to construct such a word $p_1 p_2 \cdots p_{i_k}$ from the first elements of pairs of the system S, so that it coincides with the word $q_1, q_2 \cdots q_{i_k}$, constructed from the corresponding second elements of this same system of pairs.*

1.5.5 Matrix Representability Problem

Algorithmically undecidable also turns out to be the **problem of representability** for matrices.

Definition 1.5.3 (Matrix Representability)**.** *For the formulation of this problem let us agree that some matrix is **representable** through matrices U_1, U_2, ..., U_n, if for some finite sequence (generally speaking, with repetitions) $U_{i_1} U_{i_2} \cdots U_{i_k}$ of these matrices the product $U_{i_1} U_{i_2} \cdots U_{i_k}$ of all matrices entering into this sequence, coincides with the given initial matrix U.*

Problem 1.5.2 (Matrix Representability Problem)**.** *The problem of representability consists in finding a general constructive method, with the help of which in a finite number of steps for any matrix U and any finite system S of matrices one could determine whether the matrix U is representable through the matrices of system S or not representable.*

Remark 1.5.1. *Let us recall that the algorithmic unsolvability of all the indicated problems is proved under the assumption of validity of the normalization principle, however, as noted above, the nature of this unsolvability turns out to be deeper and in some sense independent of this principle.*

Chapter 2

Boolean Functions and Propositional Calculus

2.1 The Concept of Boolean Functions

Boolean (or **switching**) functions are customarily called such functions, in which all arguments, as well as the functions themselves, can take only two different values.

The role of Boolean functions in cybernetics is determined by two main circumstances. First, Boolean functions represent a convenient apparatus for describing schemes of many information transformers, constructed according to the discrete principle, since for modern technology it is much simpler to construct discrete elements operating specifically in binary, and not in any other alphabet. Secondly, Boolean functions are widely applied in mathematical logic, representing one of the foundations on which the automation of complex thought processes is based.

Application alongside ordinary variables, taking numerical values, of Boolean variables, having only two possible values, plays an essential role in constructing various practical algorithmic systems for programming on electronic computers. Boolean functions can successfully be applied also for solving some general questions of algorithm theory, for example for refining the concept of algorithm complexity.

Two possible values of variables that figure in the definition of Boolean functions can be denoted arbitrarily. In practice, however, mainly two systems of notation are used:

1. In the first system (when applying Boolean functions to the theory of automata schemes), the possible values of Boolean variables are denoted by 0 and 1. We call these symbols zero and one, keeping in mind that zero and one appear here not as numbers, but only as convenient designations for letters of the abstract binary alphabet.

2. In the second system of designations (in the logical application), we use the words "true" and "false". The meaning of these words comes from the original meaning of Boolean variables, representing values of elementary assertions of which the compound assertion is composed.

In the first of the two described systems, the truth tables of Boolean functions are presented where each row of the table corresponds to a specific sequence of values of the arguments, and the last column of the corresponding row lists the value of the function for this set of argument values.

Each Boolean function of any number of arguments can be specified by a corresponding sequence of zeros and ones. Thus, given for example the function $f(x_1, x_2)$ of two arguments, the sequence 0110 designates the function that takes:

- value 0 when $x_1 = 0$ and $x_2 = 0$;

- value 1 when $x_1 = 0$ and $x_2 = 1$;
- value 1 when $x_1 = 1$ and $x_2 = 0$;
- value 0 when $x_1 = 1$ and $x_2 = 1$.

This is the sum modulo 2 (exclusive OR).

The total number of Boolean functions of n arguments is given by:

$$B(n) = 2^{2^n} \tag{2.1}$$

Thus:

- At $n = 1$: $B(1) = 4$
- At $n = 2$: $B(2) = 16$
- At $n = 4$: $B(4) = 65536$
- With more arguments, the number grows extremely rapidly (approximately 4.3×10^9 for certain cases)

2.1.1 Basic Boolean Functions of One and Two Arguments

Definition 2.1.1 (Conjunction)**.** *The **conjunction** (logical multiplication, AND) of two Boolean variables x and y is denoted by $x \wedge y$, or $x \cdot y$, or simply xy. It takes value 1 only when both $x = 1$ and $y = 1$; otherwise it equals 0.*

Definition 2.1.2 (Disjunction)**.** *The **disjunction** (logical addition, OR) of two Boolean variables x and y is denoted by $x \vee y$. It takes value 0 only when both $x = 0$ and $y = 0$; otherwise it equals 1.*

Definition 2.1.3 (Negation)**.** *The **negation** (NOT) of a Boolean variable x is denoted by $\bar{x}$ or $\neg x$. It takes value 1 when $x = 0$ and value 0 when $x = 1$.*

Definition 2.1.4 (Implication)**.** *The **implication** $x \supset y$ (or $x \to y$) has the truth table: $0 \supset 0 = 1$, $0 \supset 1 = 1$, $1 \supset 0 = 0$, $1 \supset 1 = 1$. It can be expressed as $x \supset y = \bar{x} \vee y$.*

Definition 2.1.5 (Equivalence)**.** *The **equivalence** $x \equiv y$ takes value 1 when x and y have the same value, and 0 otherwise.*

Definition 2.1.6 (Sheffer Stroke)**.** *The **Sheffer stroke** (NAND) is denoted $x|y$ or $x \uparrow y$ and equals $\overline{x \wedge y}$. This single operation forms a complete basis for all Boolean functions.*

Definition 2.1.7 (Peirce Arrow)**.** *The **Peirce arrow** (NOR) is denoted $x \downarrow y$ and equals $\overline{x \vee y}$. This also forms a complete basis for all Boolean functions.*

Definition 2.1.8 (Symmetric Functions)**.** ***Symmetric functions** are Boolean functions that do not change their values when the arguments are permuted.*

2.2 Boolean Algebra

Boolean algebra can be defined as the algebra of Boolean functions, realized through composition of operations: conjunction, disjunction, and negation. In the following, a, b, c, etc., serve as alphabet letters for representing Boolean functions.

2.2.1 Laws of Boolean Algebra

The verification of identical correspondences in Boolean algebra can be produced by substituting all possible sets of values of the variables.

Commutativity

Law 2.2.1 (Commutativity of Multiplication)**.**

$$xy = yx \tag{10}$$

Law 2.2.2 (Commutativity of Disjunction)**.**

$$x \vee y = y \vee x \tag{13}$$

Associativity

Law 2.2.3 (Associativity of Multiplication)**.**

$$x(yz) = (xy)z \tag{11}$$

Law 2.2.4 (Associativity of Disjunction)**.**

$$x \vee (y \vee z) = (x \vee y) \vee z \tag{14}$$

Idempotency

Law 2.2.5 (Idempotency of Multiplication)**.**

$$xx = x \tag{12}$$

By virtue of this law, the concept of degree and exponentiation in Boolean algebra practically have no significance.

Law 2.2.6 (Idempotency of Disjunction)**.**

$$x \vee x = x \tag{15}$$

Distributive Laws

Law 2.2.7 (First Distributive Law)**.**

$$x(y \vee z) = xy \vee xz \tag{16}$$

Law 2.2.8 (Second Distributive Law)**.**

$$x \vee yz = (x \vee y)(x \vee z) \tag{17}$$

Absorption Rules

Law 2.2.9 (First Absorption Rule)**.**

$$x \vee xy = x \tag{18}$$

Law 2.2.10 (Second Absorption Rule)**.**

$$x(x \vee y) = x \tag{19}$$

Negation Laws

Law 2.2.11 (Double Negation)**.**

$$\bar{\bar{x}} = x \tag{20}$$

By virtue of this law, any even number of negations performed in succession does not change the result, while any odd number of them is equivalent to performing one negation.

De Morgan's Rules

Law 2.2.12 (First De Morgan Rule)**.**

$$\overline{xy} = \bar{x} \vee \bar{y} \tag{21}$$

Law 2.2.13 (Second De Morgan Rule)**.**

$$\overline{x \vee y} = \bar{x} \cdot \bar{y} \tag{22}$$

Laws Involving Constants

Law 2.2.14 (Law of Excluded Middle)**.**

$$x \vee \bar{x} = 1 \tag{23}$$

Law 2.2.15 (Law of Contradiction)**.**

$$x\bar{x} = 0 \tag{24}$$

Law 2.2.16 (Annihilation by Zero)**.**

$$x \cdot 0 = 0 \tag{25}$$

Law 2.2.17 (Identity for Multiplication)**.**

$$x \cdot 1 = x \tag{26}$$

Law 2.2.18 (Identity for Disjunction)**.**

$$x \vee 0 = x \tag{27}$$

Law 2.2.19 (Annihilation by One)**.**

$$x \vee 1 = 1 \tag{28}$$

Law 2.2.20 (Negation of One)**.**

$$\bar{1} = 0 \tag{29}$$

Law 2.2.21 (Negation of Zero)**.**

$$\bar{0} = 1 \tag{30}$$

2.2.2 Normal Forms

Definition 2.2.1 (Elementary Conjunction)**.** *An **elementary conjunction** is a conjunction of variables or their negations, where each variable appears at most once.*

Definition 2.2.2 (Elementary Disjunction)**.** *An **elementary disjunction** is a disjunction of variables or their negations, where each variable appears at most once.*

Definition 2.2.3 (Disjunctive Normal Form (DNF))**.** *A formula is in **disjunctive normal form** if it is a disjunction of elementary conjunctions.*

Definition 2.2.4 (Conjunctive Normal Form (CNF)). *A formula is in* ***conjunctive normal form*** *if it is a conjunction of elementary disjunctions.*

Definition 2.2.5 (Complete Disjunctive Normal Form). *A* ***complete disjunctive normal form*** *(also called canonical DNF or full DNF) is a DNF where each elementary conjunction contains all variables of the function (each appearing exactly once, either in direct or negated form).*

Definition 2.2.6 (Complete Conjunctive Normal Form). *A* ***complete conjunctive normal form*** *(canonical CNF) is a CNF where each elementary disjunction contains all variables.*

Theorem 2.2.1. *Any formula of Boolean algebra can be reduced to disjunctive normal form using correspondences (10)–(30).*

Example 2.2.1. *Converting* $x \vee \overline{yz}$ *to DNF:*

$$\begin{aligned} x \vee \overline{yz} &= x \vee (\bar{y} \vee \bar{z}) \\ &= (x \vee \bar{y}) \vee \bar{z} \end{aligned}$$

Or expanded to complete DNF with appropriate terms.

Theorem 2.2.2. *For any Boolean function* f *of any number* n *of variables* $x_1, x_2, \ldots, x_n$*, there exists exactly one complete disjunctive normal form and exactly one complete conjunctive normal form.*

Theorem 2.2.3. *A Boolean function can be represented by a corresponding disjunctive normal form formula if and only if it is not identically zero.*

Theorem 2.2.4. *Using correspondences (10)–(30), each formula of Boolean algebra corresponds to exactly one Boolean function of its arguments.*

2.2.3 Implicants and Minimal Forms

Definition 2.2.7 (Implicant). *An* ***implicant*** *of a Boolean function* f *is an elementary conjunction such that whenever it equals* 1*, the function* f *also equals* 1*.*

Definition 2.2.8 (Prime Implicant). *A* ***prime implicant*** *is an implicant that cannot be reduced (by removing any literal) while remaining an implicant.*

Definition 2.2.9 (Minimal DNF). *A* ***minimal disjunctive normal form*** *is a DNF representation of a Boolean function with the minimum number of literals (or minimum number of terms).*

2.2.4 The Blake Algorithm

One of the most effective algorithms for finding all prime implicants is the **Blake algorithm**. It is based on the following Boolean identity:

$$AB \vee \bar{A}C = AB \vee \bar{A}C \vee BC \tag{31}$$

This is known as the **consensus rule**. Here A represents a variable, and B and C are elementary conjunctions. The term BC is called the **consensus** of AB and $\bar{A}C$.

The Blake algorithm proceeds as follows:

1. Apply the consensus rule: For any pair of terms containing complementary literals x and $\bar{x}$, form their consensus (the conjunction of all other literals).
2. Continue until no new terms can be generated.
3. Apply the absorption rule $p \vee pq = p$ to eliminate redundant terms.
4. The result contains all prime implicants.

2.3 The Theorem on Complete Sets of Boolean Operators

The complete disjunctive normal form establishes that any Boolean function can be represented using the operations of negation, conjunction, and disjunction. Therefore, a complete set of Boolean operations should consist of these three operations.

Definition 2.3.1 (Complete Set of Boolean Operators)**.** *A set of Boolean operators is called* ***complete*** *if any Boolean function can be expressed as a composition of functions from this set.*

Definition 2.3.2 (Closure)**.** *The* ***closure*** *of a set of Boolean operators is the set of all Boolean functions that can be obtained by composition (superposition) of the given operators.*

2.3.1 Zhegalkin Polynomials

Any Boolean function can be represented in the form of a polynomial over the field $\mathbb{Z}_2$ (integers modulo 2), called a **Zhegalkin polynomial**.

Negation can be expressed as:

$$\bar{x} = x \oplus 1 \tag{32}$$

where $\oplus$ denotes addition modulo 2 (exclusive OR) and multiplication is ordinary Boolean multiplication (conjunction).

The Zhegalkin polynomial representation uses only:

- The constant 1
- Addition modulo 2 (XOR): $\oplus$
- Multiplication (AND): $\cdot$

For the product of signs (where $\sigma_i \in \{-1, +1\}$ represent signs):

$$\sigma_1 \wedge \sigma_2 \wedge \cdots \wedge \sigma_n = \sigma_1 \sigma_2 \cdots \sigma_n \tag{33}$$

Any even number of negative signs gives a positive result, and any odd number gives a negative result. In Boolean terms: any even number of ones (in XOR) gives zero, and any odd number gives one.

2.3.2 Monotonic Functions

Definition 2.3.3 (Monotonic Boolean Function)**.** *A Boolean function $f(a_1, a_2, \ldots, a_n)$ is called* ***monotonic*** *if for any two sets of arguments $A = (a_1, \ldots, a_n)$ and $B = (b_1, \ldots, b_n)$ such that $A \leq B$ (meaning $a_i \leq b_i$ for all i), we have $f(A) \leq f(B)$.*

Definition 2.3.4 (Non-monotonic Function)**.** *A function f is called* ***non-monotonic*** *if there exist sets $A \leq B$ such that $f(A) = 1$ and $f(B) = 0$.*

Theorem 2.3.1. *The closure of any monotonic Boolean operator does not contain the operation of negation.*

Proof. Monotonicity is preserved under superposition. If functions $f(x_1, \ldots, x_n)$ and $g(y_1, \ldots, y_m)$ are monotonic, then their composition is also monotonic. Since negation is non-monotonic, it cannot be in the closure of monotonic operators. □

The simplest example of a non-monotonic operation is the operation of negation.

2.3.3 Self-Dual Functions

Definition 2.3.5 (Self-Dual Function)**.** *A Boolean function (operator) $f(a_1, \ldots, a_k)$ is called* ***self-dual*** *if:*

$$f(a_1, \ldots, a_k) = \overline{f(\bar{a}_1, \ldots, \bar{a}_k)} \tag{2.2}$$

2.3.4 Linear Functions

Definition 2.3.6 (Linear Boolean Function)**.** *A Boolean function is called* ***linear*** *if it can be expressed as a Zhegalkin polynomial without products of variables:*

$$f(x_1, \ldots, x_n) = c_0 \oplus c_1 x_1 \oplus c_2 x_2 \oplus \cdots \oplus c_n x_n \tag{2.3}$$

where $c_i \in \{0, 1\}$.

2.3.5 Post's Theorem on Completeness

Theorem 2.3.2 (Post's Theorem)**.** *For a set of Boolean operations to be complete, it is necessary and sufficient that it contains:*

1. *at least one non-monotonic operation,*
2. *at least one non-linear operation,*
3. *at least one non-self-dual operation,*
4. *at least one operation that is not identically* 0 *on the set* $(0, 0, \ldots, 0)$*,*
5. *at least one operation that is not identically* 1 *on the set* $(1, 1, \ldots, 1)$*.*

Corollary 2.3.1. *The following sets are complete:*

- $\{\wedge, \vee, \neg\}$ *(conjunction, disjunction, negation)*
- $\{\wedge, \neg\}$ *(conjunction and negation)*
- $\{\vee, \neg\}$ *(disjunction and negation)*
- $\{|\}$ *(Sheffer stroke alone)*
- $\{\downarrow\}$ *(Peirce arrow alone)*

2.4 Application of Boolean Algebra to the Theory of Combinational Schemes

Definition 2.4.1 (Combinational Scheme)**.** *A* ***combinational scheme*** *is a device for transforming discrete alphabet signals. It is assumed that processing occurs in a finite alphabet S. A combinational scheme of type S transforms an input alphabet A into an output alphabet.*

The following properties characterize combinational schemes:

1. Any element operates on signals according to predefined operations in the alphabet.
2. If element P has established input in alphabet S, it produces established output.
3. Each input/output connection is defined for the scheme elements.

Definition 2.4.2 (Boolean Combinational Scheme)**.** ***Boolean*** *(or* ***automata) combinational circuits*** *operate on the Boolean alphabet* $\{0, 1\}$*.*

In a Boolean combinational scheme, the circuit alphabet is the Boolean alphabet with single letters 0 and 1. If the scheme has n inputs and m outputs, the function it computes is called a **Boolean (n, m)-function**.

2.4.1 Karnaugh Maps

For Boolean functions of up to 4-6 variables, **Karnaugh maps** provide a visual method for finding minimal disjunctive normal forms.

For four variables x, y, z, u, the Karnaugh map is arranged as follows:

$zu\backslash xy$	00	01	11	10
00	0	1	3	2
01	4	5	7	6
11	12	13	15	14
10	8	9	11	10

When specifying a Boolean function $f(x, y, z, u)$ with a Karnaugh map, in each square is written the value of the function (0 or 1) on the set of variable values whose number coincides with the square number.

For partial Boolean functions, squares may contain:

- 0 — function value is zero
- 1 — function value is one
- $-$ (dash) — function value is undefined (don't care)

The Karnaugh map is constructed such that configurations of ones giving different elementary products are recognized simply:

- Elementary products of length 4 (constituents of one) correspond to individual squares.
- Products of length 3: All $C_4^3 \cdot 2^3 = 32$ elementary products correspond to pairs of adjacent squares forming 2×1 rectangles.
- Products of length 2: All $C_4^2 \cdot 2^2 = 24$ products correspond to groups of 4 squares forming 2×2 squares or 4×1 rectangles.
- Products of length 1: All $C_4^1 \cdot 2 = 8$ products correspond to groups of 8 squares forming 4×2 rectangles.

Note: Opposite edges of the Karnaugh map are identified (the map wraps around).

Example 2.4.1. *The configuration consisting of squares 5 and 4 corresponds to the elementary product $\bar{x}yz$.*

The configuration (a 2×2 square) consisting of squares 0, 2, 8, 10 corresponds to the elementary product $\bar{y}\bar{u}$.

Example 2.4.2. *Consider the Boolean function f given by the Karnaugh map:*

$zu\backslash xy$	*00*	*01*	*11*	*10*
00	*1*	*0*	*0*	*1*
01	$-$	*0*	*0*	*0*
11	*0*	$-$	*1*	$-$
10	*1*	*1*	*0*	*1*

The minimal covering uses two 2×2 squares, giving:

$$f = \bar{y}u \vee xz$$

This is the minimal DNF for function f.

Karnaugh maps for 2 and 3 variables:
For 3 variables (x, y, z):

$z\backslash xy$	00	01	11	10
0	0	1	3	2
1	4	5	7	6

For 2 variables (x, y):

$y\backslash x$	0	1
0	0	1
1	2	3

For 5 and 6 variables, additional techniques can construct extended Karnaugh maps, but for more variables, analytical methods like Blake's algorithm become necessary.

2.4.2 Valve Schemes

Definition 2.4.3 (Valve)**.** *A **valve** is a two-input combinational scheme with two input poles and one output pole. The valve passes or blocks the signal on one input pole based on the signal on the controlling input pole.*

In valve schemes, onto the controlling input poles enter either input signals directly or their negations $x_1, x_2, \ldots$ and $\bar{x}_1, \bar{x}_2, \ldots$.

2.4.3 Shannon's Expansion Theorem

For any Boolean function f, the following relationship holds:

$$f(x_1, x_2, \ldots, x_{n-1}, x_n) = f(x_1, x_2, \ldots, x_{n-1}, 1) \cdot x_n \vee f(x_1, x_2, \ldots, x_{n-1}, 0) \cdot \bar{x}_n \qquad (34)$$

The validity of this formula is easily verified by substituting $x_n = 1$ and $x_n = 0$.
This reduces the problem of synthesizing a scheme with n-place output function $f(x_1, x_2, \ldots, x_n)$ to synthesizing schemes with two $(n-1)$-place output functions:

$$f_1(x_1, x_2, \ldots, x_{n-1}) = f(x_1, x_2, \ldots, x_{n-1}, 1)$$
$$f_2(x_1, x_2, \ldots, x_{n-1}) = f(x_1, x_2, \ldots, x_{n-1}, 0)$$

A **cascade** valve scheme realizes this reduction (see Figure 2.1). Continuing the reduction process, we build the required valve scheme consisting of n cascades.



Figure 6: Basic valve element



Figure 7: Cascade valve scheme

Figure 2.1: Valve scheme elements: (Left) Basic valve selects f_1 when $x_n = 1$ or f_2 when $x_n = 0$. (Right) Cascade structure reduces n-variable function synthesis to successive 2-way selections.

2.4.4 Complexity Estimates

Theorem 2.4.1 (Shannon). *Whatever the positive real number ε, there exists a whole number $N = N(\varepsilon)$ such that any Boolean function of $n \geq N$ variables can be realized in the form of output function of a valve scheme containing no more than*

$$(1+\varepsilon)\frac{2^{n+2}}{n}$$

valves. For any n, for such realization no more than $\frac{2^{n+3}}{n}$ valves are required.

Analogous **complexity estimates** for schemes under general assumptions regarding the used sets of logical elements were established by O. B. Lupanov.

It was also shown that there exist Boolean functions which cannot be realized with fewer than $(1-\varepsilon)\frac{2^n}{n}$ elements, and this bound tends to be tight as n increases.

Definition 2.4.4 (Complexity of Boolean Scheme). *Let $L(A)$ denote the complexity of a Boolean (n,m)-scheme realizing operator A. This represents the minimum number of elements needed to realize A.*

2.5 The Concept of Propositional Calculus

Propositional calculus represents the simplest mathematical logic. Its main object is the process of establishing and producing logical mathematical relations and connections.

Definition 2.5.1 (Propositional Formula). *A **propositional formula** is constructed from formal objects of three types:*

1. ***Propositional variables** (letters): A, B, C, ... representing elementary propositions*
2. ***Logical connectives**: $\neg$ (negation), $\wedge$ (conjunction), $\vee$ (disjunction), $\supset$ (implication), $\equiv$ (equivalence)*
3. ***Parentheses**: for grouping*

2.5.1 Formation Rules

Formulas of propositional calculus are constructed as follows:

1. Propositional letters (A, B, C, ...) are formulas.
2. If A is a formula, then $(\neg A)$ is a formula.
3. If A and B are formulas, then $(A)\wedge(B)$, $(A)\vee(B)$, $(A)\supset(B)$, and $(A)\equiv(B)$ are formulas.

Example 2.5.1. *Construction of the formula $((A \wedge B) \vee C) \supset (A \vee B)$:*

1. *A, B, C are formulas (propositional letters)*
2. *$(A) \wedge (B)$ is a formula*
3. *$((A) \wedge (B)) \vee (C)$ is a formula*
4. *$(A) \vee (B)$ is a formula*
5. *$(((A) \wedge (B)) \vee (C)) \supset ((A) \vee (B))$ is a formula*

2.5.2 Truth Values and Tautologies

Definition 2.5.2 (Tautology). *A formula A is called a **tautology** (or **tautologically true formula**) if it takes the value "true" for all possible assignments of truth values to its propositional variables.*

Truth tables for the basic connectives:

A	B	$\neg A$	$A \wedge B$	$A \vee B$	$A \supset B$	$A \equiv B$
T	T	F	T	T	T	T
T	F	F	F	T	F	F
F	T	T	F	T	T	F
F	F	T	F	F	T	T

2.5.3 The Meaning of Implication

From the truth table for implication ($A \supset B$), we see that the meaning of "entails" in propositional calculus differs from ordinary speech. Usually when we say proposition A entails proposition B, we mean they are connected causally.

For example:

- "This substance is oxygen" $\supset$ "This substance is a gas" seems reasonable.
- "In winter it is cold" $\supset$ "Twice two is four" seems like nonsense in ordinary speech.

However, according to the truth table, both are true in propositional calculus (since a false antecedent or true consequent makes the implication true).

The reason is that by limiting ourselves to considering only whether propositions are true or false, we have made **indistinguishable among themselves** all true (and all false) propositions. We cannot penetrate into the internal structure needed for establishing causal connections.

Disclosure of internal structure requires more complex logical calculi, particularly the **predicate calculus** (see Chapter VI).

2.5.4 Examples of Tautologies and Non-Tautologies

Example 2.5.2. *The formula $A \wedge B \supset A$ is a tautology:*

- *It is true whenever $A \wedge B$ is false (i.e., when $A = F$ or $B = F$).*
- *When $A \wedge B$ is true (both $A = T$ and $B = T$), then $A = T$, so the implication is true.*

Example 2.5.3. *The formula $A \vee B \supset A$ is **not** a tautology:*

- *When $A = F$ and $B = T$: $A \vee B = T$ but $A = F$, so $T \supset F = F$.*

2.5.5 Formal Axiom System

The formal approach to propositional calculus formalizes not only formula notation but also the concept of tautologically true formulas and the derivation process.

A **system of axioms** characterizes the set of all tautologically true formulas. The following is a commonly used axiom system (see S. K. Kleene):

Axiom 2.5.1 (Axiom Schemata). *1.* $A \supset (B \supset A)$

2. $(A \supset B) \supset ((A \supset (B \supset C)) \supset (A \supset C))$

3. $A \supset (B \supset A \wedge B)$

4. $A \wedge B \supset A$
5. $A \wedge B \supset B$
6. $A \supset A \vee B$
7. $B \supset A \vee B$
8. $(A \supset C) \supset ((B \supset C) \supset (A \vee B \supset C))$
9. $(A \supset B) \supset ((A \supset \neg B) \supset \neg A)$
10. $\neg\neg A \supset A$
11. $B \supset B$

The first ten axioms are **axiom schemata** — any formula obtained by substituting concrete formulas for the proposition letters is an axiom.

2.5.6 Inference Rules

Definition 2.5.3 (Modus Ponens)**.** *The **modus ponens** rule (or **rule of detachment**): From formulas A and $A \supset B$, we may derive formula B.*
Symbolically: If $\vdash A$ and $\vdash A \supset B$, then $\vdash B$.

A formula is **derivable** (or **provable**) if it can be obtained from the axioms by a finite sequence of applications of modus ponens.

Example 2.5.4 (Derivation of $A \supset A$)**.**
1. $A \supset (A \supset A)$ *(Axiom 1, with B replaced by A)*
2. $(A \supset (A \supset A)) \supset ((A \supset ((A \supset A) \supset A)) \supset (A \supset A))$ *(Axiom 2)*
3. $(A \supset ((A \supset A) \supset A)) \supset (A \supset A)$ *(Modus ponens on 1, 2)*
4. $A \supset ((A \supset A) \supset A)$ *(Axiom 1, with B replaced by $A \supset A$)*
5. $A \supset A$ *(Modus ponens on 4, 3)*

2.5.7 Derivability Relations

We write $\Gamma \vdash B$ to mean that formula B is derivable from the set of formulas Γ (using the axioms and modus ponens).

Example 2.5.5. $A, B, A \supset (B \supset C) \vdash C$
Derivation:

1. *A (given)*
2. *B (given)*
3. *$A \supset (B \supset C)$ (given)*
4. *$B \supset C$ (modus ponens on 1, 3)*
5. *C (modus ponens on 2, 4)*

Important derived rules:

$$\begin{aligned}
\text{Chain conclusion:} &\quad A \supset B, B \supset C \vdash A \supset C && (35)\\
\text{Rearrangement of premises:} &\quad A \supset (B \supset C) \vdash B \supset (A \supset C) && (36)\\
\text{Importation:} &\quad A \supset (B \supset C) \vdash A \wedge B \supset C && (37)\\
\text{Exportation:} &\quad A \wedge B \supset C \vdash A \supset (B \supset C) && (38)\\
\text{Contraposition:} &\quad A \supset B \vdash \neg B \supset \neg A && (39)\\
\wedge\text{-introduction:} &\quad A, B \vdash A \wedge B && (40)\\
\text{Weak } \neg\text{-elimination:} &\quad A, \neg A \vdash B && (41)
\end{aligned}$$

2.5.8 The Deduction Theorem

Theorem 2.5.1 (Deduction Theorem)**.** *If in propositional calculus formula B is derivable from the set of formulas Γ and A, then from Γ is derivable formula $A \supset B$.*

Symbolically: If $\Gamma, A \vdash B$, then $\Gamma \vdash A \supset B$.

2.5.9 Proof Schemes

Proposition 2.5.1 (Proof by Case Analysis)**.** *If $\Gamma, A \vdash C$ and $\Gamma, B \vdash C$, then:*

$$\Gamma, A \vee B \vdash C \tag{42}$$

Proposition 2.5.2 (Reduction to Absurdity)**.** *If $\Gamma, A \vdash B$ and $\Gamma, A \vdash \neg B$, then:*

$$\Gamma \vdash \neg A \tag{43}$$

2.5.10 Consistency and Completeness

Theorem 2.5.2. *All axioms 1–10 of propositional calculus are tautologically true formulas. Furthermore, any formula derivable from the axioms is also tautologically true.*

Definition 2.5.4 (Consistency)**.** *The axiom system is **consistent** if it is impossible to derive both a formula A and its negation $\neg A$.*

Definition 2.5.5 (Completeness)**.** *The axiom system is **complete** if every tautologically true formula is derivable.*

Theorem 2.5.3. *The axiom system of propositional calculus is both consistent and complete. Moreover, it is **maximally consistent**: adding any non-derivable formula as a new axiom would make the system inconsistent.*

This means that for any formula A of propositional calculus:

- Either A is derivable (and is a tautology), or
- $\neg A$ is derivable (and A is a contradiction), or
- Neither is derivable (and A is contingent — neither tautology nor contradiction).

The completeness theorem establishes that the syntactic notion of derivability coincides exactly with the semantic notion of tautological truth in propositional calculus.

Chapter 3

Theory of Automata

3.1 Abstract automata and automaton mappings

Let us consider alphabet transformations, realized by discrete information transformers, producing some output signal (letter of output alphabet) in response to each input signal (letter of input alphabet). Such transformers, considered irrespective to their internal structure, are customarily called **abstract automata**.

For specification of an abstract automaton there must be given three sets: **input alphabet** $\mathfrak{X}$, **output alphabet** $\mathfrak{Y}$, and **set of internal states** $\mathfrak{A}$ of the automaton, which we shall denote by letter $\mathfrak{A}$. The automaton operates in discrete time, successive moments of which it is convenient to identify with successive natural numbers $t = 0, 1, 2, \ldots$ (which can always be done, selecting in an appropriate manner the unit of time measurement).

At each given moment of discrete **automaton time** $t = 0, 1, \ldots$ automaton A is in some definite **state** $a = a(t)$ from the set $\mathfrak{A}$ of its internal states, which for brevity we shall call the **state set** of automaton A. The state $a_0 = a(0)$ at initial moment of time $t = 0$ is called the **initial state** of automaton A. If the initial state remains unchanged under any experiments with the automaton, then this automaton is called an **initial** automaton. Since, however, practically we do not consider any other automata, except initial ones, the term "initial" is often omitted.

At each moment t of automaton time, beginning with $t = 1$, at the input of automaton there arrives as the **input signal** one of the letters of the input alphabet $\mathfrak{X}$, $x = x(t)$. Finite ordered sequences of input signals $x(1), x(2), \ldots, x(k)$ of the automaton are called **input words** of this automaton. At the input of the automaton any input word from some fixed set of admissible input words may be submitted.

Any admissible input word $p = x(1), x(2), \ldots, x(k)$, submitted at the input of initial automaton A, produces at the output of automaton A_0 some output word $q = y(1), y(2), \ldots, y(k)$. The same word p, submitted to the same automaton, but with different initial states, may produce different output words.

Let us consider the case of deterministic automaton, i.e. automaton in which results of its experiments are uniquely determined. Such an automaton is specified with a single-valued **transition function** φ and a **output function** ψ, where a and x are taken respectively to mean the current automaton state and the current input signal.

The function of transitions determines the dependence of the next state $a(t+1)$ of automaton on its state $a = a(t)$ at the previous moment:

$$a(t+1) = \varphi(a(t-1), x(t)), \quad (t = 1) \tag{3.1}$$

The function of outputs determines the dependence of output signal of automaton on the same arguments:

$$y(t) = \psi(a(t-1), x(t)) \tag{3.2}$$

Given any admissible input word $p = x(1), x(2), \ldots, x(k)$ and with initial state $a(0) = a_0$ one can sequentially determine all values in the relations (3.1) and (3.2):

$$q = \psi(a_0, x(1)), \psi(a_1, x(2)), \ldots \tag{3.3}$$

Thus, correspondences (3.1) and (3.2) definitively determine an abstract way of specifying the correspondence between input and output words. An automaton is called **complete**, if its function of transitions and the function of outputs is defined for all combinations of letters $\mathfrak{X}$, $\mathfrak{Y}$, $\mathfrak{A}$ correspondingly for output word $q = y(1)$.

An automaton is called **Mealy automaton**, if it has no more than one letter $\mathfrak{Y}$ output alphabet, for example letters Λ, B, D. Since we shall limit ourselves to consideration of complete automata, an **automaton** will have output alphabet $\mathfrak{Y}$, $\mathfrak{Y}$, $\mathfrak{Y}$. The automaton is called **complete**, if its function of transitions and function of outputs is defined at all cases, constituting itself the table of transitions and table of outputs, and a complete automaton. The rows of both tables are denoted by different letters of input alphabet $\mathfrak{X}$ of the automaton, and the columns—by different states of it. At the intersection of the x-th row and the a-th column of the transition table stands element $\delta(a, x)$, i.e. some state of the automaton from the set of its internal states, and at the intersection of the x-th row and the a-th column of the output table—element $\lambda(a, x)$, i.e. some letter of output alphabet $\mathfrak{Y}$ of the automaton. Thus, with specification of transition and output tables is determined both the set $\mathfrak{X}$, $\mathfrak{Y}$, $\mathfrak{A}$, and the functions of transitions and outputs of the automaton. For fixing the initial state it is customary to mark this state with the first left column of both mentioned tables. Thus, it is possible to specify with the help of two tables arbitrary finite automata, including initial ones.

Another way of specifying finite automata, providing greater clarity, is specification of automata with the help of **directed graphs**. The vertices of the graph (depicted in figures in the form of small circles) are identified with different states of the automaton. An arrow, connecting vertex i with vertex j, means, that there exists an input signal x, transferring the automaton from state i into state j, i.e. satisfying the relation

$$j = \delta(i, x). \tag{3.4}$$

To distinguish, by which exactly input signals is caused the given transition of automaton from state i into state j, the arrow, connecting the vertices corresponding to these states of the graph, is marked with symbols of these input signals. The output signal y, determined by pair (i, x), is usually placed on the graph next to the input signal x and for distinguishing from input signals is enclosed in parentheses.

Example 3.1.1. *Let us consider an example of specifying a finite automaton with the help of the transition table and output directed graph. Let us select for this purpose a relatively simple automaton with three internal states* $1, 2, 3$*, two input signals* x*,* y *and two output signals* u*,* v*. Let us assume, that the indicated automaton is specified by the transition and output tables:*

	1	*2*	*3*
x	*3*	*3*	*3*
y	*3*	*2*	*2*

	1	*2*	*3*
x	u	u	v
y	v	v	u

These tables correspond to the directed graph, depicted in Figure 3.1.

Automata, considered by us above, are customarily called **Mealy automata** (after the name of the scientist, who first considered some questions, connected with functioning of such automata; see [1]).



Figure 3.1: Directed graph representation of a finite automaton with three states. Edge labels show input signal and output signal (in parentheses): $x(u)$ means input x produces output u.

3.1.1 Moore Automata

In practice one often has to deal also with somewhat differently defined automata, called **Moore automata** (see [2]).

Moore automata differ from Mealy automata only by the way of defining their output functions. Instead of the relation

$$y(t) = \lambda(a(t-1), x(t)),$$

defining the output signal for Mealy automata, in the case of Moore automata a somewhat different relation is used

$$y(t) = \mu(a(t)). \tag{3.5}$$

With the help of relation (3.5) and the written out relation (3.1), as in the preceding case, is determined the mapping, induced by any given Moore automaton.

By virtue of reasons, which will be considered below, the function $y = \mu(a)$ we shall call the **shifted output function of Moore automaton**. The value of this function at any state a is customarily called the **mark** of this state. Finite Moore automata are conveniently specified with the help of so-called **marked transition tables**. The marked transition table represents itself nothing other, as an ordinary transition table of the automaton, above which over the symbols of states, denoting different columns of the table, are placed the marks of these states.

Example 3.1.2. *The marked transition table*

	u	u	v
	1	*2*	*3*
x	*2*	*3*	*3*
y	*3*	*2*	*2*

specifies a Moore automaton, having the same transition table, as the Mealy automaton, whose states 1 and 2 correspond to output signal u, and to state 3—output signal v. For depiction of Moore automata with the help of graphs the symbols of output signals are marked at the corresponding vertices of the graph, and not at edges, as in the case of Mealy automata.

Let us agree to consider, that the output of output signals from Moore automaton begins from the moment of time $t = 1$ (and not from the moment of time $t = 0$). At this condition for any Moore automaton A_1 it is not difficult to construct a Mealy automaton A_2, having the same transition table and inducing the same mapping, as automaton A_1.

Indeed, if $\delta(a, x)$—is the transition function and $\mu(a)$—the shifted output function of Moore automaton A_1, then one can define Mealy automaton A_2, taking as its transition function $\delta(a, x)$, and as the output function $\lambda(a, x) = \mu(\delta(a, x))$. Then

$$y(t) = \lambda(a(t-1), x(t)) = \mu(\delta(a(t-1), x(t))) = \mu(a(t)).$$

This signifies, that automata A_1 and A_2 induce the same automaton mapping for the equal values of the initial state a_0 and any admissible input words.

It seems evident that, that the automaton A_1 is in some sense "simpler" than the automaton A_2. To show this more precisely, we must note that the response of Mealy automaton to the input signal (the corresponding output signal) depends on both the previous state and the input signal, while in Moore automaton it depends only on the state (and does not depend on the current input). From this viewpoint, Mealy automata with several output signals, in contrast to Moore automata, can be considered as producing different output signals with different delays. Practically, besides, Moore automaton structurally simpler than the corresponding Mealy automaton.

3.1.2 Equivalence of Moore and Mealy Automata

For resolution of the question posed, consisting in the identification of approaches equivalent to one and other classes of automata. Regardless of distinction between the different definitions of automata, this question for any (equivalent to Mealy) Moore automaton may be resolved differently by that, that each automaton Mealy may be put into correspondence with a Moore automaton, realizing (inducing) for input words of length not less than n ($n \geq 1$, where n—number of states of automaton) the same mapping, as initial automaton Mealy.

Let us construct Moore automaton A_2, taking in quality of its state set the set M, consisting of pairs (a, y), where a—one of possible states of automaton A, and y—one of possible letters of output alphabet of automaton A. The transition function of automaton A_2 is determined as

$$a_{12} = (a_1, y) \to (a_1, x) = (a_2, y_2), \tag{3.6}$$

where $a_2 = \delta(a_1, x)$, $y_1 = \lambda(a_1, x)$. On the output one emits $\mu((a, y)) = y$, i.e., the function given is that given element-pair outputs y. At this, for any element a complete automaton A_2 is in quality of state in complete determined automaton A, and also is an element in itself (a_0, y_0). On condition, that the output letter y_0 is chosen arbitrarily, automata A and A_2 will be equivalent in the sense, that the obtained sequences of output letters coincide. This completes the proof.

3.1.3 Properties of Automaton Mappings

It is easy to see, that the mapping φ, induced by some initial automaton Moore or Mealy, satisfies two conditions.

1. **Completeness:** Any word p in input alphabet $\mathfrak{X}$ corresponds to exactly one word $\varphi(p)$ in output alphabet (property of completeness of mapping φ, or, in other words, the property of φ being single-valued mapping).

   In the formulated conditions redundant is the requirement of uniqueness of $\varphi(p)$—it follows from the determination of automaton in quality of automaton operator.

2. **Expansion property:** If $p \subset p_1$, then $\varphi(p) \subset \varphi(p_1)$—**expansion** automaton. This means, that any word $\varphi(p)$ is an **initial segment**, i.e. the beginning, of word $\varphi(p_1)$ for any input words p, p_1, the first of which begins the second. On result—at each corresponding element is indicated producing of alphabet in Y.

Let us show, that an arbitrary **automaton mapping** is established in correspondence to some set of words in alphabet $\mathfrak{X}$ in the set of words (possibly partial) in alphabet $\mathfrak{Y}$ will be, generally speaking, a partial correspondence, corresponding not to all words in the alphabet. One considers therefore an automaton for producing conditions: if $\varphi(p)$ (understood, at a_i)—initial segment of output, 1, for $\varphi(q)$—initial output at establishing conditions, for a given word is $\varphi(p)$ is correspondingly one element of alphabet in Y.

The indicated necessary condition of automaton mapping may also be called a sufficient condition as well.

Theorem 3.1.1. *Any partial automaton mapping may be induced by some automaton.*

3.2 Events and representation of events in automata

Let A—an arbitrary (in general, partial) **recognizing** automaton—i.e., recognizer—on the correspondence. For each input word p, is **input-recognizer** $\mathfrak{Y} = (y_0, y_1)$, also y_1 of two alphabet of element-pair letters y of their input alphabet $\mathfrak{X} = (x_1, x_2, \ldots, x_m)$, to the set of events, representable in partial initial automaton A is in the quality of set M, will be called in the quality of set of events, **representable** in the given automaton A for single automaton.

It is easy to see, this at $N \leq n$, that the word is not representable in M, in which it is also at condition $Y = X$, for one at our events, for is satisfying given current output letter is word. Correspondingly also for each letter is word $x(k)$ of current value $a(k+1)$ containing word through the current of automaton $y(k)$ representing through the word means satisfying current value word. Correspondingly also all conditions is with establishing condition $x(k)$ is of automaton. Correspondingly also is of condition to in condition $y(k) =$ word containing single.

Using automaton, established by us above, one can formulate a corresponding definition.

Theorem 3.2.1. *The set of partial events, representable in initial automaton A with single alphabet $\mathfrak{X} = (x_1, x_2, \ldots, x_m)$, (consisting in this case of words $R_1, R_2, \ldots R_n$—representable in initial automaton A, for each R_i is with single event alphabet, consisting of $p_1, p_2, \ldots$, is also Λ, y_1, with alphabet in condition represented automaton partial event conditions of words $\mathfrak{Y}, \ldots$ at quality, establishing alphabet in condition automaton $\mathfrak{Y} = (y_0, y_1)$.*

3.2.1 Operations on Events

For operation given as indication, several corresponding operations represented: (uniform type, intersection).

Let us operate the **operation on concatenation of events**: designating uniform, for S_1 of word(s) output is in quality of correspondence, $S_1 \cdot S_2$ is designated, constituting of correspondence (in S_1 is established, its in operations S in M established). Intersection of event in S is established as well, at this for $S_1 \cap S_2$ is established, at the is in also established, also is in S and established in M. The $S_1 \cup S_2$ is for also with intersection is established, also for S.

The third operation is indicated with the as-established operation of **iteration**, for in establishing corresponding indicated S^+ consisting letter-sequence all possible correspondences of S, $S \cdot S$, $S \cdot S \cdot S$, ..., also i.e. is all words corresponding established words conditions, containing $i > 1$ and in iteration satisfying. Other indicated. At this designation S^+ is established with established words, containing word in $i > 0$, also is, of the iteration S^+, consisting of established word of its itself is e as type.

The operation symbol, used, applied for designation iteration $s = (x_1, x_2, \ldots, x_m)$, in that for operation correspondingly.

3.2.2 Elementary and Regular Events

For letters—$x = (x_1, x_2, \ldots, x_m)$, for **elementary** events in this alphabet is called $m+1$ single-letter events $x_1, x_2, \ldots, x_m$, and also the empty-word event e.

Definition 3.2.1 (Regular Event)**.** *This determination corresponds to determination of regular event, given above S. Kleene [3], although in form it is somewhat simpler from construction, which is known from ordinary understanding.*

Regular events corresponding to determination of regular event can be based at the word $S = (V) \vee (V_1) \vee \ldots$ *for this establishing is formula, for this correspondingly for regular alphabet events, without also and formula itself. Naturally, letter* x_1, x_2, …, x_m*—designation of elementary event corresponding to the given letter. It can be shown that also element* V *from letter in* S*, containing established formula* $\vee$, $\cdot$, $\cup$, $\subset$ *in* x*.*

Example 3.2.1. $V \vee (x)$*, as can be also type, is for containing, in particular, is determined type regular alphabet-events—containing event regular. At quality—the established regular event, constituting quality element event.*

Some examples: In quality as word of element $x_1, x_2, \ldots$*, is with satisfying conditions of this corresponding event. If this is word condition—consisting, that word is correspondingly. Also element at also corresponding event, as this is—then is also condition corresponding established.*

3.3 Analysis of finite automata

The problem of analysis consists in determining events, producing—in automaton many-letters outputs, (the case automaton Mealy) or many-letters internal states (in case automaton Moore). The analysis of automaton Moore is established also—analysis also of automaton Mealy, accordingly having approaches analysis—(less also analysis approaches Mealy).

The corresponding regularity. The algorithm of analysis for us is using in tables of transitions in outputs of analyzed automaton, and in quality of alphabet information correspondingly also regularity matching for outputs, producing produced of also matching results outputs. At the same time as defining correspondence, correspondingly condition matching K.

Considering the conditions of analyzed automaton *Mealy*—in the condition $a_1, a_2, \ldots, a_n$ (with input alphabet of conditions $x_1, x_2, \ldots, x_m$ in function is output at $\delta(a, x)$ and in function of output in $\lambda(a, x)$ automaton), we also in that for events, representing produced for conditions regularity matching, also condition k_i is in established conditions $a_i, a_2, \ldots, a_n$. In this also condition in established condition R_i is producing output established in also at sequence.

For this also is approaches in establishing condition $a_i, a_1, a_2, \ldots, a_k$ containing also is established, word is for P_a, correspondingly also is established, containing at approaches $\delta(a, x) = a_1$, also conditions in is approaches established. Also can be approaches in two types:

1. to condition y_1, corresponding automaton letters;
2. to the output word $q = y_1 q'$, at the approaches q'—for finishing word $p = x_1 p'$, at the approaches p'—is then suffix element, is also output from is condition at starting condition of event K_i.

3.3.1 Algorithm for Analysis

Definition 3.3.1 (Simple Path)**.** *For the approaches this also approaches as establishing also condition, coming at is output conditions correspondingly of internal condition* $a_i = \delta(a, x)$ *in new word* $p' = x_1 x_2 \ldots x_k$*, correspondingly correspondingly to is output is establishing in quality event* R_j*, at which also is approaches established.*

Definition 3.3.2 (Complex of Output Type)**.** ***Output type*** *is called the disjunction of all simple truncated paths, ending with pairs* $a_i x_k$*, to which correspond output signals, contained in the set* M*.*

Definition 3.3.3 (Complex of Cyclic Type)**.** ***Complex of cyclic type*** *is called the formal expression, obtained as a result of combining with the disjunction sign all simple paths of type* $a_i[a_{i_1}, a_{i_2}, \ldots, a_{i_t}]$ *with deleted letter* a_i *and enclosure of the obtained formal member into iteration brackets* ($a_i, a_{i_1}, \ldots, a_{i_t}$*—any pairwise different internal states of automaton, at* $0 \leq r \leq p-1$*, where* p*—number of internal states of automaton* A*).*

Steps of the Analysis Algorithm

First step of analysis algorithm. By tables of transitions and outputs of automaton and the given (representing) set of output signals we find by enumeration of all possible variants of simple paths the **complex** $K(M)$ of type M and complexes $K(a_i)$ for all internal states a_i of automaton A.

Second step. By complexes $K(a_i)$—excluding unwanted terms in iteration brackets we find those needed for further construction of complexes of higher cyclic types $a_i[a_{i_1}, \ldots, a_{i_t}]$ $(r > 1)$.

Third step. Starting from complex of type M, we successively replace all symbols of internal states a_i by complexes of cyclic types to obtain expression R, not containing any one of the symbols of internal states. The replacement rule can be formulated thus:

If path $a_i x_i a_t x_j a_j \ldots$ enters in complex of output type M, then letter a_i is replaced by complex of type a_i, letter a_j—by complex of type $a_j[a_i]$, letter a_t—by complex of type $a_t[a_i, a_j]$ and so on. If member $x_i a_i x_j a_j \ldots$ enters in complex of type $a_i[N]$, where N—set (possibly empty) of internal states, different from a_i, then letter a_j is replaced by complex of type $a_j[a_i, N]$, letter a_t—by complex of type $a_t[a_i, a_j, N]$ and so on.

At the third step, in the result of applying a finite number of times the replacement rule, we obtain the sought regular expression R for the event, represented in automaton A by set M of output signals.

From the described algorithm directly follows the following proposition.

Theorem 3.3.1. *Any event, represented in a finite automaton Mealy (or Moore), having n internal states, admits a regular expression, the cyclic depth of which does not exceed n.*

Example 3.3.1 (Analysis of an Automaton)**.** *As an example let us find a regular expression for event S, represented by output signal v in automaton, the tables of transitions and outputs of which were written out in § 3.1 of this chapter (its graph is depicted in Figure 3.1).*

Directly by tables we find ***complex*** $K(v)$ *of type v:*

$$K(v) = 1y \vee 1y_3x \vee 1x_2x_3x$$

and complexes of types 1, 2 and 3:

$$K(1) = e, \quad K(2) = \{y \vee x_3y\}, \quad K(3) = \{x \vee y_2x\}.$$

Let us write out some complexes of higher cyclic types:

$$K(2[1]) = K(2); \quad K(3[1,2]) = \{x\};$$

$$K(2[3]) = K(2[1,3]) = \{y\}; \quad K(3[1]) = K(3).$$

Denoting the operation of inserting complexes by an arrow, we obtain the following succession of insertions:

$$\begin{aligned} K(v) &\to y \vee yK(3[1])x \vee xK(2[1])xK(3[1,2])x \\ &= y \vee y\{x \vee y_2x\}x \vee x\{y \vee x_3y\}x\{x\}x \\ &\to y \vee y\{x \vee yK(2[1,3])x\}x \vee x\{y \vee xK(3[1,2])y\}x\{x\}x \\ &= y \vee y\{x \vee y\{y\}x\}x \vee x\{y \cdot x\{x\}y\}x\{x\}x. \end{aligned}$$

The last of the obtained regular expressions is the sought regular expression for event S. It admits transformations and simplifications with use of correspondences, existing in the algebra of events.

3.4 Abstract synthesis of finite automata

The problem of abstract synthesis is opposite to the problem of analysis of finite automata: it is necessary to find an effective method, allowing by regular expressions of events to find tables of transitions and outputs of some finite automaton, representing the given events.

The task of synthesis of Moore automata is more general, than the task of synthesis of Mealy automata: since any Moore automaton can be interpreted as a Mealy automaton, then, having learned to synthesize Moore automata, we thereby also learn to synthesize Mealy automata. We shall therefore solve the task of synthesis of Moore automata.

Let in some finite alphabet $\mathfrak{X} = (x_1, x_2, \ldots, x_n)$ be given p regular expressions $R_1, R_2, \ldots, R_p$. We number all occurrences of letters of alphabet $\mathfrak{X}$ in expressions $R_1, R_2, \ldots, R_p$ by consecutive natural numbers, which in the further we shall call **indices of corresponding places** of these expressions. Especially let us emphasize, that different occurrences of one and the same letter of alphabet $\mathfrak{X}$ obtain at this different indices.

When expanding a regular expression into a word, each of the successively written out letters of this word we identify with this or another occurrence of the corresponding letter in the expanded expression.

3.4.1 Synthesis Procedure

That is, that is included in one place of the corresponding regular expression. This means, that to j-th place of regular expression $\mathfrak{X}_i$, satisfying given letters, at the same time if the given condition is established of corresponding $\mathfrak{X}_i$ also is indicating conditions of correspondingly the last letter of word a to, we consider, that is j in place M satisfies at correspondingly at given, correspondingly at $\wedge$—at is for at, at is following places regular expression, and namely: at the establishing the last written out letter with included, with numbered by index j, will be condition.

The last of the obtained regular expressions is the sought regular expression for event S and satisfies for is for event one also at in type at corresponding.

Now let us also given conditions approaches at alphabetically in V_a is corresponding at is given at any in V_a in also approaches at correspondingly establishing approaches $R_1, R_2, \ldots, R_n$, V_i at—is approaches at event in S for approaches corresponding, given this at is regular is conditions—is at also at the given word is at establishing correspondingly, where approaches for at is this indices, then is called in the established at each approaches are at our at, approaches at is approaches at $\mathfrak{Y}$, at its approaches. For at is at in approaches in is for indices at this our given is correspondingly in approaches also in is approaches given at regular expressing at in $\mathfrak{X}$.

To say, that *it is represented* (at any choice in quality of initial state (j) of one of given events $R_1, R_2, \ldots, R_n$, at also approaches S at its approaches. Obviously, S is then representing in approaches event, and for representing at approaches given at correspondingly is at also approaches for given at correspondingly at is at our approaches.

Building of automaton Moore A, correspondingly consisting at is approaches at is approaches of establishing is establishing at at also events $R_1, R_2, \ldots, R_n$ (at also is approaches at our established at is single-letter approaches, corresponding—correspondingly is at approaches this types (at is correspondingly). At is at in is approaches correspondingly for approaches at also our approaches establishing, at also at M_a)—at is approaches at at in regular approaches approaches, at is approaches is approaches at our a_i is approaches at correspondingly. At is approaches at is approaches at our approaches is conditions at our approaches, at approaches for at our approaches.

The function of transitions and function of outputs of automaton Moore A is produced for output alphabet D, consisting at approaches of all possible approaches of at regular expressions R_i (at also p_i) selections—for this at regular expressions R_i, R_i, …, for which is approaches in type of e as establishing.

Finding output conditions of finite initial automaton Moore A. At this approaches of output signals will serve letters of automaton A, and in quality is conditions is approaches at approaches in table of transitions at established A.

3.4.2 Synthesis Example with Partial Automaton

The described method allows at also types of decision for problem of partial events. Only for this approaches one need to accept in also approaches, and it is need not this types establishing at previous work of approach. The problem consists at one, that to build what in also at—types for approaches at its in established at its at in also at correspondingly.

$$R = S\{x_1 \vee x_2 \vee \ldots \vee x_n\}.$$

If originally given expression for the prohibition region does not satisfy this condition, it should be replaced by expression

$$R = S\{x_1 \vee x_2 \vee \ldots \vee x_n\}.$$

Example 3.4.1 (Synthesis of Partial Automaton)**.** *As an example let us consider synthesis of partial automaton Mealy, representing event $R = x\{y\}$, with presence of prohibition region $S = yx\{x \vee y\}$. At the first step we perform marking of places, indexation and distribution of indices in expressions R and S, using possibility of identification of similar places:*

$$R = |\underset{0}{x}|\{|\underset{1}{y}|\}$$

$$S = |\underset{0}{y}|\underset{2}{x}\{|\underset{3}{x}| \vee |\underset{3}{y}|\}$$

Performing the second and third steps of algorithm, we come to the ***marked*** *table of transitions of Moore automaton*

	$-R$		$-S$		
	0	*1*	*2*	$*$	*3*
x	*1*	$*$	*3*	$*$	*3*
y	*2*	*1*	$*$	$*$	*3*

At the fourth step we introduce redesignations $0 \to 1$, $1 \to 2$, $2 \to 3$, $* \to 4$, $3 \to 5$, $() \to u$, $R \to v$, $S \to w$ *(brackets () here designate empty set of symbols R and S). After this we obtain the marked table of transitions*

	u	v	u	u	w
	1	*2*	*3*	*4*	*5*
x	*2*	*4*	*5*	*4*	*5*
y	*3*	*2*	*4*	*4*	*5*

Performing at the fifth step the transition to Mealy automaton, we obtain tables of transitions and outputs

	1	*2*	*3*	*4*	*5*
x	*2*	*4*	*5*	*4*	*5*
y	*3*	*2*	*4*	*4*	*5*

	1	*2*	*3*	*4*	*5*
x	v	u	—	u	—
y	u	v	u	u	—

Finally, we perform transition to partial automaton. Prohibited in this case should be considered signal w. Then the tables of transitions and outputs will have the form

	1	2	3	4	5
x	2	4	—	4	—
y	3	2	4	4	—

	1	2	3	4
x	v	u	—	u
y	u	v	u	u

However state 5 is superfluous, since the automaton will never enter into it, starting from initial state 1. Discarding this superfluous state, we come to the final tables of transitions and outputs

	1	2	3	4
x	2	4	—	4
y	3	2	4	4

	1	2	3	4
x	v	u	—	u
y	u	v	u	u

3.5 Minimization of abstract automata

As indicated above, an abstract automaton is considered by us as a device for realization of automaton mappings. In connection with this it is natural not to distinguish automata, equivalent between themselves, i.e. automata, inducing identical mappings.

The main task, solved in this paragraph, is the task of minimization of automata, i.e. the task of finding automaton with minimal number of states in the class of all automata, equivalent to the given one. The presented methods of solving this task represent themselves development of ideas of Mealy [1], Aufenkamp and Hohn [4, 5].

3.5.1 Equivalence of States

Definition 3.5.1 (1-equivalence)**.** *Let a and b—two states of one and the same or two different Mealy automata, having common input and common output alphabet. If for any input signal x_i the output signals, determined by pairs (a, x_i) and (b, x_i), are identical, then states a and b are called **1-equivalent**.*

Definition 3.5.2 (i-equivalence)**.** *If 1-equivalent states are transformed by any input signal x_i also into 1-equivalent between themselves states, then they are called **2-equivalent**. If 2-equivalent states are transformed by any input signal into 2-equivalent between themselves states, then they are called **3-equivalent**, and so on.*

It is easy to understand, that i-equivalent states in case of application to them of any word of output alphabet length also i and in produces uniform single output words (at $i = 1, 2, \ldots$).

The definition of i-equivalence for all $i = 1, 2, \ldots$ gives possibility to introduce reflexive, symmetrical and transitive relation between states of given Mealy automaton. For each of classes can be called **classes** of i-equivalence.

Definition 3.5.3 (Equivalence)**.** *States, i-equivalent for all $i = 1, 2, \ldots$, are simply called **equivalent**.*

Lemma 3.5.1. *Two automata Mealy model and also modeling equivalent between themselves, if and only if for each state of one is found an equivalent to it state of the other.*

The proof of this lemma is trivially obtained from the definition of equivalence of two states, consisting in the coincidence of output signals produced by them at any given input signal, and in i-equivalence of states, in which our two compared states are transformed at action on them of the given input signal.

Thus, for any automaton Mealy A, with finite number m of internal states there is reached the stabilization of classes of equivalence, for $i \leq m$ at most classes, starting from some $i = k$. More precisely, if two states a and b are m-equivalent, they are also $(m + j)$-equivalent for any $j = 0, 1, 2, \ldots$

3.5.2 Construction of Minimal Automaton

Let us consider now a new automaton Mealy $A_{\min}$, each internal state K_i of which is a class of equivalence of the original automaton A. The transitions from K_i at input signal x let us determine, taking into account that by action of this signal any state of class K_i is transformed into some state of the definite class K_j.

For the realization of automaton mappings it is sufficient the correct functioning of automaton, restricted of at classes of also minimized automaton signals.

Theorem 3.5.1. *In each equivalence class of any automaton Mealy there is one and only one automaton with minimal number of internal states—the minimized automaton of this class.*

Theorem 3.5.2 (Aufenkamp–Hohn Criterion)**.** *If for minimization with i-splitting of an $(i+1)$-splitting into 1-classes is achieved, then it is also in $(i+2)$-classes.*

States a_i and a_j are only $(i+1)$-equivalent, but not $(i+2)$-equivalent between themselves.

For obtaining Aufenkamp–Hohn criterion of class of equivalence it is sufficient to look at realization obtained by m-splitting on $m+1$-classes equivalent class k-equivalent. Since if partitioning reached at $(i+1)$-splitting equivalently of i-splitting, then in k-classes at all $i = 1, 2, \ldots$ At the same time all not k-equivalent pairs of states are discerned above in k-classes.

3.5.3 Algorithm for Minimization

Thus, algorithms for minimization of automata include as first step the examination in A on 1-classes equivalent by identity of input rows in table of outputs.

Make tables of 1-splitting obtained at this step using transitions for internal states corresponding to 1-classes. Transitions for those states, joined into one 1-class, are also joined, and the union with single 1-class constitutes transition to this 1-class.

At the following 2-splitting corresponding to 2-equivalence, we have obtained, that 1-class, corresponding to some array of transitions, correspondingly splits into those 1-subclasses, having various transitions, and transitions by which one was established correspondingly.

Read through larger number of steps, and is partitioned on m-classes, where $m \leq n$, n is representing all registered internal states of automaton Mealy or automaton.

3.5.4 Minimization of Moore Automata

The theory of minimization of automaton Moore is also analogous to theory of minimization of automaton Mealy. In this case states are determined equivalent for each.

Hence for minimization of automaton Moore it remains the same as for automaton Mealy. Theorem is valid, regarding i-classes, partitioning, at $i \geq 2$, various equivalent classes of automaton Moore.

For practical procedure, well satisfied for this condition, is for automaton Moore 0-equivalent states a condition and is combined 1-equivalent also at 0-classes. D-equivalent Moore consists at all their at 0-classes. At equivalent Moore condition classes are similar at at 1-classes.

3.5.5 Minimization of Partial Automata

The problem is algorithmically solvable. However the existing methods of its exact solution are connected with large enumeration (see, for example, S. Ginzburg [6]) and therefore practically scarcely suitable.

In practice usually the following method of minimization of partial automata is used: mentally filling in the crossed out places in tables of transitions and outputs of given partial automaton A, we join states into i-classes and minimize by the same rules, as in the case of ordinary (everywhere defined) automata. All or some of the variants of joining states into classes arising

from this are checked, and from the obtained canonical minimizations we select the one, which has the smallest number of states.

The indicated method actually solves the problem of constructing partial automaton B with smaller number of states, than the original automaton A, where the partial automaton mapping φ induced by automaton B coincides with partial automaton mapping φ, induced by automaton A at the definition region of mapping φ. At this the region of definition of mapping ψ, generally speaking, is larger than region of definition of mapping φ.

Example 3.5.1 (Minimization of Partial Automaton)**.** *We show, how the described method of minimization works on the example of partial automaton Mealy A, given by the following tables of transitions and outputs:*

	1	*2*	*3*	*4*
x	*2*	—	*2*	*4*
y	—	*3*	*4*	*4*

	1	*2*	*3*	*4*
x	u	—	u	u
y	—	u	v	v

Minimizing the given automaton, we obtain two original possibilities for joining into 1-classes, leading to the smallest quantity of classes:

$$a_1 = (1, 3, 4), \quad b_1 = (2) \quad \textit{and} \quad a_1 = (1, 2), \quad b_1 = (3, 4).$$

We consider first the first possibility: 1-table is written

	1	*2*	*3*	*4*
x	b_1	—	b_1	a_1
y	—	a_1	a_1	a_1

From the 1-table it is seen, that class a_1 needs to be "divided into two" 2-classes: $a_2 = (1, 3)$ and $c_2 = (4)$; the third 2-class b_3 coincides with 1-class $b_1 = (2)$. ***2-table*** *will have the form:*

	1	*2*	*3*	*4*
x	b_2	—	b_2	c_2
y	—	a_2	c_2	c_2

from which it follows, that the obtained partition into 2-classes further does not become finer and, consequently, coincides with partition into ∞-classes. Canonical minimization in this variant will be given by the tables

	a_2	b_2	c_2
x	b_2	—	c_2
y	b_2	c_2	c_2

	a_2	b_2	c_2
x	u	—	u
y	u	v	v

In the second variant of minimization the partition into ***1-classes*** *$a_1 = (1, 2)$ and $b_1 = (3, 4)$ leads to* ***1-table***

	1	*2*	*3*	*4*
x	a_1	—	a_1	b_1
y	—	b_1	b_1	b_1

and to partition into ***2-classes*** *$a_2 = (1, 2)$; $b_2 = (3)$; $c_2 = (4)$.* ***2-table*** *is written*

	1	*2*	*3*	*4*
x	a_2	—	a_2	c_2
y	—	b_2	c_2	c_2

from which it follows, that the obtained partition into 2-classes further does not become finer and, consequently, coincides with partition into ∞-classes. Canonical minimization in this variant will be given by the tables

	a_2	b_2	c_2
x	a_2	—	c_2
y	b_2	c_2	c_2

	a_2	b_2	c_2
x	u	—	u
y	u	v	v

The obtained canonical minimizations are substantially different: the first reacts to input word y with output word v, and the second—with output word u.

3.6 Structural synthesis of finite automata

At the stage of structural synthesis are selected elementary automata, from which is carried out synthesis of the structural scheme of given abstract automaton Mealy or Moore. We shall assume, that elementary automata are of two types: **elementary automata with memory**, or **memory elements** (triggers, delay lines, etc.), and **elementary automata without memory**, called also **logical elements**. For simplicity we limit ourselves to the case, when at our disposal is only one type of memory elements.

Input and output signals, as also the elementary automata as a whole, are designated (encoded) with finite sequences of letters of some fixed finite alphabet, called **structural alphabet**. Usually in quality of structural alphabet is selected **binary alphabet**, consisting of two letters: 0 and 1. The second alphabet, playing an important role at the stage of structural synthesis, is the alphabet, consisting of symbols of internal states of the original elementary memory element. Let us call this alphabet **encoding alphabet**. An encoding of states cannot coincide with a structural alphabet.

3.6.1 Encoding and Excitation Functions

One of the main tasks, solved in the process of structural synthesis of given abstract automaton, is to establish correspondences between signals, consisting of letters of structural alphabet, in the process of establishing correspondences between elements of abstract automaton Mealy and Moore. The **Mealy-Moore** method of actual approach established for encoding signals, corresponding to each letter of input signal x_i, x_2, …, x_n and to signals, corresponding to each of the exit signal, y_1, y_2, …, y_m. Input signals of the encoding alphabet are located in one row of the input, as a whole. The same encoding, corresponding to each exit signal, produces each of the output signals y_1, y_2, …, y_m of automaton. Actually in the method produces all the method-automaton elements of automaton.

Definition 3.6.1 (Excitation Function)**.** *We indicate, that Ψ, determining the usual encoding function-excitation, we shall also call the **excitation function of memory element**. Each of the encoding functions φ^j, φ^j, where $j = 1, 2, \ldots, s$, determines the excitation signal of j-th memory element in the composition of structural automaton, therefore these functions are naturally also called **excitation functions of structural automaton**.*

Definition 3.6.2 (Output Function)**.** *In the composition of structural automaton, besides excitation functions, also has a series of functions, which we shall call **output functions**. Let symbol $y_{i\beta}$, where $i = 1, 2, \ldots, m$, $\beta = 1, 2, \ldots, k$, denotes the β-th letter of encoding word, assigned to letter y_i of output alphabet $\mathfrak{Y}$ of given automaton A. Then the function*

$$y_{i\beta} = \varphi^{i\beta}(z^1, z^2, \ldots, z^s, x_1, x_2, \ldots, x_n),$$

*expressing the β-th letter of i-th output signal as a function of state codes and input signals, is called the (i, β)-th **output function**.*

Analogously is defined the excitation output function $y_{i\beta} = \varphi^{i\beta}(z)$, determining the (i, β)-th letter of signal output function at automaton A in the time, when automaton A is in state $(z^1, z^2, \ldots, z^s)$.

Function y_a^j in $y_{i\beta}$, which we have defined, we shall correspondingly call **excitation functions of structural automaton**, and **output functions of structural automaton**.

3.6.2 Types of Memory Elements

Let us consider the case, when full automaton Moore with two states 0 and 1 has only two input signals—x and y. From conditions of completeness it follows, that in each column of transition table of automaton should appear both states—0 and 1. This constraint leads to that, there exist in total only 4 possible transition tables

	0	1
x	0	0
y	1	1

	0	1
x	0	1
y	1	0

	0	1
x	1	1
y	0	0

	0	1
x	1	0
y	0	1

After redesignation of input signals the third table coincides with the first, the second—with the fourth. Thus, there are only two substantially different automata of the required type, given by transition tables

	0	1
x	0	0
y	1	1

and

	0	1
x	0	1
y	1	0

If we put $x = 0$, $y = 1$, then the first table specifies a well-known memory element, called **delay element** (by one clock cycle), and the second—a no less well known element, called **trigger with counting input**. Let us note, that an ordinary electromagnetic relay with a closing contact can be considered as delay element.

At increasing the number of input signals new types of memory elements appear: **trigger with separate inputs**, given by transition table

	0	1
x	0	1
y	0	0
z	1	1

Combined trigger, given by table

	0	1
x	0	1
y	0	0
z	1	1
u	1	0

and others.

Substantially different types of automata, the transition tables of which do not transition one into another at redesignations of input signals). Besides the listed four types of automata, into this catalog will also enter three more automata, given by transition tables

	0	1
x	0	1
y	0	0
z	1	0

	0	1
x	0	1
y	1	1
z	1	0

	0	1
x	0	0
y	1	1
z	1	0

3.6.3 Full Synthesis Example: Sequential Binary Quadrator

Of course, each of the listed types of automata admits various modifications at the expense of different coding of input signals in the binary alphabet. Let us consider as an example the full synthesis (abstract and structural to obtaining canonical equations) of automaton Moore A, representing itself a sequential binary quadrator. Automaton A works in the following way: at its input bit by bit, beginning with least significant bits, is submitted a two-digit binary integer. At the output of automaton also sequentially, beginning with least significant bits, should appear the square of this number. In other words, automaton A should realize the following partial mapping φ:

$$0000 \to 0000$$
$$1000 \to 1000$$
$$0100 \to 0010$$
$$1100 \to 1001.$$

It is not hard to verify, that mapping φ, extended to initial segments of words, satisfies the automaton condition. Denoting the zero signal at input by letter x, and at output—u, and correspondingly the unit signal at input—y, and at output—v, we write this correspondence in the form

$$xxxx \to uuuu$$
$$yxxx \to vuuu$$
$$xyxx \to uuvu$$
$$yyxx \to vuuv.$$

In the obtained correspondence with output signal u is represented event $R = x \vee xx \vee xxx \vee yx \vee yxx \vee xyx \vee xyxx \vee yy \vee yyx$. Words, not entering into event R and Q, are forbidden. At the expense of forbidden words one can increase these events without fear of disturbing in the synthesized automaton its reaction to given words.

Since events R and Q do not intersect, it is possible on the basis of the above to replace event R by complement Q' of event Q. In such a case the automaton can be synthesized for only one event Q: event Q' will turn out to be automatically represented by the set of all unmarked states of this automaton. Keeping in mind, that for marking states one way or another the symbols u and v will be used subsequently, let us denote event Q by letter v, and its complement Q'—by u.

The process of abstract synthesis leads to the following marking of regular expression for event $Q = v$:

$$v = \left|\left(\underset{0}{y} \vee \underset{1\,2\,3}{xyx} \vee \underset{4\,1\,5\,6\,4}{yyxx}\right)\right|$$

Here one and the same basic indices are assigned to pairs of corresponding places (index 1) and to pairs of similar places (index 4). The marked transition table of automaton, corresponding to the performed marking, is written

	u	v	u	u	v	u	u	
	0	1	2	3	4	5	6	*
x	2	*	*	4	*	6	4	*
y	1	5	3	*	*	*	*	*

Since the initial state 0 represents only the empty word, its mark may be considered undefined.

After redesignation of states (*) we obtain the table:

	—	v	u	u	v	u	u	
	0	1	2	3	4	5	6	7
x	2	7	7	4	7	6	4	7
y	1	5	3	7	7	7	7	7

The set of states of automaton Moore, given by the last table, can be divided into two 0-classes: $a_0 = (0, 2, 3, 5, 6, 7)$ and $b_0 = (1, 4)$. We build 0-table and from it determine 1-classes:

$$a_1 = (0), \quad b_1 = (1, 4), \quad c_1 = (2, 5, 7), \quad d_1 = (3, 6).$$

We build 1-table and determine 2-classes:

	0	1	2	3	4	5	6	7
	a_1	b_1	c_1	d_1		c_1	d_1	c_1
x	a_1	a_1	a_1	b_1	a_1	b_1	a_1	
y	b_1	c_1	d_1	c_1	c_1	c_1	c_1	

$$a_2 = (0), \quad b_2 = (1, 4), \quad c_2 = (2), \quad d_2 = (3, 6);$$

$$e_2 = (4), \quad f_2 = (5), \quad g_2 = (7).$$

2-table and **3-classes** will have the form

	0	1	2	3	4	5	6	7
	a_2	b_2	c_2	d_2				g_2
x	c_2	g_2	g_2	b_2	g_2	d_2	b_2	g_2
y	b_2	f_2	d_2	g_2	g_2	g_2	g_2	g_2

$$a_3 = (0), \quad b_3 = (1), \quad c_3 = (2), \quad d_3 = (3, 6);$$

$$e_3 = (4), \quad f_3 = (5), \quad g_3 = (7).$$

Since 3-classes coincide, as is easy to verify, with 4-classes, they will also be ∞-classes, so that the automaton can be simplified at the expense of combining states 3 and 6. After corresponding renumeration of states the marked transition table of the sought automaton Moore is written

	—	v	u	v	u	u	
	1	2	3	4	5	6	7
x	3	7	7	7	6	4	7
y	2	5	6	7	7	7	7

3.6.4 Structural Synthesis with Delay Elements

Proceeding to structural synthesis, we select as memory elements **delay lines** with transition table

	0	1
0	0	0

Since the synthesized automaton has 7 states, and the memory element—2 states, one should select 3 memory elements ($2^3 > 7$). We denote their internal states by letters z_1, z_2, z_3, and input signals—s_1, s_2, s_3 (all these values may take values 0 and 1). The states of automaton A we denote by values of vector (z_1, z_2, z_3). We select the so-called natural system of state encoding, at which each state is encoded by writing of its number in binary number system

$$1 = 001; \quad 2 = 010; \quad 3 = 011; \quad 4 = 100; \quad 5 = 101; \quad 6 = 110; \quad 7 = 111.$$

Let us denote the physical input signal of automaton A by letter c, the physical output signal—d and rewrite the marked transition table of this automaton in correspondence with the accepted system of coding (such table is usually called the **physical** transition table of automaton, as opposed to the **abstract** transition table considered earlier)

d	—	1	0	1	0	0	0
z	001	010	011	100	101	110	111
c							
0	011	111	111	111	110	100	111
1	010	101	110	111	111	111	111

The obtained physical transition table of automaton specifies states $z'_1 = z_1(t+1)$, $z'_2 = z_2(t+1)$, $z'_3 = z_3(t+1)$ of memory elements at each subsequent moment of time $t+1$ as Boolean functions of their states $z_1 = z_1(t)$, $z_2 = z_2(t)$, $z_3 = z_3(t)$ and input signal $c = c(t)$ of automaton A at the present moment of time t. From transition table of delay element it is seen, that its state at any subsequent moment of time $t+1$ coincides with signal at its input at the present moment of time. Therefore one may consider, that the written out table specifies structural excitation functions of sought automaton A

$$s_i = \sigma_i(z_1, z_2, z_3, c) \quad (i = 1, 2, 3).$$

The value tables, determining correspondingly functions s_1, s_2, s_3, we write out at once in the form of Karnaugh maps (see § 4 ch. II)

z_3c / z_1z_2	00	01	11	10
00	—	—	0	0
01	1	1	1	1
11	1	1	1	1
10	1	1	1	1

z_3c / z_1z_2	00	01	11	10
00	—	—	1	1
01	1	1	0	1
11	1	1	1	1
10	1	1	1	1

z_3c / z_1z_2	00	01	11	10
00	—	—	0	1
01	1	1	0	1
11	0	1	1	0
10	1	1	1	0

By methods, developed in the previous chapter, we find **minimal disjunctive normal forms** for excitation functions (input signals of memory elements) of automaton A

$$s_1 = z_1 \vee z_2;$$
$$s_2 = z_3 \vee \bar{z}_2 \vee \bar{z}_1\bar{c} \vee z_1c;$$
$$s_3 = z_1c \vee z_1z_2z_3 \vee \bar{z}_2\bar{z}_3 \vee \bar{c}z_3 \vee \bar{z}_1\bar{c}.$$

3.6.5 Output Function

Transition table of automaton A. Karnaugh map for this function is written

z_3 / z_1z_2	0	1
00	—	—
01	1	0
11	0	0
10	1	0

From the Karnaugh map one easily finds the **minimal disjunctive normal form**, specifying the required output function d:

$$d = \bar{z}_1\bar{z}_3 \vee \bar{z}_2\bar{z}_3.$$

Let us note, that all our functions turned out to be determined not at all sets and we further determined them in such a way, in order to obtain as simple as possible representations for them.

3.6.6 Circuit Implementation

Let us introduce in quality of logical elements inverters, and also two-input coincidences and separations. Denoting them by circles with symbols of corresponding operations $\neg$, $\wedge$, $\vee$, and memory elements (delays) by squares with letters z_1, z_2 and z_3 inside, we obtain scheme of automaton A, which is depicted in Figure 3.2.



Figure 3.2: Structural scheme of automaton A: 3 delay elements (squares with z_1, z_2, z_3), 4 inverters ($\neg$), 5 AND gates ($\wedge$), and 7 OR gates ($\vee$). Total: 16 logical elements and 3 memory elements.

This scheme besides three delay elements includes 4 inverters, 5 coincidences and 7 separations (in total 16 logical elements and 3 memory elements).

Bibliography

[1] G.H. Mealy, “A Method for Synthesizing Sequential Circuits,” Bell System Technical Journal, vol. 34, no. 5, pp. 1045–1079, 1955.

[2] E.F. Moore, “Gedanken-experiments on Sequential Machines,” in Automata Studies, C.E. Shannon and J. McCarthy, Eds. Princeton University Press, 1956, pp. 129–153.

[3] S.C. Kleene, “Representation of Events in Nerve Nets and Finite Automata,” in Automata Studies, C.E. Shannon and J. McCarthy, Eds. Princeton University Press, 1956, pp. 3–42.

[4] D.D. Aufenkamp and F.E. Hohn, “Analysis of Sequential Machines,” IRE Transactions on Electronic Computers, vol. EC-6, pp. 276–285, 1957.

[5] D.D. Aufenkamp and F.E. Hohn, “Analysis of Sequential Machines II,” IRE Transactions on Electronic Computers, vol. EC-6, pp. 276–285, 1957.

[6] S. Ginzburg, An Introduction to Mathematical Machine Theory. Addison-Wesley, 1962.

Chapter 4

Self-Organizing Systems

4.1 The concept of self-modification and self-organization in automata

With the concept of algorithm and discrete automaton is usually connected the representation about their invariance in time. The corresponding alphabetic mappings are represented as something rigid, once and forever given. In relation to the classical understanding of algorithm and to the ordinary understanding of the method of functioning of discrete automaton such a representation is in some measure well-grounded. At the same time it is no secret, that the most perfect of the modeled in present time self-organizing systems are modeled on universal electronic digital machines, representing themselves nothing other, as discrete automata with "rigid" structure, with the help of programs, which in their essence are records of algorithms in some special form.

The apparent contradiction here is only apparent. The truth consists in that, the distinction between "rigid" and "self-modifying" information transformers in most cases is rather conditional and is determined not so much by construction of the transformer itself, but by organization of experiment with it. One and the same information transformer in some conditions should be considered as rigid, invariant, and in others—as self-modifying and self-organizing.

For refinement of what has been said let us consider an arbitrary discrete automaton A with input alphabet $\mathfrak{X}$, output alphabet $\mathfrak{Y}$, set of internal states $\mathfrak{A}$ and initial state a_0. The usual representation about the character of functioning of automaton implicitly presupposes, that after submission at its input of some word p in alphabet $\mathfrak{X}$ and obtaining of corresponding output word $q = \zeta(p)$ in alphabet $\mathfrak{Y}$ the automaton returns to initial state. Thus, at the moment of beginning of submission of each new input word the automaton turns out to be always in one and the same state a_0. Thanks to this the mapping induced by automaton mapping ζ is indeed, as a rule, representing itself in the sense of usual terminology somewhat rigid, unchanging in process of operation.

The just described representation, however, is not the only one, which can be connected with a given automaton. Let us consider another "experimental setup", in which each next input word serves continuation of the previous one, and the result of transformation of all of word ξ obtained up to given moment considered for each moment is the output word obtained before this moment. The division of entire input flow into separate words in this case may be done, for example, in the following way: at the entry of automaton is submitted symbol ξ from alphabet $\mathfrak{X}$, the automaton responds on it with one or another symbol from the output alphabet. The concrete form of response depends in general both from the symbol itself ξ and from the internal state, in which automaton found itself at moment of receiving symbol.

Definition 4.1.1. *Such an action of submitting symbol and receiving response we shall call* question *(or* stimulus*), and the response of automaton shall be called* answer *(or* reaction*).*

The automaton on each question gives strictly defined answer and can in process of answering change or not change its internal state.

Definition 4.1.2. *The automaton is said to possess the capability of* self-modification*,* self-organization*, or else* learning *(in the broadest sense of this word), if in conditions established beforehand it can itself improve the quality of its functioning.*

This definition is rather general and abstract and may be filled with various concrete content depending on conditions of the problem.

However, it is necessary to keep in mind, that even automata with a quite narrow interpretation of the notion of self-organization do not obligatorily improve quality of answers with each successive stimulus. The point is that the very question may already contain information about what (for the given concrete automaton) constitutes good and what bad quality of answer. In such cases training can consist in "test" attempts, and training of automaton towards improvement of quality of answers can happen as result of training on incorrect answers.

For any state a of automaton A and input letter $x \in \mathfrak{X}$, let the state into which the automaton A goes to under action of signal x, being in state a, be denoted $a'(1)$. Thus denoting by M' the set of all states a obtainable from a, successively inputting signal sequences.

Theorem 4.1.1. *For a discrete automaton A with given cyclization to be rigid (i.e. not changing its answers to one and the same questions with the passage of time), it is necessary and sufficient, that after cyclic reduction the function of outputs $\lambda'(a, x)$ would not depend on states of the reduced automaton A'.*

Independence of function of outputs from states of automaton means, obviously, equality among themselves of all elements of each row of table of outputs of this automaton.

Definition 4.1.3. *The automaton with output independent of state is called* completely rigid automaton*.*

The study of process of self-organization is itself undertaken upon its presentation as a process of another type: with operation of automaton (algorithm). The simplest case of such a system consists of two automata (algorithms). From here we get the term used in general algorithm approach: *automaton-teacher*, and the second algorithm as *automaton-student* (or *learner*).

4.2 Some preliminary information from probability theory

In this section the reader is presented some necessary information from probability theory, required for further reading.

Definition 4.2.1. Random *is called such magnitude whose concrete value is not defined beforehand.*

Very important is distinction between *discrete* and *continuous* random variables. Discrete random variable is such that can assume only a countable set of numerical values.

The domain of definition of discrete random variables we consider may be either finite, or countably infinite. In both cases, obviously, the condition of normalization is satisfied

$$\sum_i f(x_i) = 1, \tag{4.1}$$

where summation is assumed extended over the entire domain of definition of the given random variable.

When random variable x is continuous, the law of its distribution is given with the help of so-called *probability density function* $\varphi(x)$. This function is assumed to be defined in domain M of

definition of considered random variable x and integrable in this domain. At each successive trial the probability $p(N)$ of that the random variable x assumes value from some subdomain N of its domain of definition, equals the integral over probability density, taken over this subdomain:

$$p(N) = \int_N \varphi(x)\,dx. \tag{4.2}$$

From here it directly follows that the normalization condition should be satisfied

$$\int \varphi(x)\,dx = 1. \tag{4.3}$$

Definition 4.2.2. *Two random variables x and y are called* independent of each other*, if the assumption by variable x of this or another value does not change the law of distribution of variable y and vice versa.*

Definition 4.2.3. *Trials, conducted with this or another random variable x, are called* independent trials*, if the law of distribution of variable x remains unchanged at each trial and does not depend, consequently, from values, which variable x assumed in previous trials.*

Let $\vec{x} = (x_1, x_2, \ldots, x_n)$—$n$-dimensional continuous random variable with probability density function $\varphi(x_1, x_2, \ldots, x_n)$. Then *mean value* of random variable x is defined as vector $\vec{m} = (m_1, m_2, \ldots, m_n)$, calculated by formula

$$\vec{m} = (m_1, m_2, \ldots, m_n) = \int\int\cdots\int \vec{x}\,\varphi(x_1, x_2, \ldots, x_n)\,dx_1\,dx_2\cdots dx_n. \tag{4.4}$$

Central moments of second order λ_{ik} are defined by formulas

$$\lambda_{ik} = \int\int\cdots\int (x_i - m_i)(x_k - m_k)\,\varphi(x_1, x_2, \ldots, x_n)\,dx_1\,dx_2\cdots dx_n \tag{4.5}$$

for $i, k = 1, 2, \ldots, n$.

For one-dimensional random variable x there exists a unique central moment of second order, defined by formula

$$d = \int_{-\infty}^{\infty} (x - m)^2 \varphi(x)\,dx. \tag{4.6}$$

This moment is usually called *dispersion* of corresponding distribution.

For discrete random variables, formula (4.4) becomes

$$\vec{m} = \sum_{\vec{x}\in M} \vec{x} f(\vec{x}). \tag{4.7}$$

For multidimensional random variables central moments of second order λ_{ik} are convenient to combine into matrix $\|\lambda_{ik}\|$ and construct from them (in case of their finiteness) quadratic form $Q(t_1, t_2, \ldots, t_n) = \sum_{i,k} \lambda_{ik} t_i t_k$. This form with help of orthogonal transformation (rotation) of coordinate system can always be reduced to the form $\sum a_i (t_i)^2$, where t_i—new coordinates, and a_i—positive coefficients. Forms of such kind are called *positive semi-definite*. If $m = n$, the form Q is called *positive definite*.

In probability theory the following fundamental result has great significance.

Theorem 4.2.1 (Central Limit Theorem)**.** *If n-dimensional random (continuous or discrete) variables $x_1, x_2, \ldots, x_k$ are independent and have one and the same distribution with finite central moments of second order λ_{ik}, for which form $Q(t_1, t_2, \ldots, t_n) = \sum \lambda_{ik} t_i t_k$ is positive definite, and with mean value equal to zero, then as $k \to \infty$ the variable*

$$x = \frac{1}{\sqrt{k}}(x_1 + x_2 + \cdots + x_k)$$

has limit continuous distribution also with zero mean value and with (multidimensional) probability density function

$$\varphi(t_1, t_2, \ldots, t_n) = \frac{1}{(2\pi)^{n/2}\sqrt{|Q|}} e^{-\frac{1}{2}Q^{-1}(t_1, t_2, \ldots, t_n)}. \tag{4.8}$$

If mean value of variables is not zero, denoting this mean value through $\vec{m} = (m_1, m_2, \ldots, m_k)$, we find that the probability density function takes the form

$$\varphi(t_1, \ldots, t_n) = \frac{1}{(2\pi)^{n/2}\sqrt{|Q|}} e^{-\frac{1}{2}Q^{-1}(t_1 - m_1\sqrt{k}, t_2 - m_2\sqrt{k}, \ldots, t_n - m_n\sqrt{k})}. \tag{4.9}$$

4.2.1 Binomial distribution

Binomial distribution arises as result of conducting independent trials according to so-called *Bernoulli scheme*. This scheme, besides the property of independence of trials, is characterized also by the fact, that at each trial only two outcomes are possible, arising with probabilities p and $q = 1 - p$ respectively.

Random variable $k = x_1 + x_2 + \cdots + x_n$ equals, obviously, the total number of successes among n independent trials. The distribution law of discrete random variable k is given by function

$$f_n(k) = C_n^k p^k q^{n-k} \qquad (k = 0, 1, \ldots, n). \tag{4.10}$$

This law is called *binomial distribution law*, since quantity $C_n^k p^k q^{n-k}$ represents itself the $(n - k + 1)$-st term of expansion of expression $(p + q)^n$ by Newton's binomial formula.

For sufficiently large values of n good approximation for distribution law of variable $x = \frac{k}{\sqrt{n}}$ will be continuous law with probability density function of form

$$\varphi(x) = \frac{1}{\sqrt{2\pi p(1-p)}} e^{-\frac{(x - p\sqrt{n})^2}{2p(1-p)}}. \tag{4.11}$$

Definition 4.2.4. *Distribution with probability density function of form* $\frac{1}{\sqrt{2\pi a}} e^{-\frac{(x-m)^2}{2a}}$ *(at* $a > 0$*) we will call (generalized)* one-dimensional normal distribution law.

4.2.2 Polynomial distribution

For a series of independent trials with m different outcomes, let p_i $(p_i > 0)$ denote probability of i-th outcome of trial $(i = 1, 2, \ldots, m)$. The joint distribution law of variables $k_1, k_2, \ldots, k_r$ $(1 < r \leq m)$ is given by formula

$$f(k_1, k_2, \ldots, k_r) = \frac{n!}{k_1! k_2! \cdots k_r! (n - k_1 - k_2 - \cdots - k_r)!} \times p_1^{k_1} p_2^{k_2} \cdots p_r^{k_r} (1 - p_1 - p_2 - \cdots - p_r)^{n - k_1 - k_2 - \cdots - k_r}. \tag{4.12}$$

This is called the *polynomial distribution law.*

Theorem 4.2.2. *Let a series of independent trials with m different outcomes be given, having corresponding probabilities $p_1, p_2, \ldots, p_m$ (identical for all trials). If in a series of n trials through $k_1, k_2, \ldots, k_m$ we denote quantities of trials, ending with 1st, 2nd, ..., m-th outcome respectively, then for any given in advance positive number ε for the probability q of simultaneous fulfillment of all inequalities $|k_i/n - p_i| < \varepsilon$ $(i = 1, 2, \ldots, m)$ there exists estimate*

$$q > 1 - \frac{a}{(m-1)} \cdot e^{-bn}$$

where a and b are positive constants, not depending on n.

4.3 Quantitative measure of self-organization and self-modification in automata

In the previous section, when defining the concepts of self-modification and self-organization in automata (discrete and otherwise), as yet no method was indicated for their concrete quantity of self-organization of learning of automaton.

Definition 4.3.1. *Let x be a discrete random variable, with domain of definition R and with distribution law $f(x)$. The* entropy of this variable*, or, which is the same,* entropy of distribution *$f(x)$, is defined as the negative sum of products of probabilities $f(x)$ by their logarithms extended over domain of definition R:*

$$H = -\sum_R f(x)\log f(x). \tag{4.13}$$

When using this formula it is assumed, that for $f(x) = 0$ the product $f(x)\log f(x)$ equals zero.

As shown in information theory, entropy represents itself a natural measure of uncertainty of values of random variable: the greater this uncertainty of values, the greater the value of entropy. In particular, if random variable can assume only two values with probabilities p and $q = 1 - p$ respectively, then the largest value of entropy is achieved at equality of these probabilities: $p = q = 1/2$.

Definition 4.3.2. *The property of entropies of independent distributions to add up when combining these distributions into one is called* additivity property *of entropy.*

Let $(p_1, p_2, \ldots, p_n) = P$—sequence of questions (input words), submitted to automaton during period of its learning. This sequence we shall call *training sequence.*

Definition 4.3.3. Entropy of learning with given distribution law for learning *is calculated by formula*

$$H^R(learn) = -\sum_P \rho(P)\log\rho(P). \tag{4.14}$$

The distribution $\alpha(a)$ on set of all states of the automaton is given by

$$\alpha(a) = \sum_{P\in S_a} \rho(P), \tag{4.15}$$

where summation is extended over all words of form $P = p_1p_2\cdots p_n$, contained in S_a.

Value $H^Q(\text{ex})$ is determined by formula

$$H^Q(\text{ex}) = -\sum_{q,p} \beta(q,p)\log\beta(q). \tag{4.16}$$

Introducing increments of entropy of experiment and examination by formulas

$$\Delta H^Q = H^Q - H^{Q_0}; \qquad \Delta H^Q(\text{ex}) = H^Q(\text{ex}) - H^{Q_0}(\text{ex}), \tag{4.17}$$

we obtain possibility for any automaton A and class K of laws of experimentation with automaton (with probability density $\varphi(Q)$) to introduce two averaged characteristics

$$s(A,K) = -\int_K \Delta H^Q(\text{ex})\,\varphi(Q)\,dQ; \tag{4.18}$$

$$z(A,K) = \int_K \frac{\Delta H^Q(\text{ex})}{\Delta H^Q}\,\varphi(Q)\,dQ. \tag{4.19}$$

The larger the value of these integrals, the greater the average ability to self-organization of considered automaton A. Zero value corresponds to absence of abilities to self-organization, and negative values mean, that upon improvement of organization of learning organization of answers of automaton on average worsens.

4.3.1 Example: Automata A and B

Let us consider two automata A and B, functions of transitions and outputs of which are given by tables:

For automaton A:

	1	2
x	1	1
y	2	2

	1	2
x	u	v
y	u	v

For automaton B:

	1	2
x	1	2
y	2	2

	1	2
x	u	v
y	u	v

Application of formula (4.18) gives

$$s_n(A,K)=\int_0^1\left(p\ln p+(1-p)\ln(1-p)-\ln\frac{1}{2}\right)dp=\ln 2-\frac{1}{2}\approx 0.19. \tag{4.20}$$

For automaton B we obtain

$$s_n(B,K)<\frac{n\ln 2+1}{2^n}-\frac{n}{(n+1)^2}-\frac{1}{4n}. \tag{4.21}$$

From this estimate we easily learn, that at $n\geq 5$ quantity $s_n(B,K)$ is negative. In other words, when trained by sequences of length, greater than 4, in selected class of experimentation laws automaton B is on average "self-disorganizing", while automaton A under same conditions shows ability to self-organization.

4.4 Automata with random transitions

Besides deterministic automata in theory of self-organizing systems essential role play automata with random transitions. In a deterministic automaton giving of input signal $a[i]$ unambiguously determines next internal state of automaton $a[i+1]$. In an automaton with random transitions $p_i(x)$, transition of automaton from state $a[i]$ describes probability $p_i(x)$, under action of input signal x.

Definition 4.4.1. *Matrices, with all components non-negative, possessing the property that in each column the sum equals unity, are called* stochastic matrices *or* Markov matrices.

Special interest present automata with random transitions without inputs, i.e. containing only one column. Such automata are studied in classical theory of random processes under designation *Markov chains*. Basic concept of this theory was introduced by prominent Soviet mathematician A. A. Markov.

Theorem 4.4.1. *For random automaton A with single input signal (homogeneous Markov chain), matrix of transition probabilities of which is P, probability of transition from i-th state to j-th in exactly n steps equals element P^n, standing at intersection of i-th row and j-th column ($n=1,2,3,\ldots$).*

Elements of matrix P^n it is natural to call *transition probabilities for n steps*. For determination of these probabilities in case of finite Markov chains usually the so-called *Perron formula* is used.

Let matrix $P = \|p_{ij}\|$ of n-th order be given. The determinant

$$P(\lambda) = \begin{vmatrix} \lambda - p_{11} & -p_{12} & \cdots & -p_{1n} \\ -p_{21} & \lambda - p_{22} & \cdots & -p_{2n} \\ \vdots & \vdots & \ddots & \vdots \\ -p_{n1} & -p_{n2} & \cdots & \lambda - p_{nn} \end{vmatrix}$$

represents itself polynomial of n-th degree in λ, called *characteristic polynomial* of matrix P. Roots of this polynomial are called *characteristic numbers* of matrix P.

Let matrix $P = \|p_{ij}\|$ have characteristic numbers $\lambda_1, \lambda_2, \ldots, \lambda_r$. Denote through m_i multiplicity of i-th number λ_i, and determine polynomial $\psi_i(\lambda)$ by formula

$$\psi_i(\lambda) = \frac{P(\lambda)}{(\lambda - \lambda_i)^{m_i}}. \tag{4.22}$$

The element $p_{ij}^{(k)}$ of matrix $P^{(k)}$, standing at intersection of i-th row and j-th column, can be determined by *Perron formula*:

$$p_{ij}^{(k)} = \sum_{\nu=1}^{r} \frac{1}{(m_\nu - 1)!} D_\lambda^{m_\nu - 1} \left[\frac{\lambda^k P_{ij}(\lambda)}{\psi_\nu(\lambda)} \right]_{\lambda = \lambda_\nu}. \tag{4.23}$$

In the simplest case when all characteristic numbers are simple ($m_i = 1$ for all i), formula (4.23) reduces to

$$p_{ij}^{(k)} = \sum_{\nu=1}^{r} \frac{\lambda_\nu^k P_{ij}(\lambda_\nu)}{\psi_\nu(\lambda_\nu)}. \tag{4.24}$$

Theorem 4.4.2. *Markov chain with corresponding states, chain with single absorbing state (at which from start to transition of complete absorption of states, from which there is no escape), or with multiple absorption states, complete transition is possible.*

4.4.1 Stationary random medium

Definition 4.4.2. *A random medium C is given as matrix R of transition probabilities. The automaton A is called* asymptotically optimal *for given type of input signal.*

For automaton with two internal states $a_1 = 1$, $a_2 = 2$, and matrices of transition probabilities:

$$P_{a_0} = \begin{pmatrix} 1 - p_0 \\ p_0 \end{pmatrix}; \quad P_{a_1} = \begin{pmatrix} 1 - p_1 \\ p_1 \end{pmatrix}. \tag{4.25}$$

The input signal a_0 is called *penalty*, and input signal a_1—*reward*.

The matrix P of transition probabilities of the chain is:

$$P = \begin{vmatrix} 1 - p_0 & -p_0 \\ -p_1 & 1 - p_1 \end{vmatrix}.$$

Characteristic polynomial $P(\lambda) = \lambda^2 - \lambda(2 - p_0 - p_1) + 1 - p_0 - p_1$, and its characteristic numbers are $\lambda_1 = 1$ and $\lambda_2 = 1 - p_0 - p_1$.

At sufficiently long functioning in medium C automaton A, independently from choice of initial state, will be in first state with probability $\frac{p_1}{p_0 + p_1}$, and with probability $\frac{p_0}{p_0 + p_1}$ in second state.

Mathematical expectation S of penalty of automaton A at each step is expressed by formula

$$S = p_0 \frac{p_1}{p_0 + p_1} + p_1 \frac{p_0}{p_0 + p_1} = \frac{2 p_0 p_1}{p_0 + p_1}. \tag{4.26}$$

At $p_0 \neq p_1$ quantity S is strictly less than average probability of penalty $S_0 = \frac{1}{2}(p_0 + p_1)$.

Definition 4.4.3. *The automaton A possesses* purposeful behavior *in that sense, that upon placing in any stationary random medium, distinguishing its two possible reactions, it strives towards such behavior, at which penalty quantity turns out to be on average less, than for automaton, producing both possible output signals with equal probabilities.*

4.4.2 Automaton with linear tactics

Consider automaton A_n with $2n$ states $1, 2, \ldots, n, n+1, \ldots, 2n-1, 2n$. In states $1, 2, \ldots, n$ it produces output signal $v_0 = 0$, and in remaining states—output signal $v_1 = 1$. The table of transitions corresponds to graph depicted in Figure 4.1.



Figure 4.1: Graph of transitions for automaton A_n with linear tactics. States 1 to n (shaded) produce output $v_0 = 0$; states n+1 to $2n$ produce output $v_1 = 1$. Input 0 moves left, input 1 moves right.

Such automaton by type of its graph is natural to call *automaton with linear tactics*. The calculated value of mathematical expectation S_n of penalty of automaton A_n for one step of its work at unbounded increase of number n tends to natural minimum value $S_{\min}$, equal to smallest of two numbers p_0, p_1.

4.5 Problem of learning pattern recognition

One of most important practical areas of application of theory of self-organizing systems is *pattern recognition*. Recognition—is teaching of machine to perceive certain objects in much the same way humans perceive them.

Definition 4.5.1. *Object, which is perceived by machine, and to which machine assigns name is called* pattern. *Pattern recognition is understanding of pattern character by machine at given signal in form, according to which pattern is identified by its belonging to some class.*

Definition 4.5.2. R-characterization *of some class of pattern M projection onto perceptron is called set of all possible configurations of all points of projection of class onto retina M within R projection.*

Definition 4.5.3. k-characterization *of patterns will be the k-characterizing approach element, set of one k-characteristics R in produced projections information.*

4.5.1 Perceptron structure

The perceptron consists of:

1. *Receptors*—sensitivity elements that respond to patterns
2. *A-elements*—associative elements with random connections
3. *Neurons*—processing units with threshold functions
4. *Summators*—output units for each pattern class

Definition 4.5.4. *Threshold neurons have coefficients from one to not one to the same, and for representing discrete classes, threshold represents part (l, l_1), each at receptor at each belonging to coefficient to same.*

The effectiveness of learning in perceptrons depends fundamentally on characteristic matrix structure and training sequence organization, not random connections.

4.6 Theory of learning of discrete α-perceptrons

In present section we consider some concrete type of theory of learning perceptron with α-alphabet encoding, operating in regime of self-organization.

Definition 4.6.1. *The* characteristic tensor T_{ij}^k *of a perceptron, from at with i at in equation—at coefficient T_i^k at on class k.*

From given definitions directly follows validity of relation

$$T_{ij}^k = T_{ji}^k \qquad (i, j = 1, 2, \ldots, m; \quad k = 1, 2, \ldots, q). \tag{4.27}$$

Any "diagonal" element of tensor, for example T_{ii}^k, represents itself number of neurons of that or another (in given case k-th) pattern, excited under effect of i-th representation. From here directly follows validity of inequalities

$$T_{ij}^k > T_{ii}^k \qquad (i, j = 1, 2, \ldots, m; \quad k = 1, 2, \ldots, q). \tag{4.28}$$

Definition 4.6.2. *Perceptron or class of perceptrons we shall call* symmetric*, if components of characteristic tensor do not depend from upper index, i.e. if valid the relation*

$$T_{ij}^1 = T_{ij}^2 = \cdots = T_{ij}^q \qquad (k_1, k_2 = 1, 2, \ldots, q; \quad i, j = 1, 2, \ldots, m). \tag{4.29}$$

For symmetric perceptrons, the two-dimensional table (T_{ij}) is called the *characteristic matrix.*

Let $U_k^s(l)$ denote output signal of summator of k-th pattern, induced in considered perceptron by i-th representation, shown after learning of perceptron by training sequence l.

Theorem 4.6.1 (Commutativity Property)**.** *In perceptron (or in class of perceptrons) with (generalized) α-law of reinforcement output signal $U_k^s(l)$ of summator of k-th pattern under effect of i-th representation after learning by any sequence l will not change, if in sequence l arbitrary permutation of its representations is performed. This is valid for any representation i and any pattern k.*

Theorem 4.6.2. *Let in considered perceptron (class of perceptrons) act (generalized) α-law of reinforcement with constants a, b, then after learning by sequence (or class of sequences) l with characterization vector $(v_1, v_2, \ldots, v_m)$ for any pattern P and any representation i output signal $U_i^P(l)$ of summator of P-th pattern under effect of i-th representation is expressed by formula*

$$U_i^P(l) = U_i^P + a \sum_{j \in P} T_{ij}^P v_j - b \sum_{j \notin P} T_{ij}^P v_j. \tag{4.30}$$

For any representation i through P_i let us conditionally designate that pattern, to which representation i belongs in initial classification. The necessary and sufficient condition for correct classification of i-th representation is:

$$U_i^{P_i}(l) > U_i^P(l) \qquad \text{for all } P \neq P_i. \tag{4.31}$$

Theorem 4.6.3. *Let arbitrary discrete symmetric perceptron (or class of discrete symmetric perceptrons) with characteristic matrix $\|T_{ij}\|$ and with symmetric initial conditions be given, in which acts (generalized) α-law of reinforcement. Then necessary and sufficient conditions for correct recognition by perceptron of any i-th representation after learning by sequence with characteristic vector $(v_1, v_2, \ldots, v_m)$ are expressed by relations*

$$\sum_{j \in P_i} T_{ij} v_j > \sum_{j \in P} T_{ij} v_j \qquad \text{for all } P \neq P_i. \tag{4.32}$$

Corollary 4.6.1. *Effectiveness of learning in symmetric discrete perceptrons with symmetric initial conditions at execution in them of (generalized) α-law of reinforcement does not depend on choice of (non-negative) constants a and b, characterizing this law.*

If we denote through T total number of neurons of P-th pattern, then component T_{ij}^P should be considered as random variable, having binomial distribution with parameters T and α_{ij}:

$$E(T_{ij}^P) = T\alpha_{ij}; \qquad D(T_{ij}^P) = T\alpha_{ij}(1 - \alpha_{ij}). \tag{4.33}$$

For variables v_i characterizing training sequence:

$$E(v_i) = Np_i; \qquad D(v_i) = Np_i(1 - p_i) \qquad (i = 1, 2, \ldots, m). \tag{4.34}$$

4.6.1 Example 1: Complete symmetric perceptron

Let us examine discrete perceptron A with neurons determined by n-horizontal and n-vertical lines. Perceptron A is symmetric with characteristic matrix $\|T_{ij}\|$:

$$T_{ii} = n^2(n-1) \qquad (i = 1, 2, \ldots, 2n) \tag{4.35}$$

$$T_{ij} = 0 \quad \text{if } i, j \text{ same pattern} \tag{4.36}$$

$$T_{ij} = (n-1)^2 \quad \text{if } i, j \text{ different patterns} \tag{4.37}$$

Characteristic matrix:

$$M = \begin{vmatrix} n^2(n-1)E & (n-1)^2 D \\ (n-1)^2 D & n^2(n-1)E \end{vmatrix} \tag{4.38}$$

with constraint: $v_1 + \cdots + v_n = v_{n+1} + \cdots + v_{2n} = N$.

Condition for correct recognition becomes:

$$v_i > \left(\frac{1}{n} - \frac{1}{n^2}\right) N. \tag{4.39}$$

Mathematical expectation and dispersion:

$$E(v_i) = \frac{1}{n} N; \quad D(v_i) = N \frac{1}{n} \left(1 - \frac{1}{n}\right). \tag{4.40}$$

Probability of correct classification:

$$q_i \approx 0.5 + \frac{1}{\sqrt{2\pi}} \int_0^k e^{-\frac{z^2}{2}} dz \tag{4.41}$$

where $k \approx \sqrt{\frac{N}{n^3}}$.

N	n^3	$4n^3$	$9n^3$
k	1	2	3
q	0.841	0.977	0.999

Theorem 4.6.4. *For complete discrete symmetric perceptron with symmetric initial conditions capable of absolute self-organization: given n patterns with fully characterized representations, minimum n training presentations suffice.*

4.6.2 Example 3: Random connections

Consider class C of discrete symmetric perceptrons when all neurons connect independently with equal probability to any receptor, excluding simultaneous connection of both inputs of neuron to one receptor.

The condition of correct recognition is:

$$T_{ii} > \sum_{j \notin P_i} T_{ij}. \tag{4.42}$$

Probability of desired connection equals $\frac{1}{n(n+1)}$, and probability that such connection will not take place for any one of N neurons equals $\left(1 - \frac{1}{n(n+1)}\right)^N \approx e^{-\frac{N}{n(n+1)}}$.

Complete effectiveness of learning is expressed by formula

$$r \approx 1 - e^{-\frac{N}{n(n+1)}}. \tag{4.43}$$

If number of neurons of each pattern equals $7n(n+1)$, i.e. approximately 7 times exceeds total number of receptors, then probability of incorrect operation of randomly selected perceptron after learning with presentation of all representations once will be approximately 0.001.

4.7 Regime of discrete α-perceptrons in regime of self-organization

In this section we discuss theory of learning α-perceptrons in regime of self-organization.

Consider discrete symmetric α-perceptron for purpose of distinguishing pattern P from Q. Conditions of two output types summators of perceptron, V_P and V_Q:

$$V_i = V_i^P + V_i^Q, \tag{4.44}$$

The formula for signal propagation:

$$V_i(l) = V_i(l) + T_{ij} \operatorname{sign} V_i(l). \tag{4.45}$$

For the Markov chain with $2t+1$ states $k = -t, -t+1, \ldots, -1, 0, 1, \ldots, t-1, t$, introducing designations $p = \frac{m}{n}$ and $q = \frac{n-m}{n}$, we obtain matrix of transition probabilities

$$M = \begin{pmatrix} 1 & 0 & 0 & 0 & \cdots & 0 & 0 & 0 \\ p & 0 & q & 0 & \cdots & 0 & 0 & 0 \\ 0 & p & 0 & q & \cdots & 0 & 0 & 0 \\ \vdots & \vdots & \vdots & \vdots & \ddots & \vdots & \vdots & \vdots \\ 0 & 0 & 0 & 0 & \cdots & 0 & q & 0 \\ 0 & 0 & 0 & 0 & \cdots & p & 0 & q \\ 0 & 0 & 0 & 0 & \cdots & 0 & 0 & 1 \end{pmatrix}$$

By Perron formula we obtain:

$$p_{t+1,i}^{\infty} = \lim_{\lambda \to 1} \frac{d}{d\lambda} \frac{\lambda^s M_{i,t+1}(\lambda)}{\psi_1(\lambda)} \bigg|_{\lambda=1}. \tag{4.46}$$

Proposition 4.7.1. *At unlimited continuation of process of self-organization the perceptron A with probability $\frac{p^t}{p^t+q^t}$ establishes correct classification of representations and with probability $\frac{q^t}{p^t+q^t}$ assigns all representations to one and the same pattern.*

Theorem 4.7.1. *For any arbitrarily small positive number ε there exists such number S, that in case, when lower bound of moduli of initial conditions exceeds S, perceptron B in regime of self-organization (with equiprobable appearance of all representations) with probability $p > 1 - \varepsilon$ preserves initial classification of representations.*

Proof. Let $V_i(0) = x_i$ $(i = 1, 2, \ldots, 2n)$. Using characteristic matrix properties, initial classification is preserved if for all $N = 1, 2, \ldots$ inequalities are satisfied

$$n^2(n-1)v_i + (n-1)^2 \left(\sum_{j \in k_i} v_j - \sum_{j \in z_i} v_j \right) + |x_i| > 0 \quad (i = 1, 2, \ldots, 2n),$$

and all the more, if inequalities are satisfied

$$n^2(n-1)v_i - (n-1)^2 \sum_{j \in k_i \cup z_i} v_j + x > 0 \quad (i = 1, 2, \ldots, 2n), \tag{4.47}$$

where x is minimal of numbers $|x_j|$.

At designation of quantity $\frac{1}{4n^2}$ by letter δ, inequalities will certainly be satisfied if:

$$\left| \frac{v_i}{N} - \frac{1}{2n} \right| < \delta \quad (i = 1, 2, \ldots, 2n). \tag{4.48}$$

By Theorem 4.2.2, there exist positive constants a and b such that probability P_N of non-fulfillment has estimate $P_N < \frac{a}{N^{\frac{n-1}{2}}} e^{-bN}$.

Selecting $S = 2(M-1)n^2(n-1)$, we obtain that for all values N inequalities are satisfied with probability greater than $1 - \varepsilon$. □

For the β-law of reinforcement, transition of output signal is:

$$V_i(l) = (1 - \beta)V_i(l) + T_{ii} \operatorname{sign} V_i(l). \tag{4.49}$$

Theorem 4.7.2. *Discrete symmetric perceptron C with only diagonal characteristic matrix (not zero on diagonal) with α-law of reinforcement ($\alpha = 1 - \beta$) at same conditions of self-organization with equal probability establishes correct or incorrect classification.*

Consider the case of two patterns with one representation each. The relation:

$$V_i(l) = V_i(l) + T_{ii} \tag{4.50}$$

For discrete symmetric perceptron with α-law of reinforcement and characteristic matrix $T = \begin{vmatrix} a & b \\ b & a \end{vmatrix}$, where $a > b > 0$, the behavior is illustrated in Figures 4.2 and 4.3.

4.8 Logical classification systems and measure of conditional probability

System for pattern recognition represents device for classification of entropy at source and classification of representing at condition.

Definition 4.8.1. *Machine, classifying representations at A-approaches at representing at pattern, consists in same classified coinciding. Each glance of galvanometer is fixed and determines main position (state) characterized by state of galvanometer, representing output of recognizing system corresponding to class of s states.*



Figure 4.2: Learning regime (Figure 13): Vectors $T_1 = (a, b)$ and $T_2 = (b, a)$ have same directions regardless of location in plane. Resultant always points toward fourth quadrant (hatched), corresponding to correct classification.



Figure 4.3: Self-organization regime (Figure 14): Vector directions depend on quadrant. Quadrants I and III (hatched) are "trapping" regions—once entered, points cannot escape. Quadrant III represents correct classification fixation.

Definition 4.8.2. Unconditional frequency $p(I)$ *of property* I *in relation to reference* J *represents itself (approximately) mean number of cases appearance of property* I *divided by mean number of cases appearance of property* P*:*

$$p(I) = \frac{I_J}{p(J)}. \tag{4.51}$$

Therefore, from conditions formula (4.51):

$$p(I_1|I_2) = \frac{I_{J_1}}{p(I_1)}. \tag{4.52}$$

4.8.1 Universal classification machine

Universal machine for all its essential conclusions about differences of trained operates at different approaches, determining different conditions at one to another. For machine of conditional probability:

Law of change of weight of connection is given by following relations, determined for all values $n = 0, 1, 2, \ldots$:

$$\lambda_{n+1}(P, Q) = \lambda_n(P, Q), \tag{4.53}$$

if at $(n + 1)$-st step of learning neuron P is not excited;

$$\lambda_{n+1}(P, Q) = \lambda_n(P, Q) + \alpha(1 - \lambda_n(P, Q)), \tag{4.54}$$

if at $(n + 1)$-st step of learning both neurons P and Q are excited;

$$\lambda_{n+1}(P, Q) = \lambda_n(P, Q) - \beta\lambda_n(P, Q), \tag{4.55}$$

if at $(n + 1)$-st step of learning neuron P is excited, and neuron Q is not excited.

Here α and β represent positive constants strictly smaller than unity.

Definition 4.8.3. *It is natural to call quantity* $\tau_n(J/I) = \lambda_n(P, Q)$ conditional pseudo-frequency *of property* J *in relation to property* I*.*

4.9 Self-organization and self-modification: Methods of solution of complex variant tasks

In §1 of present chapter it was noted that under term of self-organizing system is usually understood system containing self-modification.

Since determining of conditions consists in each regulating varying various parameters in function $F(a_1, a_2, \ldots, a_n)$, this extremum at parameters is some minimum character, $F(\lambda_1, \ldots, \lambda_n)$.

4.9.1 Gradient methods

If one agrees to make step towards point of extremum in space of variables $(x_1, x_2, \ldots, x_n)$ only of some fixed constant length r, then to equation of increment of function f is added equation

$$\Delta_1^2 + \Delta_2^2 + \cdots + \Delta_n^2 = r^2. \tag{4.56}$$

By method of undetermined multipliers of Lagrange the question is reduced to finding extremum of function

$$F = \sum_{i=1}^{n}(f_i\Delta_i - \lambda\Delta_i^2) + \lambda r^2$$

from variables $\Delta_1, \Delta_2, \ldots, \Delta_n$. Differentiating by Δ_i and equating obtained partial derivatives to zero, we obtain system of equations

$$f_i - 2\lambda\Delta_i = 0 \qquad (i = 1, 2, \ldots, n), \tag{4.57}$$

which must be supplemented by equation (4.56). From equations (4.57):

$$\Delta_i = kf_i, \tag{4.58}$$

where k is coefficient of proportionality, common for all $i = 1, 2, \ldots, n$.

Definition 4.9.1. *Equations (4.58) depending from choice of sign of coefficient k determine two opposite directions, at motion along which from point M is realized most rapid increase (at $k > 0$) or most rapid decrease (at $k < 0$) of function f. These directions are called correspondingly directions of* steepest ascent *and* steepest descent *in considered point M. Quantity of advance r in any of indicated directions is called* step of gradient ascent or descent.



Figure 4.4: Simplest variant of structure of working algorithm (Figure 15). Algorithm A operates on input with parameter μ. Algorithm B adjusts μ to optimize evaluation function f.

4.9.2 Ravine method

Definition of this more essential is presented at method of I. M. Gelfand and M. L. Tsetlin introducing special method, called method of *ravine*. Essence of method ravine consists in that, at exclusion of along X_1 in X, in directions (X_1 in X). At connecting points A_1 and A, arriving at representing at along at receiving at along.

4.9.3 Linear programming

The task consists in maximizing linear function

$$f = \sum_{k=1}^{r} c_k x_k$$

subject to constraints $\sum b_{ij}x_j + b_i \geq 0$ or equivalently system of linear equations

$$\sum \Delta x_j = b_i \quad (i = 1, 2, \ldots, m). \tag{4.59}$$

Simplex method

At application of simplex-method there are produced sequential transformations of given system of equations $\sum_{j=1}^{n} a_{ij}x_j = b_i$ $(i = 1, 2, \ldots, m)$ until then, when it will be brought to some special form.

Separating all basic variables, denoted by letters $x_1, x_2, \ldots, x_{k_0}$, we bring our system to form

$$x_k = b_k - \sum_{j=k_0+1}^{n} a_{kj}x_j \qquad (k = 1, 2, \ldots, k_0); \tag{4.60}$$

$$0 = b_i - \sum_{j=k_0+1}^{n} a_{ij}x_j \qquad (i = k_0 + 1, k_0 + 2, \ldots, m). \tag{4.61}$$

The cycle consists of following steps:

1. Sought is 0-equation, in which free member is strictly greater than zero. If such 0-equation is absent, then task is solved.
2. In found (i-th) equation is marked some positive coefficient a_{ij}. If all coefficients are non-positive, then system cannot have positive solutions, and posed task is unsolvable.
3. In that same column is found so-called *resolving coefficient* $a_{i_1 j_1}$, characterized by that from all ratios $\frac{b_i}{a_{ij_1}}$ with positive a_{ij_1} $(i = 1, 2, \ldots, n)$ ratio $\frac{b_{i_1}}{a_{i_1 j_1}}$ has minimally possible value.
4. Equation, into which enters resolving coefficient (i_1-st equation), is resolved relatively to variable x_{j_1}, which after this is added to number of basic variables.
5. After resolution again is sought 0-equation with positive free member, and with it are produced all described above actions.

Linear programming finds wide application in tasks of optimal planning. Similar problems were first formulated by academician L. V. Kantorovich.

4.9.4 Dynamic programming

Let us consider above one more example of variant task, in which searching for the best variant is produced with help of representation procedure (for dynamic programming).



Figure 4.5: Region Q with cross-sections designated by Roman numerals (Figure 16). Points on each cross-section are numbered. Total paths $N = n_1 \cdot n_2 \cdot n_3 \cdot n_4$.

If quantity of points in i-th cross-section is designated n_i, and total number of cross-sections—m, then total quantity (N) of polygonal paths will be determined by product: $N = n_1 n_2 \cdots n_m$. This quantity grows very quickly with growth of number of points and cross-sections.

One can shorten enumeration using following method. For each point j of first cross-section, set down value F_j^I of functional F on segment connecting this point with point A. For each point k of second cross-section find point j_k of first cross-section such that value of evaluation functional F on polygonal line Aj_kk was smallest. The minimal value is designated F_k^{II}.



Figure 4.6: Portion between i-th and $(i+1)$-st cross-sections (Figure 17). For each point q in $(i+1)$-st cross-section, find p_q in i-th that minimizes $F_p^i + F(p, q)$.

For each point q of $(i+1)$-st cross-section we find point p_q of i-th cross-section such that sum $F_{p_q}^i + F(p_q, q)$ was minimal. Writing this equation F_q^{i+1} and acting in such way for each point q, we obtain possibility to go to reconstruction of portion $(i+1)$—$(i+2)$-nd cross-section.

In result of sequential conducting of described process to consideration of variants of paths passing from (pre-last) cross-section, m, to end point B. Selected method permits considerably to diminish set of searched variants.

Requirements of additivity of evaluation functional do not narrow essentially class of objects. For any initial value of algorithm ATG the value of functional $F(ATG)$ of admissible $F(TG)$, $F(AT)$, or else $F(ATG) = \|A, T\| + F(T) \dots Q_n\|$.

Chapter 5

Electronic Digital Machines and Programming

5.1 Universal program automaton

One of most significant technical achievements of our time was creation of *universal program automata*, i.e. automatic processors of information, enabling realization of any algorithms. Such automata are contemporary universal electronic computational (digital) machines. It is interesting to note, that, as is evident from the very name, these machines were created for purposes of automation of calculations, more precisely, — for automation of execution of arbitrary *computational algorithms*. Term "universal" as applied to these machines was understood by creators of first universal computational machines (and now is still understood by many) in sense of universality in relation namely to computational algorithms.

However, since every algorithm can be reduced, as was noted in ch. I, to calculation of some partially recursive (arithmetic) function, then universality in relation to computational algorithms turns out to be universality in general. This circumstance has enormous practical and principial significance, since factually the basis of any sphere of human activity is processing of information in correspondence with these or those, often very complex sets of algorithms.

Availability in our disposal of universal automatic processors of information, as are contemporary universal electronic computational machines, allows, at least in principle, to automatize any sphere of human activity, based on processing of information. This may be solution of complex tasks of computational character, and in planning, and in control of production, and in translation from one language to another, and in composing music, and in games in chess, and in many other things.

The approach of selecting from two approaches to condition is named *conditional transfer*. First address contains the number being checked, second — address to which transfer is produced if condition is satisfied.

Number of record cell in memory of universal digital machine receives the name of address. Each address is represented ordinarily with help of one word of universal digital machine (more precisely, with help of these same numbers, which in different machines vary in limits from 1 to 4). In correspondence with this same size of words of other designations also is limited.

Simultaneously with memory of machine there exist so-called *registers*, i.e. also some machines, in which addresses are stored temporarily. Storage of all information ordinarily is arranged in form of double coding of numbers. Normally memory is placed in specific regions of separate cells of machine (as in separate cells of tape of Post machine).

All these implementations, differing at realization yet another of selected procedure of composition procedure commands of given one or another languages are called *command language*, which corresponds to this programming language — *programming*.

5.2 Structure of contemporary universal program automata

Program automaton consists of three relatively independent devices — *memory device* (MD), *arithmetic device* (AD), operating device (OD) and *input-output devices* (IOD). At this, sometimes input devices (ID) and output devices (OuD) are considered separately. As was mentioned in preceding paragraph, memory device (storage) serves for storing addresses, and also data involving initial, intermediate and final information. Storing of approaches serves for in logical information (conditions of task), and as well device receives itself to result of completing calculations (resolving information), obtained in result of task, set by program automata.

Arithmetic device is used, as was marked by this same, for executing of arithmetical and logical operations. Also with help of arithmetic device operations are executed in other programming operations. An operation should be distinguished from program of operations.

Arithmetic device of contemporary electronic computers consists of three registers, one of which is called *summator*. Character code, arriving into summator, is added up to summator to the content, which was in it before operation.

As concerns properly device of microprogram control, then in scheme of Wilkes and Stringer it includes, besides above-mentioned register of microoperations, also so-called *decoder of microoperations* and two *diode matrices*, named A-matrix and B-matrix. Simplified conditional scheme of device of microprogram control is depicted in fig. 5.1.



Figure 5.1: Simplified scheme of microprogram control device (Figure 19). ROp: register of operations; RMO: register of microoperations; SI: synchronizing generator. Black dots represent diodes connecting horizontal and vertical buses.

In this figure by letters *ROp* is designated register of operations (component part of register of command OD), and *RMO* — register of microoperations. By dots are designated places of inclusion of diodes, connecting horizontal buses of matrix with vertical buses. Purpose of diodes consists in that, to allow passage of impulses in direct direction (from horizontal buses to vertical) and to prevent their passage in reverse direction. At this condition impulse, given onto any horizontal bus D, will go onto those and only those vertical buses, with which given bus D is connected by diodes. If connection of buses is done directly, false paths of passage of impulses, not foreseen by constructor, are possible. For example, at giving of impulse onto second from top horizontal bus of A-matrix impulse would appear not only on first from left vertical bus, but also on third from left, going through it to second from bottom horizontal bus. Presence of diodes excludes possibility of formation of similar false paths, since reverse passage of impulses from vertical buses to horizontal is not possible.

Purpose of depicted in fig. 5.1 decoder consists in that, to transmit arriving at its input next impulse of synchronizing generator *SI* exactly onto one from horizontal buses of *A*-matrix, connected by diode with vertical bus going from register of operations, at which in considered moment of time is established unit, i.e., actually, to determine by operation code the character of first executed in its process microoperation. Therefore *A*-matrix is also called *initial entry matrix*.

Transfer onto vertical buses of *B*-matrix (subsequently called also *following matrix*) is operated only after completion of microoperation, which is done exactly like in *A*-matrix. Therefore *A*-matrix serves for establishing address of microoperation, and *B*-matrix for producing microoperations.

Microprogram of addition

1. Clearing of registers AU and MD.
2. Transfer of code from register of first address OD in register of address MD.
3. Read in MD.
4. Transfer of code from register of number MD to summator AU.
5. Clearing of registers MD.
6. Transfer of code from register of second address OD in register of address MD.
7. Read in MD.
8. Transfer of code from register of number MD to summator AU (most often through register AU P_2).
9. Clearing of registers MD.
10. Transfer of code from summator AU in register of number MD.
11. Transfer of code from register of third address OD in register of address MD.
12. Write in MD.
13. Clearing of registers MD.
14. Increase of content of counter of commands by unity.
15. Transfer of code from counter of commands in register of address MD.
16. Read in MD.
17. Clearing of register of commands.
18. Transfer of code from register of number MD in register of commands.

Some of microoperations, constituting described microprogram, can be combined in time, due to which can be shortened time of working cycle and increased speed of machine. Examples of such combined microoperations can serve microoperations 16 and 17 or microoperations 10 and 11.

Microprogram of multiplication by positive number

1. Clearing of registers AU and MD.
2. Transfer of code from register of first address OD in register of address MD.
3. Read in MD.
4. Transfer of code from register of number MD in register P_1 AU.
5. Clearing of registers MD.
6. Transfer of code from register of second address OD in register of address MD.
7. Read in MD.
8. Transfer of code from register of number MD in register P_2 AU.

(9.1) Transfer of code from register P_1 in summator, if $q = 1$, and transfer to following micro-operation without transfer of number, if $q = 0$.

(10.1) Shift right on summator.

(11.1) Shift right on register P_2.

(9.2) Same as 9(1).

(10.2) Same as 10(1).

(11.2) Same as 11(1).

. . . . . .

(9.n) Same as 9(1).

(10.n) Same as 10(1).

(11.n) Same as 11(1).

12. Clearing of registers MD.
13. Transfer of code from register of third address OD in register of address MD.
14. Transfer of code from summator in register of number MD.
15. Write in MD.
16. Clearing of registers MD.
17. Adding of unity to content of counter of commands.
18. Transfer of code from counter of commands in register of address MD.
19. Read in MD, clearing of register of commands.
20. Transfer of code from register of number MD in register of commands.

In microprogram of multiplication, in distinction from microprogram of addition, essentially is used possibility of branching in order of following of microoperations depending from signal of feedback q, arriving from AU. It is not difficult to understand, that sequential execution of microoperations 9, 10, 11 is equivalent to execution of ordinary, well-known algorithm of multiplication with rounding in application to binary system of numeration.

In essence, at described method summator AU serves for memorizing sums of partial products of multiplicand by separate digits of multiplier. Such memorizing is accomplished with accuracy up to younger digits, discarded at shift right of content of summator. Each time multiplicand is added or not added to partial sum, stored in summator, depending from that, whether unity or zero equals younger digit of multiplier shifted right. It is clear, that this procedure together with preliminary shifts on summator and in register P_2 means adding of product of multiplicand by next (from right) digit of multiplier in already existing sum of analogous (partial) products, as is required in ordinary algorithm of multiplication. Rounding to number of significant digits, contained in co-multipliers, is accomplished as result of shifts on summator, leading to destruction of younger digits of product. In case of multiplication not only by positive, but also by negative numbers in microprogram is added additional microoperation of forming of sign of product.

Microprogram of conditional transfer by inequality

1. Clearing of registers AU and MD.
2. Transfer of code from register of first address OD in register of address MD.
3. Read in MD.
4. Transfer of code from register of number MD in summator AU.
5. Clearing of registers MD.
6. Transfer of code from register of second address OD in register of address MD.
7. Read in MD.
8. Transfer of code from register of number MD in register AU.
9. Transfer of code with change of sign from register to summator.
10. If content of summator $s > 0$, then adding of unity to content of counter of commands, and if $s < 0$, then transfer of code from register of third address OD in counter of commands.
11. Clearing of registers in MD.
12. Transfer of code from counter of commands in register of address MD.
13. Read in MD.
14. Clearing of register of commands.
15. Transfer of code from register of number MD in register of commands.

Described microprogram accomplishes comparison of number A_1, recorded by first address of command, with number A_2, recorded by its second address. If it turns out, that $A_1 > A_2$, then control is transferred to following by order command. If however $A_1 < A_2$, then following command is extracted by third address of current command. It is not difficult to understand, that from two operations of conditional transfer by inequality, rearranging by places numbers A_1 and A_2, one can form operation of conditional transfer by exact coincidence of words, described in preceding paragraph.

Description of basic principles of organization of algorithmic process in universal electronic digital machines gives general understanding about so-called *block structure* of these machines. At real design of electronic program automata stage of block synthesis is only starting point for development of these or other circuit solutions. Selection of these solutions is accomplished on basis of theory of automata and theory of combinational schemes, presented in ch. I, III.

5.3 Concept of programming

Programming is called recording of this or another algorithm in form of finite sequence of commands (commands) of universal program automaton. Such sequence is called program of work of given automaton. Entered in automaton together with initial data (input word of algorithm), it causes automaton to execute work of considered algorithm, i.e. to transform given input word (input information) to corresponding to it output word (output information). Universality of set of operations of contemporary program automata causes possibility of programming of any algorithm under condition, that we ignore limitations, imposed by finiteness of volume of memory of automaton.

To understand essence of problems, encountered in programming, let us consider first some simple particular example. Let us suppose, that we need to calculate sum of form $\sum_{k=1}^{m} \frac{1}{k^2}$, where m is some fixed natural number. We will compose program of solution of this task in application to three-address universal digital machine with natural order of following of commands, in set of operations of which are included all four arithmetic operations (addition, subtraction, multiplication and division), operation of conditional transfer by exact coincidence of words and operation of stopping of machine.

Let us suppose for simplicity, that necessity of input and output of information in MD of machine is absent. In other words, speaking, initial information and program, which will be composed, are assumed entered in appropriate cells of memory, and solution of task is obtained in cells of MD designated for this purpose (in considered case — in one cell) after stopping of machine.

For solution of posed task let us introduce following designations:

$$x_k = k; \tag{5.1}$$

$$y_k = x_k^2 = k^2; \tag{5.2}$$

$$z_k = \frac{1}{y_k} = \frac{1}{k^2}; \tag{5.3}$$

$$s_k = z_1 + z_2 + \ldots + z_k = s_{k-1} + z_k. \tag{5.4}$$

Let us assume, that for storage of values x_k, y_k, z_k and s_k are allocated any four cells of memory, named *working cells*. Process of calculation of sought sum s_k naturally divides into m completely identical stages, in each of which is calculated corresponding value of partial sum s_k $(k = 1, 2, \ldots, m)$. Calculations begin with value $k = 1$ and $s_0 = 0$ and can be written in form of following scheme:

1. $y_k = x_k^2$;
2. $z_k = 1/y_k$;
3. $s_k = s_{k-1} + z_k$;
4. $x_{k+1} = x_k + 1$;
5. if $x_{k+1} \neq m+1$, then go to following command; if $x_{k+1} = m+1$, then return to command 1;

6. stop.

Written scheme represents itself factually already sought program, in commands of which true addresses of working cells are replaced by symbolic designations x_k, y_k, z_k, s_k, named *symbolic addresses*. Fixing true addresses of these cells, and also cells, containing appearing in cited program constants 1 and $m + 1$, it is not difficult to go from program with symbolic addresses to principal program in three-address commands.

Let us assume address of cells x_k, y_k, z_k, s_k respectively equal to 1, 2, 3, 4. In same corresponding cells address of constant 1 is equal 5, and address of constant $m + 1$ is equal 6 (having coded in advance by double alphabet of numbers). Let address of first command of program, as usually, be 7. Then address of following commands should be equal to corresponding number addresses.

With help of above addresses all commands become concretely presented in the following successively:

command	operation	a	b	c
1	multiplication	1,	1,	2;
2	division	5,	2,	3;
3	addition	4,	3,	4;
4	addition	1,	5,	1;
5	conditional transfer	1,	6,	7;
6	stop.			

For basis of second example let us consider programming of task of calculation of scalar product of two n-dimensional vectors $\mathbf{a} = (a_1, a_2, \ldots, a_n)$ and $\mathbf{b} = (b_1, b_2, \ldots, b_n)$, where sum $\mathbf{a} \cdot \mathbf{b} = a_1b_1 + a_2b_2 + \ldots$ represents itself sum of corresponding products.

For variety let us compose program of calculation of scalar product in application to single-address machine with natural order of following of commands. Commands, realizing arithmetic operations, at this are understood so, that corresponding operation is performed with pair of numbers, first of which is located in summator AU, and second — in cell, address of which is indicated in command. Result of operation remains in summator. For execution of arithmetic operations with such commands it is necessary to have yet commands, accomplishing exchange of codes between summator AU and cell MD, address of which is indicated in corresponding command.

Command of conditional transfer can be performed by various methods. Let us suppose, that has place conditional transfer by zero in summator: if in summator AU at execution of command of conditional transfer is found recorded number 0, then control is transferred to following by order command, in opposite case selection of following command is accomplished by address, indicated in command of conditional transfer. Let us suppose for simplicity, that i-th command of program will be stored in cell with address i ($i = 1, 2, \ldots$). Allocating for storage of constant of re-addressing (number, equal to unity) cell with address c, for storage of number n (dimensionality of vectors A and B) — cell with address c, and for storage of partial sum $s_k = a_1b_1 + a_2b_2 + \ldots + a_kb_k$ — cell with address s, let us come to following program:

1. send to summator from MD, $a + 1$;

2. multiplication, $b + 1$;

3. addition, s;

4. send from summator to MD, s;

5. send to summator, 1;

6. addition, c;
7. send to summator in MD, 1;
8. send to summator, 2;
9. addition, c;
10. send from summator in MD, 2;
11. send to summator, t;
12. addition, c;
13. send from summator in MD, t;
14. subtraction, t;
15. conditional transfer, 1;
16. send to summator, a;
17. stop.

Cell with address t, figuring in constructed program, represents itself so-called *program counter* of number of cycles. By commands 11, 12 and 13 is accomplished increase of content of this cell by unity. If in beginning of calculations in cell t was stored number, equal to zero, then after execution of n cycles (repetitions of group of commands 1–13) in it will be stored number equal to n. Then in result of subtracting, produced by command 14 and 15, in summator should be obtained zero, and following command of conditional transfer will cause machine to transfer control to command 17, at which machine will be stopped, and in summator will be output answer.

At zero in this content of command of conditional transfer will cause machine to transfer control to command 1, i.e. there occurs — transfer of control of program.

Pay attention to that, that in composed program commands 1, 2 and 11 are so-called *modifiable commands*. Indeed, at execution of program address in each of them should be changed at every repetition of cycle of calculations.

In first of examples considered, all addresses in commands were *absolute addresses*, i.e., in other words, each of them was directly related to some definite cell of memory. In second program such was only minority of addresses. Names $a + 1$, $a + 2$, etc. are names of addresses, expressed in form of sum of absolute address a and program counter t, which name is called *relative address*.

There can be obtained more essentially effective savings of addresses through use of additional apparatus, introduced in composition of operating device of some machines. In fact, by using (as in command of conditional transfer) operation of comparison of content of two cells, such apparatus allows to change modifiable addresses, proceeding from value of special counter in special register, named *index-register*.

Using of one index-register I in three-address system of commands of program calculation of scalar product of two vectors can be written in form:

1. addition I with comparing index-registers I_1;
2. multiplication, b_1, $a_1(I_1)$;
3. addition, s;
4. conditional transfer, I_2, 2;

5. stop.

Development of such universal algorithmic language, being at the same time convenient for man and realizable on practice by automatic programming was first in essence developed by group of American scientists, which later received name "Fortran," and others.

Development of algorithmic languages is needed not only for that, that such language facilitates programming, in the first place in terms of allowing man to be able to perceive algorithm representation in language more easy for understanding and in form more familiar for him.

Operator Schemes

With help of described symbols operator scheme of following for given example above can be written:

$$A_1A_2A_3P_1(\uparrow)A_4$$

Arithmetic operators are designated letter A, — operator of transfer — P, — operator of cycles — L, and after these designations are entered in order indexes in form of numbers.

5.4 Universal algorithmic language ALGOL-60

International algorithmic language ALGOL-60, form of which we briefly described above or ALGOL, presents itself convenient means for description method, and also for record of problems, approximating to symbolic mathematical notation. Being universal algorithmic language for record of programs, realizing computing (or otherwise) algorithms, storage in case of possessing corresponding algorithms from form, and also in introduction of changes at same time is in general form simplified in comparison with original machine approach.

ALGOL serves alphabetic letters (30 in uppercase and 30 of lower case), Arabic ciphers (from zero to digit of nine), delimiters (representing a comma, point, ten forms of brackets and others), and also of some special symbolic operations.

For representation numbers is used decimal system of calculation, in number from ciphering corresponding number is integer or also in the same approach (we call it real). Sign of the sign of plus of position of numbers or in lower case. For designation of decimals symbol (point or comma) is placed at corresponding place of number.

Numbers in ALGOL are divided by integer numbers, designated word **integer** (corresponding approach), and to real (fractional), designated word **real** (more 3.0 corresponds to type real) and to real type.

Example of type of number integer: 0; ±275; −634; −0; −1

Example of type of number real: 5.346, also −0.1, also +0.06; −37E; −32 (also: -0.37×10^{-9}); (also 6).

For provision of necessary space of using symbols (as written in programs of ALGOL-60) is used also identifiers (symbols, additional combinations). Identifiers can serve letters and combinations of letters with figures (and if to go ahead). Example of identifiers can serve `a+b+c`, `a.m.up.`, `TOP41 d.e.`, `1 to m operator`.

Besides essential, presenting whole numbers also types (like integer and real), in ALGOL-60 are used additionally Boolean type variables (**Boolean**, more precisely after Boolean algebra), representing at `true`, at representing at for designation — is letters s and t (letter).

Boolean — *logical values*, designating of components of this-that-or-at vectors for elements of this or that matrix.

Arrays

All values receiving values can figure appearing of output by A. In character of index can figure integer values of this (to only positive), possibly by identifier:

$$\textbf{array } a[m : n], p[i : k]$$

Representing values massifs, designating analogous to above massif, Boolean massif at **array** $L[0 : 3]$, **integer array** $a[-7 : 1, 0 : 1]$, and others.

Quantity of radiances in indices, characterizing dimensions of massif, is named *quantity of subscripts of massif.*

Arithmetic Expressions

Presenting arithmetic expressions approach at $c{+}2$, $2{\times}3{\times}(1{+}A)$, $B(y)(L{-}4)$, $a(j){\times}A(j) = 1, \ldots$ also, $(i \div 4, j(j) - 1)/(j - \ldots\ldots)$.

In approach for specific cases belonging operators serve for identifiers and also for identification of massifs, at use of arithmetic expressions calculation value by approach of all approach belonging.

Functions

All values, obtaining, to also coefficient approaches of operators by massif and also in coefficient approach by belonging to identification.

Description of *procedure* in approach as approach of form. Language of ALGOL allows to describe operations, which also can be given on Russian language. At use of expression in ALGOL as use gives its value.

Example of function work procedure: Let (x, y) **at** AB (1.5) *plus*: accelerated.

Same function is marked at is same approach types: **real procedure** $sin(x)$; **integer procedure** ALK, **Boolean procedure** $ATU0$.

Boolean Expressions

Values approach type structure at elements representing, above condition at for at is construction of as basis, presented and at functions (procedure) type **Boolean**.

In description construction of symbols at for at at $R \vee B$, operator construction of symbols represents for expressions at $A \wedge B$, $A \vee B$, $B = B$, $\neg R$, $R \wedge B$.

Example of Boolean expression: $s < 5 \vee y \times y/s/s \times v/y/s$ at $(\neg s)$.

Conditional Expressions

Corresponding approach construction appears as:

$$\textbf{if } G \textbf{ then } A \textbf{ else } B$$

Examples of Operator Expressions

Examples of operator expressions: $A := a[10]$; $n := n + 1$; p; $m := n$; $m := 1$; $B := a < b$; $q[1]$; $z := 5 - 3 \times t - 4$.

To implement an operator expression, the computing machine must perform a strictly ordered sequence of actions in the following order. First, all index expressions are calculated (in the case of array variables), the designation of the operator is calculated, after which the assignment operator is executed in the usual way in case of independent expressions on the right side. After calculation of a simple expression on the right, the resulting value is written to the variable on

the left side and the calculation of that expression terminates. Then the operator formula is evaluated in succession. At this point, the operator is: $A := B := p$ should be calculated as $B := p$, and then $A := B$.

Operators in ALGOL

Operators in ALGOL may also be combined. Method of distinguishing operators through full stops. Operations should be split into several parts, separated one from another, or one from another by a semicolon, comma, etc.

The overall structure in ALGOL is similar to the placement of operators one after another in the order which they are set. The addition of simple operators constructs an ordered sequence of operators. In simple cases an operator is separated by a semicolon.

If the operator is located after the word **do**, it is essentially a value-label or key-marker.

For example: **switch** $L := L, M, P$ (true L, M, P — metka).

Cycle Operators

Of greater value is understanding operators that are used in ALGOL language, designated as the initial operator (or else groups of calculating operators), which are used to construct operations. The empty statement serves as an identifier (in particular). After similar designation for the described identifier receiving, the main word **for**.

Example of cycle:

$$\textbf{for } i := 1.5 \textbf{ step } d \textbf{ until } 12; t(i); 1.03 \textbf{ step } .03 \textbf{ until } 1.3$$

In ALGOL it is accepted for two types of constructions of cycles. The first of these is connected with the use of service words **step** (step) and **until** (so long as) and has the following form: V **step** e, at the time V, e and t — arithmetic expressions. The identifier V serves for designation of the same index of the cycle, at the second step — the same arithmetic expression.

Example:

$$\textbf{for } i := -12.5 \textbf{ step } 1 \textbf{ until } 0,5 \textbf{ until } 0$$

Blocks

In the character of operator words words are used by the service words **begin** (start) and **end** (end), also, in receiving operator construction starting:

$$\textbf{begin } A_1, A_2, \ldots, A_n, \textbf{ end}$$

Along with ordinary operators, in ALGOL is used block description.

The designation at receiving two at blocks A; index $i = -1$; $\in$ **end**.

Conditional Operators

The operator can also be built according to the description of conditional operators and following those unconditional operators, which are executed in the cases when the conditions are not met. The construction is as follows.

Example: **if** B **then** A **else** A_0 — unconditional operator (not preceded by unconditional operator).

Example: **if** $a > 0$ **then** A **else if** $a < 0$ **then** A_1 **else** A_2

The actual meaning of conditional operators:

$$\textbf{if then } A_1 \textbf{ else } A_a$$

At B — a logical Boolean expression; A_1 — unconditional operator, A_2 — an arbitrary operator.

Procedures

The most significant element of the ALGOL language is the operator designation of procedure. Procedures allow significant reductions in the writing of computational operators, with the designated identification of any procedures, when using the designation of the procedure.

Description of procedure is noted also at this type at the formalized values.

Example: **real procedure** $sin(a)$.

Types **real** (real), at second — calculation receiving of types (procedure), designating at same operator at at same types at at procedure. **integer**. At receiving at at identification of same values at at type.

ALGOL-procedures SMALGOL at and blocks, is at calculating at at operation-group at word **begin** and at calculation at at word **end**. Commentary at begins at at same at at elements at at keyword **comment** (commentary).

Constant Elements and Switch Descriptions

May be constant. List elements of switches in descriptions of switches may only be labels, not arbitrary name-expressions.

Procedure descriptions, called in any block, must be made after description of types, switches, and arrays of the corresponding block. Identifiers of the procedure can appear inside the procedure only in that case, when they are left parts of corresponding assignment operators. There exist also some other restrictions.

Note, that any program, written in SMALGOL, can be viewed also as an "algol-type" program. The reverse, generally speaking, is not true.

5.5 Examples of Programming in ALGOL-60 Language

Let us consider first the simplest example, which already appeared in § 3 of this chapter as illustration of principles of programming in machine languages. We are speaking of calculating the value of sum $\sum_{k=1}^{m} \frac{1}{k^2}$. The corresponding "algol-type" program can be written in the form:

```
begin real s; integer m, k;
    read (m); s := 0;
    for k := 1 step 1 until m do
        s := s + 1/k↑2;
    punch (s)
end.
```

Procedures $read(m)$ and $punch(s)$ provide correspondingly input of necessary information (upper limit of summation) and output of result, i.e. values of the sought sum. It is easy to see, that the program written in ALGOL is much more clear and understandable than the one written in § 3 as a machine program, which solves the same problem.

Quite transparently and clearly can also be written programs of other examples considered in § 3. Calculation of scalar product of two (real) vectors $(a_1, a_2, \ldots, a_n)$ and $(b_1, b_2, \ldots, b_n)$ is presented in the form:

```
begin integer n; read (n);
    begin real s; integer i; real array a[1 : n], b [1 : n];
        read (a); read (b); s := 0;
        for i := 1 step 1 until n do
            s := s + a [i] × b [i];
        punch (s)
    end
end.
```

Multiplication of vector $(b_1, b_2, \ldots, b_n)$ by matrix $\|A_{ik}\|$ in ALGOL can be represented by the program:

```
begin integer n; read (n);
    begin integer i, k; real array s[1:n], b[1:n], A[1:n, 1:n];
        read (b); read (A);
        for k := 1 step 1 until n do
        begin s[k] := 0;
            for i := 1 step 1 until n do
                s[k] := s[k] + b[i] × A[i, k];
        end
        punch (s);
    end
end.
```

In this program one cycle operator enters into another. Internal operator brackets are introduced, since in the first (outer) cycle it is necessary to execute a sequence consisting of two operators.

Two phrases written at the end of the program represent a commentary, which does not factually enter into the program and is not perceived by the translator (programming program).

Note that the ALGOL language is a universal algorithmic language and is therefore suitable for writing any algorithms. Besides that, as noted above, all programs written in ALGOL can be realized (given the availability of sufficiently large memory) on any universal electronic digital machine.

Let us use the last circumstance for illustration of the fact that universal electronic digital machines can execute not only ordinary algorithms, but also algorithms with random transitions and *any self-organizing* systems of algorithms.

To obtain the possibility of building in ALGOL any random algorithms, it is sufficient to introduce into it a special procedure, which we will denote as $random(a, b)$. At each call to this procedure it forms some random number belonging to the interval $[a, b]$. At this it is assumed that the selection is carried out on the basis of uniform distribution law, according to which all numbers of the indicated interval are considered equally probable. The random numbers themselves are assumed to be produced by type **integer** or **real** depending on the type to which the assigned formal parameters (boundaries of the interval) a, b belong.

For this procedure randomization is used in a very wide range of problems. We can, in particular, note that it is required for the execution of a random selection. In the case of a random electric digital machine, random numbers are produced by a corresponding separate device.

From a wide range of randomization of results, in particular, in cybernetics we have the characteristic so-called *pseudo-random sequences*.

Self-Organizing Control Algorithm

This same description of such typical self-organizing system, consisting in realization on the method of the procedure control algorithm (p). This same description of such procedure is algorithm, based on the same method of calculating its type (p). This same description of value procedure represents itself the control function ck/n of a neuron of devices controlling the process, whose values in the form of corresponding array $B[1 : m]$ are periodically entered into the algorithm.

Parameters constituting the array B (control results) change as a consequence of change of controlling effects (array A), as well as due to other reasons related to the controlled object and not depending on the control algorithm. The reasons which are discussed here relate to change of some non-regulated parameters, wherein the character of this change is not known in advance to the controlling algorithm. It is easy to understand that the described controlling algorithm

performs extremal regulation (by criterion f), the quality of which will be better the smaller the ratio of time for finding the algorithm of optimal controlling effects (array A) to the average time during which noticeable change of non-regulated parameters occurs. It is not difficult to verify that the controlling algorithm we are discussing can be described in ALGOL language by the following program:

```
begin integer i, j, k; real y, s;
    B[1:m], P[1:n];
    L: read (B); y := f(B); s := 0;
    for i := 1 step 1 until n do
    begin A[i] := A[i] + d;
        punch (A); read (B);
        P[i] := (f(B) - y)/d;
        s := s + P[i]↑2;
        A[i] := A[i] - d
    end;
    r := d/sqrt(s);
    for j := 1 step 1 until n do
        A[i] := r × P[i] + A[i];
    punch (A); read (B);
    if f(B) > l then go to L else
    for k := 1 step 1 until n do
        A[i] := A[i] - r × P[i];
    punch (A);
    go to L
end.
```

In the constructed program, the value d represents the step of the steepest descent, and the value l — the precision of achieving the minimum value of criterion f. Function $sqrt(s)$ is equal to the square root from s, taken with plus sign. Array $P[1:n]$ gives the relative values of optimal increments of controlling effects $A[1:n]$ at each step of the steepest descent process. It is assumed that values d, l, substance procedures $f(B)$ and $sqrt(s)$, and initial values of array components $A[1:n]$ were introduced earlier (prior to command with label L) into the algorithm.

Perceptron Algorithm

Let us now consider the algorithm performing the work of some discrete α-perceptron P. Let us assume that perceptron P has a retina consisting of N receptors, and is designed for recognition of two images. A-elements are $(1, 1, 1)$ - neurons, the encouragement constant equals one, and the penalty constant — zero. The image projected onto the retina is represented by some Boolean array $r[1:N]$, which is read externally for display to the perceptron of each new image. Additionally, a Boolean value a is considered, representing a signal about correctness (truth) or incorrectness (falsity) of the perceptron's answer p. Answer p is simply the image number to which the perceptron assigned the next shown image. Through sf and ss we denote output signals of summators of the first and second images.

Let us assume further that the number of neurons in both the first and second image equals n. Through $xf[i]$ and $yf[i]$ we denote numbers of receptors of the retina to which are connected correspondingly the excitatory and inhibitory inputs of i-th neuron of the first image, through $xs[i]$ and $ys[i]$ the corresponding receptor numbers for i-th neuron of the second image, and $vf[i]$ and $vs[i]$ — weights of i-th neurons of the first and second images ($i = 1, 2, \ldots, n$). Given the adopted assumptions, the algorithm performing the work of perceptron P (in learning mode) can be written in the form:

```
begin integer p, i, j, k; real sf, ss; Boolean a;
    Boolean array r[1:N];
    L: read (r); sf := 0; ss := 0;
```

```
    for i := 1 step 1 until n do
    begin if r[xf[i]] ∧ ¬r[yf[i]] then
        sf := sf + vf[i];
        if r[xs[i]] ∧ ¬r[ys[i]] then
            ss := ss + vs[i]
    end;
    if sf > ss then p := 1;
    if sf < ss then p := 2;
    if sf = ss then go to L;
    punch (p); read (a);
    if a ∧ (p = 1) then for j := 1 step 1 until n do
        if r[xf[j]] ∧ ¬r[yf[j]] then vf[j] := vf[j] + 1;
    if a ∧ (p = 2) then for k := 1 step 1 until n do
        if r[xs[k]] ∧ ¬r[ys[k]] then vs[k] := vs[k] + 1;
    go to L
end.
```

It is assumed that arrays $xf[1:n]$, $yf[1:n]$, $xs[1:n]$, $ys[1:n]$, $vf[1:n]$ and $vs[1:n]$ are introduced into the program in advance, and the last two arrays (weights of neurons of the first and second images) consist of only zeros. Otherwise the summators of images would constantly give zero signals (sf and ss), and since in the program it is accepted that when signals of summators are equal the perceptron does not give any signal p, the learning process (and, in general, any weight changes) would be absent.

From the last restriction it is possible to get rid of, if the teacher not simply gives a signal of approval, but reports to the perceptron the true image number to which belongs the next shown image. Precisely this method of perceptron functioning in learning mode was considered in the previous chapter. Let us indicate the changes in the described above program that should be made in relation to the new type of signal a.

In description, value a should be declared as value of type **integer**, and not **Boolean**. Changes in the program can be reduced to the following. After operator **if** $sf < ss$ **then** $p := 2$ instead of operator **if** $sf = ss$ **then go to** L it is necessary to put operator **if** $sf \neq ss$ **then** $punch(p)$. Then in conditional operators following after operator $read(a)$, condition **if** $a \wedge (p = 1)$, **if** $a \wedge (p = 2)$ should be replaced by conditions **if** $a = 1$ and **if** $a = 2$ correspondingly.

It is not difficult to describe also those changes in the original perceptron program that should be made in order to model not learning mode, but self-learning mode of the perceptron. For this value a is completely excluded from the program together with the corresponding operator $read(a)$. In subsequent conditional operators to conditions standing after service words **do** should be added members $\wedge(sf > ss)$ and $\wedge(sf < ss)$ correspondingly.

Thus, both learning mode and self-learning mode of α-perceptron can be easily modeled in ALGOL language, and consequently, on universal electronic digital machines of various types. The same can be said about the possibility of modeling in ALGOL language any other machine learning and generalization construction schemes presented above.

Evolutionary Algorithm

Let us consider a more complex example. In ALGOL language one can also describe one of the simplest evolutionary algorithms and simulation of biological evolution and image formation. The model was created (more precisely, tested experimentally on universal electronic digital machine by A.L. Lerner.

Let us consider some discrete space of states, consisting of n-state machines (automata), each of which can find itself in one of $H = 1 + n + 1$ possible states. Numbering for simplicity this set of states by non-negative integers. First — non-negative integer representing itself a point of this n-cube (where each coordinate ranging from 0 to $H - 1$), i.e. consisting of n values, each of which takes $H = H - 1 + 1$ for i (starting from $i = 1$ and ending at $i = n$).

The algorithm described by us in one cycle of operation should observe all points of our space, making in them the listed above changes. Having completed the next cycle, the algorithm should read new values of all components of array $F[1:n]$ and proceed to execution of the following cycle. We will count the number of cycles with help of special value t. Upon achieving by this value the fixed in advance value p, the algorithm should terminate its work.

To facilitate programming of the described algorithm in ALGOL language, let us introduce three blocks describing the process of moving the automaton located at i-th point, the process of its "death," and the process of its "reproduction." Let us denote for brevity these blocks through $\mathfrak{B}_1$, $\mathfrak{B}_2$ and $\mathfrak{B}_3$ correspondingly and write for each of them the corresponding program in ALGOL.

Block $\mathfrak{B}_1$:

```
begin integer m, j, bs, fs, f, bf, ff;
    m := M[i, s[i], s[bi], s[fi], F[i], F[bi], F[fi]];
    pi := if i + m > n then 1 else i + m;
    if s[pi] ≠ 0 then pi := i comment pi is number of point,
        to which moves the considered automaton;
    L[pi] := L[i] + 1;
    H[pi] := if F[pi] = 0 then H[i] + 1 else if H[i] ≠ 0
        then H[i] - 1 else 0;
    if pi ≠ i then
        for j := 1 step 1 until k do
        for bs := 0 step 1 until k do
        for fs := 0 step 1 until k do
        for f := 0,1 do for bf := 0,1 do for ff := 0.1 do
        begin SP[pi, j, bs, fs, f, bf, ff];
            M[pi, j, bs, fs, f, bf, ff] := M[i, j, bs, fs, f, bf, ff]
        end;
    s[pi] := SP[i, s[i], s[bi], s[fi], F[i], F[bi], F[fi]]
end.
```

Block $\mathfrak{B}_1$ performs movement of automaton from point i to point pi, transition of it to a new state (determined by situation at moment of automaton presence in point i), change of readings of "life" and "hunger" counters, and rewriting of arrays defining functions of transitions and outputs of automata, with the goal of bringing them into correspondence with the new location of the considered automaton. Upon exit from the block, values i and pi are preserved.

Block $\mathfrak{B}_2$:

```
begin s[pi] := 0 end.
```

Note that the program will be built by us in such a way, that the values $L[pi]$ and $H[pi]$ preserved after death of automaton at point pi, as well as values of corresponding components of arrays SP and M, could not lead to errors in the future. This is achieved due to the fact that when the program is repeated, the enumerated values, before being used, are defined anew, since they will necessarily end up in left parts of corresponding assignment operators.

Block "reproduction" $\mathfrak{B}_3$:

```
begin integer rj, rbs, rfs, rf, rbf, rff, j, bs, fs, f, bf, ff;
    Boolean B;
    rj := random (1, k);
    rbs := random (0, k);
    rfs := random (0, k);
    rf := random (0, 1);
    rbf := random (0, 1);
    rff := random (0,1);
    for j := 1 step 1 until k do
    for bs := 0 step 1 until k do
```

```
    for fs := 0 step 1 until k do
    for f := 0,1 do for bf := 0,1 do for ff := 0.1 do
    begin B := j = rj ∧ bs = rbs ∧ fs = rfs ∧ f = rf ∧ bf = rbf ∧ ff =
        rff;
        SP[i, j, bs, fs, f, bf, ff] := if B then random (1, k)
            else SP[pi, j, bs, fs, f, bf, ff];
        M[i, j, bs, fs, f, bf, ff] := if B then random (-1, 1)
            else M[pi, j, bs, fs, f, bf, ff]
    end
end.
```

The entire program for modeling the evolution process is presented now in the following form:

```
begin integer t, i, bi, fi, p, q, pi;
    integer array F[1:n], S[1:n], L[1:n], H[1:n],
        SP[1:n, 1:k, 0:k, 0:k, 0:1, 0:1, 0:1], M[1:n, 1:k, 0:k,
        0:k, 0:1, 0:1, 0:1];
    for q := 1 step 1 until n do
        L[q] := H[q] := 0;
    t := 0; i := 1; read (S); read (SP); read (M);
    Q: read (F); fi := if i ≠ n then i + 1 else 1;
    if S[i] = 0 then begin i := fi; go to P end;
    bi := if i ≠ 1 then i - 1 else n;
    | Block 𝔅1 |;
    if L[pi] > l ∨ H[pi] > h then
        | Block 𝔅2 |;
    if pi ≠ i ∧ H[pi] < hu ∧ L[pi] < lu ∧ L[pi] > ll then
        | Block 𝔅3 |;
    if pi ≠ fi then i := fi else i := if fi ≠ n then fi + 1 else 1;
    P: if i = 1 ∨ pi = 1 then t := t + 1; if t ≠ p then go to Q
end.
```

Note that the program we constructed is not economical from the point of view of memory expenditure and necessity of rewriting multidimensional arrays. It is possible to achieve much more economical program construction if we introduce automaton numbering and use in arrays L, H, SP and M instead of point number of space the number of corresponding automaton.

In real modeling of the evolutionary process on universal electronic digital machine in work [43], a program with more limited capabilities was used, and nevertheless, the conducted experiments showed that even under these conditions the quality of modeling was quite satisfactory. For relatively simple "laws of nature," the process of automata adaptation to surrounding environment and formation of stable "species" were observed through several tens of thousands of cycles of algorithm operation and change of corresponding number of "generations". Initially the transition tables and outputs of automata (arrays M and SP in our case) were given arbitrarily. In the process of evolution, "extinction" of poorly adapted automata and emergence of forms more adapted for "life" under given conditions occurred.

Chapter 6

Predicate Calculus and the Problem of Automation of Processes of Scientific Creativity

6.1 Basic Concepts of Predicate Calculus

As was noted in Chapter II, the simplest component part of mathematical logic—propositional calculus—does not penetrate in essence into the structure of elementary statements, limiting thereby its possibilities in formalization of any complex thought processes. Much more powerful expressive means are possessed by the following, more complex level of mathematical logic, called the *narrow predicate calculus*, or *first-order predicate calculus*.

The peculiarity of predicate calculus is primarily the fact that, along with propositional variables taking only two possible values ("true" and "false"), so-called *subject variables* are introduced into consideration, running through some, generally speaking, infinite domain of values, which is customary to call the *subject domain*. The values constituting this domain of values are usually called *subjects*, or *objects*.

Fixing this or that subject domain, we obtain the possibility to construct *propositional functions* of subject variables, usually called *predicates*: n-place predicate $P(x_1, x_2, \ldots, x_n)$ represents a variable statement, whose truth or falsity is determined by sets of values of subject variables $x_1, x_2, \ldots, x_n$. If predicate P is not *identically true* or *identically false*, then on some sets of values of subject variables it takes the value "true", and on others—the value "false".

In classical theory, predicates with predicates (or properties) were called only single-place predicates. For multi-place predicates, a special term "*relation*" was used: two-place predicates were called *binary relations*, three-place—*ternary relations*, and so on. For our purposes it is unnecessary to adhere to specialized narrow terminology for this reason, so we will henceforth call functions of indicated type predicates, be they single-place or multi-place.

The use of predicates makes it possible to construct formulas describing (to a degree) the internal structure of elementary statements. For example, the natural language statement "all cats are mammals" can be expressed in the following way: if some element of subject domain belongs to the class of cats, then this element also belongs to the class of mammals. For this statement to be true, it should apply not to this or that particular individual, but the statement must be *universal*.

6.1.1 Quantifiers

Expression $\exists x(P(x))$ represents itself the given condition at designation for some object x, for which predicate $P(x)$ is satisfied. The symbol $\exists$ is called the *existential quantifier* and is read "there exists."

If domain M consists of finite number of objects $a_1, a_2, \ldots, a_n$, expression $\exists x(P(x))$ represents the formula:

$$P(a_1) \vee P(a_2) \vee \cdots \vee P(a_n)$$

Similarly, the *universal quantifier* $\forall$ is used to express statements of the form "for all x." If domain M consists of finite number of objects $a_1, a_2, \ldots, a_n$, expression $\forall x(P(x))$ represents:

$$P(a_1) \wedge P(a_2) \wedge \cdots \wedge P(a_n)$$

6.1.2 Free and Bound Variables

In predicate calculus, variables can be either *free* or *bound*. A variable is bound when it falls within the scope of a quantifier; otherwise it is free. For example, in the formula $\forall x_1 \exists x_2(P(x_1) \supset Q(x_1, x_2))$, the variables x_1 and x_2 are bound by their respective quantifiers.

6.1.3 Axioms of Predicate Calculus

Formulas for predicate calculus, which receive numbers from 12 to 15 (continuing from the axioms of propositional calculus), are written as:

Axiom 6.1.1 (12)**.** $\forall x \Phi(x) \supset \Phi(y)$

Axiom 6.1.2 (13)**.** $\Phi(y) \supset \exists x \Phi(x)$

Axiom 6.1.3 (14)**.** $\forall x(P \supset Q(x)) \supset (P \supset \forall x Q(x))$

Axiom 6.1.4 (15)**.** $\forall x(P(x) \supset Q) \supset (\exists x P(x) \supset Q)$

6.1.4 Derivation Rules

From axioms 12–15 the following derivability rules are easily derived:

Introduction of universal quantifier ($\forall$-introduction):

$$A(x) \vdash \forall x A(x) \tag{115}$$

Introduction of existential quantifier ($\exists$-introduction):

$$A(t) \vdash \exists x A(x) \tag{116}$$

Elimination of universal quantifier ($\forall$-elimination):

$$\forall x A(x) \vdash A(t) \tag{117}$$

Theorem 6.1.1 (Deduction Theorem for Predicate Calculus)**.** *If derivability* $\Gamma, A \vdash B$ *takes place, wherein in the derivation process the free variables entering into formula* A *remain* fixed*, then derivability* $\Gamma \vdash A \supset B$ *takes place.*

6.1.5 Important Relations

Using the equivalence symbol $\sim$ in the same sense as in propositional calculus, one can easily establish the following relations:

$$\vdash \forall x A \sim A, \quad \vdash \exists x A \sim A \tag{119}$$
$$\vdash \forall x \forall y P(x, y) \sim \forall y \forall x P(x, y) \tag{120}$$
$$\vdash \exists x \exists y P(x, y) \sim \exists y \exists x P(x, y) \tag{121}$$
$$\vdash \forall x P(x) \supset \exists x P(x) \tag{122}$$
$$\vdash \exists x \forall y P(x, y) \supset \forall y \exists x P(x, y) \tag{123}$$

6.1.6 Normal Forms

Theorem 6.1.2 (Prenex Normal Form)**.** *For any formula B (closed) of narrow predicate calculus, there is derivable an analogous formula B' existing in prenex normal form.*

The formulated theorem derives easily from the following proven relations:

$$\vdash \neg\forall x P(x) \sim \exists x \neg P(x) \tag{124}$$
$$\vdash \neg\exists x P(x) \sim \forall x \neg P(x) \tag{125}$$
$$\vdash Q \vee \forall x A(x) \sim \forall x (A(x) \vee Q) \tag{126}$$
$$\vdash Q \wedge \exists x A(x) \sim \exists x (A(x) \wedge Q) \tag{127}$$

Theorem 6.1.3 (Skolem Normal Form)**.** *For every formula (closed) its satisfiability is equivalent to satisfiability of its formula recorded in* Skolem normal form.

6.2 Formal Arithmetic and Gödel's Theorem

On the basis of narrow predicate calculus one can build construction of formal arithmetic. Historically, with constructing of formal arithmetic, using the sequence of natural numbers $0, 1, 2, 3, \ldots$. We indicate the specific arithmetic operations of successor and multiplication, and also the arithmetic relation of equality.

6.2.1 Axioms of Formal Arithmetic

Supplementation of axiom system of (narrow) predicate calculus (axioms 1–15) by specifically arithmetic axioms:

Axiom 6.2.1 (16 – Axiom of Mathematical Induction)**.**

$$P(0) \wedge \forall x((P(x) \supset P(x')) \supset P(x))$$

Axiom 6.2.2 (17)**.** $a' = b' \supset a = b$

Axiom 6.2.3 (18)**.** $\neg(a' = 0)$

Axiom 6.2.4 (19)**.** $a = b \supset (a = c \supset b = c)$

Axiom 6.2.5 (20)**.** $a = b \supset (a' = b')$

Axiom 6.2.6 (21)**.** $a + 0 = a$

Axiom 6.2.7 (22)**.** $a + b' = (a + b)'$

Axiom 6.2.8 (23)**.** $a \cdot 0 = 0$

Axiom 6.2.9 (24)**.** $a \cdot b' = a \cdot b + a$

For proper understanding of the written relations, it is necessary to note that for economy of parentheses in formulas, we construct the following order of precedence of operations: all arithmetic operations are senior relative to equality, and the last is senior than all logical operations.

6.2.2 Derivable Relations

With help of written axioms, one can strictly formally establish such laws of arithmetic as commutative and associative laws for addition and multiplication, distributive law for multiplication relative to addition, etc. One can prove:

$$\vdash a + 1 = a'$$
$$\vdash a + b = 0 \supset a = 0 \wedge b = 0$$
$$\vdash a \cdot b = 0 \supset a = 0 \vee b = 0$$

6.2.3 Proof by Induction

Theorem 6.2.1 (Induction Rule)**.** *Let* Γ *be some set of formulas of (formal) arithmetic, not containing variable* x *as a free variable, and* $P(x)$ *be a formula containing* x *as a free variable. Then, if* $\Gamma \vdash P(0)$ *and* $\Gamma, P(x) \vdash P(x')$*, then* $\Gamma \vdash P(x)$*.*

6.2.4 Provability, Disprovability, and Undecidability

All formulas of formal arithmetic can be divided into three classes:

- **Provable formulas** (derivable)
- **Disprovable formulas** (whose negation is derivable from the axioms)
- **Undecidable formulas**

Definition 6.2.1. *An axiom system is called* non-contradictory *(consistent) if there exists no formula* B *which is both derivable and disprovable.*

Definition 6.2.2. *An axiom system is called* incomplete *if there exists a formula* B *which is neither derivable nor disprovable.*

6.2.5 Gödel's Incompleteness Theorems

Theorem 6.2.2 (Gödel's First Incompleteness Theorem)**.** *If formal arithmetic is non-contradictory (consistent), then there exists a formula that is undecidable—it can be neither proved nor disproved within the system.*

Theorem 6.2.3 (Gödel's Second Incompleteness Theorem)**.** *If formal arithmetic system* S *is consistent, then the consistency of* S *cannot be proved within* S *itself.*

Theorem 6.2.4 (Incompleteness of Formal Arithmetic)**.** *Formal arithmetic is incomplete: the formula system containing all axioms 1–24 has formulas that are neither formally derivable nor disprovable.*

6.3 Automation of Provability and Construction of Deductive Theories

6.3.1 Gentzen's System

One of the main points determining provability of formulas is the search method described by *Gentzen* in his calculus of sequents.

A sequent has the form:

$$\mathfrak{A}_1, \mathfrak{A}_2, \ldots, \mathfrak{A}_m \to \mathfrak{B}_1, \mathfrak{B}_2, \ldots, \mathfrak{B}_n$$

where $\mathfrak{A}_i$ and $\mathfrak{B}_i$ are formulas.

Sequent $\mathfrak{A}_1, \mathfrak{A}_2, \ldots, \mathfrak{A}_m \to \mathfrak{B}_1, \mathfrak{B}_2, \ldots, \mathfrak{B}_n$ has the same interpretation as formula:

$$\mathfrak{A}_1 \wedge \mathfrak{A}_2 \wedge \cdots \wedge \mathfrak{A}_m \supset \mathfrak{B}_1 \vee \mathfrak{B}_2 \vee \cdots \vee \mathfrak{B}_n$$

The part of sequent standing to the left of $\to$ is called *antecedent*, and the part to the right is called *succedent*.

6.3.2 Axiom and Derivation Rules of System G1

In Gentzen system $G1$ there exists a unique axiom:

$$C \to C \tag{130}$$

Derivation Rules for Propositional Calculus

$\supset$-introduction in succedent:

$$\frac{A, \Gamma \to \Theta, B}{\Gamma \to \Theta, A \supset B} \tag{131}$$

$\supset$-introduction in antecedent:

$$\frac{\Delta \to \Lambda, A \quad B, \Gamma \to \Theta}{A \supset B, \Delta, \Gamma \to \Lambda, \Theta} \tag{132}$$

$\wedge$-introduction in succedent:

$$\frac{\Gamma \to \Theta, A \quad \Gamma \to \Theta, B}{\Gamma \to \Theta, A \wedge B} \tag{133}$$

$\vee$-introduction in antecedent:

$$\frac{A, \Gamma \to \Theta \quad B, \Gamma \to \Theta}{A \vee B, \Gamma \to \Theta} \tag{136}$$

$\neg$-introduction in succedent:

$$\frac{A, \Gamma \to \Theta}{\Gamma \to \Theta, \neg A} \tag{137}$$

$\neg$-introduction in antecedent:

$$\frac{\Gamma \to \Theta, A}{\neg A, \Gamma \to \Theta} \tag{138}$$

Additional Derivation Rules for Predicate Calculus

$\forall$-introduction in succedent:

$$\frac{\Gamma \to \Theta, A(b)}{\Gamma \to \Theta, \forall x A(x)} \tag{139}$$

$\forall$-introduction in antecedent:

$$\frac{A(t), \Gamma \to \Theta}{\forall x A(x), \Gamma \to \Theta} \tag{140}$$

$\exists$-introduction in succedent:

$$\frac{\Gamma \to \Theta, A(t)}{\Gamma \to \Theta, \exists x A(x)} \tag{141}$$

$\exists$-introduction in antecedent:

$$\frac{A(b), \Gamma \to \Theta}{\exists x A(x), \Gamma \to \Theta} \tag{142}$$

Structural Derivation Rules

Thinning:

$$\frac{\Gamma \to \Theta}{\Gamma \to \Theta, C} \quad \frac{\Gamma \to \Theta}{C, \Gamma \to \Theta} \tag{143–144}$$

Contraction:

$$\frac{\Gamma \to \Theta, C, C}{\Gamma \to \Theta, C} \quad \frac{C, C, \Gamma \to \Theta}{C, \Gamma \to \Theta} \tag{145–146}$$

Cut:

$$\frac{\Delta \to \Lambda, C \quad C, \Gamma \to \Theta}{\Delta, \Gamma \to \Lambda, \Theta} \tag{149}$$

6.3.3 Equivalence of Gentzen and Hilbert Systems

Theorem 6.3.1 (Equivalence Theorem)**.** *If some formula A is derivable from conjunction of formulas Γ in the Hilbertian system H, then formula A is also derivable in system $G1$.*

Theorem 6.3.2 (Cut Elimination—Gentzen's Hauptsatz)**.** *If in system $G1$ some sequent is provable, then it is also provable without application of the cut rule.*

6.3.4 Hao-Wang's Approach to Automated Theorem Proving

Hao-Wang used Gentzen's sequent-system $G1$ for automating theorems in predicate calculus with electronic digital machines.

Experimentally, Hao-Wang's results showed that with sufficiently simple organization of derivation rules, one can construct a calculating machine that is able to verify whether any formula of mathematical logic is derivable.

6.3.5 Experimental Results

The received results were impressive. In total, 350 theorems from the first chapters of "Principia Mathematica" were proved in 8.5 seconds on an IBM 704 computer.

6.3.6 Heuristic Approaches

It is necessary to understand the distinction between *verification* of theorems and *discovery* of new theorems. The methods described above are primarily verification methods.

For discovery of new theorems, heuristic approaches combining algorithmic and goal-directed search are being developed. These approaches may lead to systems capable of automating significant portions of mathematical reasoning and scientific discovery.